Latitude 5330/Latitude 5330 2in1

Setup and Specifications

Regulatory Model: P138G/P139G
Regulatory Type: P138G002/P139G002
May 2024
Rev. A03

DELL Technologies

Notes, cautions, and warnings

NOTE: A NOTE indicates important information that helps you make better use of your product.

CAUTION: A CAUTION indicates either potential damage to hardware or loss of data and tells you how to avoid the problem.

WARNING: A WARNING indicates a potential for property damage, personal injury, or death.

© 2022-2024 Dell Inc. or its subsidiaries. All rights reserved. Dell Technologies, Dell, and other trademarks are trademarks of Dell Inc. or its subsidiaries. Other trademarks may be trademarks of their respective owners.

Contents

Chapter 1: Set up your Latitude 5330 5

Chapter 2: Views of Latitude 5330 7

Right 7
Left 7
Top 8
Display 9
Bottom 10
Service Tag 10
Modes 11
Battery charge and status light 13

Chapter 3: Specifications of Latitude 5330 14

Dimensions and weight 14
Processor 14
Chipset 15
Operating system 15
Memory 15
External ports 16
Internal slots 16
Wireless module 16
WWAN module 17
Audio 17
Storage 18
Media-card reader 19
Keyboard 19
Camera 20
Clickpad 20
Power adapter 21
Battery 21
Display 23
Fingerprint reader (optional) 24
Sensor 24
GPU—Integrated 25
Hardware security 25
Smart-card reader 25
Contactless smart-card reader 25
Contacted smart-card reader 27
Operating and storage environment 28

Chapter 4: ComfortView Plus 29

Chapter 5: Using the privacy shutter 30

Chapter 6: Dell Optimizer..... 31

Chapter 7: Keyboard shortcuts of Latitude 5330..... 32


Chapter 8: Getting help and contacting Dell Technologies.....34

1

Set up your Latitude 5330

NOTE: The images in this document may differ from your computer depending on the configuration you ordered.

1. Connect the power adapter and press the power button.



NOTE: To conserve battery power, the battery might enter power saving mode. Connect the power adapter and press the power button to turn on the computer.

2. Finish operating system setup.

   For Ubuntu:

   Follow the on-screen instructions to complete the setup. For more information about installing and configuring Ubuntu, search in the Knowledge Base Resource at Dell Support Site.

   For Windows:

   Follow the on-screen instructions to complete the setup. When setting up, Dell Technologies recommends that you:

   - Connect to a network for Windows updates.

     NOTE: If connecting to a secured wireless network, enter the password for the wireless network access when prompted.

   - If connected to the Internet, sign-in with or create a Microsoft account. If not connected to the Internet, create an offline account.
   - On the **Support and Protection** screen, enter your contact details.

3. Locate and use Dell apps from the Windows Start menu—Recommended.

Table 1. Locate Dell apps

Resources	Description
	**Dell Product Registration** Register your computer with Dell.
	**Dell Help & Support** Access help and support for your computer.
	**SupportAssist** SupportAssist is the smart technology that keeps your computer running at its best by optimizing settings, detecting issues, removing viruses and notifies when you need to make system updates. SupportAssist proactively checks the health of your system's hardware and software. When an issue is detected, the necessary system state information is sent to Dell to begin troubleshooting. SupportAssist is preinstalled on most of the Dell devices running Windows operating system. For more information, see SupportAssist for Home PCs User's Guide on Serviceability Tools at the Dell Support Site. **NOTE:** In SupportAssist, click the warranty expiry date to renew or upgrade your warranty.
	**Dell Update** Updates your computer with critical fixes and latest device drivers as they become available. For more information about using Dell Update, search in the Knowledge Base Resource at Dell Support Site.
	**Dell Digital Delivery** Download software applications, which are purchased but not preinstalled on your computer. For more information about using Dell Digital Delivery, search in the Knowledge Base Resource at Dell Support Site.

2

Views of Latitude 5330

Right




1. microSIM-card slot
2. Universal audio port
3. USB 3.2 Gen 1 port with PowerShare
4. HDMI 2.0 port
5. Wedge-shaped lock slot

Left



1. Thunderbolt 4 port with DisplayPort Alt Mode/USB Type-C/USB4/Power Delivery
2. Thunderbolt 4 port with DisplayPort Alt Mode/USB Type-C/USB4/Power Delivery
3. USB 3.2 Gen 1 port
4. microSD-card slot
5. Smart-card reader slot (optional)

Top



1. Power button with fingerprint reader (optional)
2. Keyboard
3. NFC/Contactless smart card reader (optional)
4. Clickpad

1. **Touchpad**

   Move your finger on the touchpad to move the mouse pointer. Tap to left-click and two fingers tap to right-click.

2. **Left-click area**

   Press to left-click.

3. **Right-click area**

   Press to right-click.


4. **Power button**

   Press to turn on the computer if it is turned off, in sleep state, or in hibernate state.

   When the computer is turned on, press the power button to put the computer into sleep state; press and hold the power button for 10 seconds to force shut-down the computer.


   NOTE: You can customize the power-button behavior in Windows. For more information, see *Me and My Dell* at Dell Support Mannuals.

Display



1. Dual array microphone
2. IR emitter/Ambient Light Sensor (ALS) (optional)
3. Camera shutter
4. HD RGB camera / FHD IR camera / FHD IR camera with Proximity Sensor (optional)
5. Camera status LED
6. LCD panel
7. Battery charge and status indicator LED/ Diagnostic LED


Bottom



1. Speaker
2. Fan vents
3. Service tag label

Service Tag

The service tag is a unique alphanumeric identifier that allows Dell service technicians to identify the hardware components in your computer and access warranty information.



Modes

The following modes are applicable for your 2-in-1 computers (optional).

Notebook



Tablet



Stand



Tent



Battery charge and status light

The following table lists the battery charge and status light behavior of your Latitude 5330.

Table 2. Battery charge and status light behavior

Power Source	LED Behavior	System Power State	Battery Charge Level
AC Adapter	Off	S0 - S5	Fully Charged
AC Adapter	Solid White	S0 - S5	< Fully Charged
Battery	Off	S0 - S5	11-100%
Battery	Solid Amber (590+/-3 nm)	S0 - S5	< 10%

- S0 (ON) - Computer is turned on.
- S4 (Hibernate) - The computer consumes the least power compared to all other sleep states. The computer is almost at an OFF state. The context data is written to a storage device so that you can resume everything from where you left, once the computer is turned on.
- S5 (OFF) - The computer is in a shutdown state.

3

Specifications of Latitude 5330

Dimensions and weight

The following table lists the height, width, depth, and weight of your Latitude 5330.

Table 3. Dimensions and weight

Description	Values
Height:	
Front height	16.92 mm (0.67 in.)
Rear height	18.43 mm (0.73 in.)
Width	305.70 mm (12.04 in.)
Depth	207.50 mm (8.17 in.)
Weight (minimum)	• Laptop: 1.20 kg (2.65 lb) • 2-in-1: 1.32 kg (2.91 lb) **NOTE:** The weight of your computer depends on the configuration ordered and manufacturing variability.

Processor

The following table lists the details of the processors that are supported in your Latitude 5330.

Table 4. Processor

Description	Option one	Option two	Option three	Option four
Processor type	12th Generation Intel Core i3-1215U	Intel vPro Essentials with 12th Gen Intel Core i5-1235U	Intel vPro Enterprise with 12th Gen Intel Core i5-1245U	Intel vPro Enterprise with 12th Gen Intel Core i7-1265U
Processor wattage	15 W	15 W	15 W	15 W
Processor core count	2+4	2+8	2+8	2+8
Processor thread count	8	12	12	12
Processor speed	1.20 GHz to 4.40 GHz	1.30 GHz to 4.40 GHz	1.60 GHz to 4.40 GHz	1.80 GHz to 4.80 GHz
Processor cache	10 MB	12 MB	12 MB	12 MB
Integrated graphics	Intel UHD Graphics	Intel Iris Xe Graphics	Intel Iris Xe Graphics	Intel Iris Xe Graphics

Chipset

The following table lists the details of the chipset that is supported in your Latitude 5330.

Table 5. Chipset

Description	Values
Chipset	Intel PCH-LP
Processor	12th Generation Intel Core i3/i5/i7 processors
DRAM bus width	64-bit (for dual-channel)
Flash EPROM	• vPro: 16 MB + 32 MB • Non-vPro: 32 MB
PCIe bus	Up to Gen 4.0

Operating system

Your Latitude 5330 supports the following operating systems:

- Windows 11 Home
- Windows 11 Pro
- Windows 11 Pro Downgrade (Windows 10 Pro Image-factory installed)
- Ubuntu Linux 20.04 LTS

Memory

The following table lists the memory specifications that are supported by your Latitude 5330.

Table 6. Memory specifications

Description	Values
Memory slots	Dual Channel On-board Memory **NOTE:** The memory is not upgradable.
Memory type	DDR4
Memory speed	3200 MHz
Maximum memory configuration	32 GB
Minimum memory configuration	8 GB
Memory size per slot	8 GB, 16 GB, 32 GB
Memory configurations supported	• 8 GB, DDR4, 3200 MHz, dual-channel • 16 GB, DDR4, 3200 MHz, dual-channel • 32 GB, DDR4, 3200 MHz, dual-channel

External ports

The following table lists the external ports on your Latitude 5330.

Table 7. External ports

Description	Values
USB ports	• One USB 3.2 Gen 1 port • One USB 3.2 Gen 1 port with PowerShare • Two Thunderbolt 4 ports with DisplayPort Alt Mode/USB-C/USB4/Power Delivery
Audio port	One Universal audio port
Video port/ports	One HDMI 2.0 port
Media-card reader	One microSD-card slot
Power-adapter port	USB Type-C power input
Security-cable slot	One wedge-shaped lock slot
SIM-card slot	One microSIM-card slot

Internal slots

The following table lists the internal slots of your Latitude 5330.

Table 8. Internal slots

Description	Values
M.2	• One M.2 2230 slot for Wi-Fi and Bluetooth card • One M.2 2230/2280 slots for solid-state drive **NOTE:** To learn more about the features of different types of M.2 cards, search in the Knowledge Base Resource at Dell Support Site.

Wireless module

The following table lists the Wireless Local Area Network (WLAN) module specifications of your Latitude 5330.

Table 9. Wireless module specifications

Description	Option one	Option two	Option three
Model number	Realtek RTL8822CE	Intel AX211	MediaTek MT7921
Transfer rate	Up to 867 Mbps	Up to 2400 Mbps	Up to 1200 Mbps
Frequency bands supported	2.4 GHz/5 GHz	2.4 GHz/5 GHz/6 GHz	2.4 GHz/5 GHz
Wireless standards	• Wi-Fi 802.11a/b/g • Wi-Fi 4 (Wi-Fi 802.11n) • Wi-Fi 5 (Wi-Fi 802.11ac)	• Wi-Fi 802.11a/b/g • Wi-Fi 4 (Wi-Fi 802.11n) • Wi-Fi 5 (Wi-Fi 802.11ac) • Wi-Fi 6E (Wi-Fi 802.11ax)	• Wi-Fi 802.11a/b/g • Wi-Fi 4 (Wi-Fi 802.11n) • Wi-Fi 5 (Wi-Fi 802.11ac) • Wi-Fi 6 (Wi-Fi 802.11ax)

Table 9. Wireless module specifications (continued)

Description	Option one	Option two	Option three
		NOTE: Wi-Fi 6E is available only in selected countries.	
Encryption	• 64-bit/128-bit WEP • AES-CCMP • TKIP	• 64-bit/128-bit WEP • AES-CCMP • TKIP	• 64-bit/128-bit WEP • AES-CCMP • TKIP
Bluetooth wireless card	Bluetooth 5.0	Bluetooth 5.2	Bluetooth 5.2
	NOTE: The version of the Bluetooth wireless card may vary depending on the operating system that is installed on your computer.		

WWAN module

The following table lists the Wireless Wide Area Network (WWAN) module supported on your Latitude 5330.

Table 10. WWAN module specifications

Description	Values
Model number	Intel 7360 (DW5820e)
Transfer rate	Up to 450 Mbps DL/50 Mbps UL (Cat 9)
Frequency bands supported	• LTE FDD: 450 Mbps DL/50 Mbps UL (Cat 9) • LTE TDD: 347 Mbps DL/30 Mbps UL (Cat 9) • UMTS/HSPA+: UMTS 384 Kbps DL/384 Kbps UL
Wireless standards	• LTE Category 9 • UMTS/HSPA+
Encryption	Not supported
Global Navigation Satellite System (GNSS)	Supports GPS, BDS, and GLONASS
NOTE: For instructions on how to find your computer's IMEI (International Mobile Station Equipment Identity) number, see the knowledge base article 000143678 at Dell Support Site.	

Audio

The following table lists the audio specifications of your Latitude 5330.

Table 11. Audio specifications

Description	Values
Audio controller	Realtek ALC3204 with Waves MaxxAudio Pro
Stereo conversion	24-bit Digital-to-Analog (DAC) and Analog-to-Digital (ADC)
Internal audio interface	High definition audio interface
External audio interface	Universal audio jack

Table 11. Audio specifications (continued)

Description		Values
Number of speakers		Two
Internal-speaker amplifier		Supported (audio codec integrated)
External volume controls		Keyboard shortcut controls
Speaker output:		
	Average speaker output	2 W
	Peak speaker output	2.5 W
Subwoofer output		Not supported
Microphone		Dual-array microphones

Storage

This section lists the storage options on your Latitude 5330.

Table 12. Storage matrix

Storage	Single M.2 socket
M.2 2230, Gen 3 PCIe x4 NVMe	Yes
M.2 2280, Gen 3 PCIe x4 NVMe	Yes
M.2 2280, Gen 4 PCIe x4 NVMe	Yes
M.2 2280, Gen 3 PCIe x4 NVMe, SED	Yes

Table 13. Storage specifications

Storage type	Interface type	Capacity
M.2 2230, Class 35 SSD	PCIe NVMe Gen3 x4	Up to 1 TB
M.2 2230, Class 35 SSD	PCIe NVMe Gen4 x4	Up to 1 TB
M.2 2230, Class 35 SSD, self-encrypting drive	PCIe NVMe Gen3 x4	256 GB
M.2 2230, Class 35 SSD, self-encrypting drive	PCIe NVMe Gen4 x4	256 GB
M.2 2280, Class 40 SSD	PCIe NVMe Gen3x4	Up to 1 TB
M.2 2280, Class 40 SSD	PCIe NVMe Gen4 x4	Up to 2 TB
M.2 2280, Class 40 SSD, self-encrypting drive	PCIe NVMe Gen3 x4	Up to 1 TB
M.2 2280, QLC PCIe NVMe	PCIe NVMe	512 GB

Media-card reader

The following table lists the media-card reader specifications of your Latitude 5330.

Table 14. Media-card reader (standard offering)

Description	Values
Media supported (Maximum capacity supported will vary by Flash Media Types)	
Media Supported	• Micro Secure Digital (mSD) • Micro Secure Digital High Capacity (mSDHC) • Micro Secure Digital Extended Capacity (mSDXC)
Support Specification Versions	microSD 4.0 card

Keyboard

The following table lists the keyboard specifications of your Latitude 5330.

Table 15. Keyboard specifications

Description	Values
Keyboard type	• Standard backlit keyboard • Standard non-backlit keyboard
Keyboard layout	QWERTY
Number of keys	• United States and Canada: 79 keys • United Kingdom: 80 keys • Japan: 83 keys
Keyboard size	X=18.05 mm key pitch Y=18.05 mm key pitch
Keyboard shortcuts	Some keys on your keyboard have two symbols on them. These keys can be used to type alternate characters or to perform secondary functions. To type the alternate character, press Shift and the desired key. To perform secondary functions, press Fn and the desired key. **NOTE:** You can define the primary behavior of the function keys (F1–F12) changing **Function Key Behavior** in BIOS setup program. **NOTE:** If Copilot in Windows is not available on your computer, the Copilot key launches Windows Search. For more information about Copilot in Windows, search in the Knowledge Base Resource at the Dell Support site.

Camera

The following table lists the camera specifications of your Latitude 5330.

Table 16. Camera specifications

Description	Option one	Option two	Option (Only for 2-in-1)	Option (Only for clamshell)
Number of cameras	One	One	One	One
Camera type	Integrated 6 mm HD RGB Webcam	Integrated 6 mm FHD RGB + IR Webcam	Integrated 6 mm FHD RGB + IR Webcam with proximity sensor and Ambient light sensor (Optional)	Integrated 6 mm FHD RGB + IR Webcam with Human presence detection
Camera location	Front camera	Front camera	Front camera	Front camera
Camera sensor type	CMOS sensor technology	CMOS sensor technology	CMOS sensor technology	CMOS sensor technology
Camera resolution:				
Still image	0.92 megapixel	0.92 megapixels	0.92 megapixels	0.92 megapixels
Video	1280 x 720 (HD) at 30 fps	1920 x 1080 (FHD) at 30 fps	1920 x 1080 (FHD) at 30 fps	1920 x 1080 (FHD) at 30 fps
Infrared camera resolution:				
Still image	NA	0.23	0.23	0.23
Video	NA	640 x 360	640 x 360	640 x 360
Diagonal viewing angle:				
Camera	78.60 degrees	87 degrees	87.60 degrees	87.60 degrees
Infrared camera	NA	87 degrees	87.60 degrees	87.60 degrees

Clickpad

The following table lists the touchpad specifications of your Latitude 5330.

Table 17. Clickpad specifications

Description		Values
Clickpad resolution:		>300 dpi
Clickpad dimensions:		
	Horizontal	115 mm (4.53 in.)
	Vertical	67 mm (2.64 in.)
Clickpad gestures		For more information about clickpad gestures available on Windows, see the Microsoft knowledge base article 4027871 at support.microsoft.com.

Power adapter

The following table lists the power adapter specifications of your Latitude 5330.

Table 18. Power adapter specifications

Description	Option one	Option two	Option three	Option four
Type	60 W AC adapter, USB-C	60 W AC adapter, USB-C, 2-pin	65 W AC adapter, USB-C	90 W AC adapter, USB-C
Power-adapter dimensions:				
Height	22 mm (0.87 in.)	22 mm (0.87 in.)	28 mm (1.10 in.)	22 mm (0.87 in.)
Width	55 mm (2.16 in.)	55 mm (2.16 in.)	51 mm (2.01 in.)	66 mm (2.60 in.)
Depth	66 mm (2.60 in.)	66 mm (2.60 in.)	112 mm (4.41 in.)	130 mm (5.12 in.)
Input voltage	100 VAC–240 VAC	100 VAC–240 VAC	100 VAC x 240 VAC	100 VAC x 240 VAC
Input frequency	50 Hz–60 Hz	50 Hz–60 Hz	50 Hz to 60 Hz	50 Hz to 60 Hz
Input current (maximum)	1.70 A	1.70 A	1.70 A	1.50 A
Output current (continuous)	• 20 V/3 A (Continuous) • 15 V/3 A (Continuous) • 9 V/3 A (Continuous) • 5 V/3 A (Continuous)	• 20 V/3 A (Continuous) • 15 V/3 A (Continuous) • 9 V/3 A (Continuous) • 5 V/3 A (Continuous)	• 20 V/3.25 A (Continuous) • 15 V/3 A (Continuous) • 9 V/3 A (Continuous) • 5 V/3 A (Continuous)	• 20 V/4.5 A (Continuous) • 15 V/3 A (Continuous) • 9 V/3 A (Continuous) • 5 V/3 A (Continuous)
Rated output voltage	20 VDC/15 VDC/9 VDC/5 VDC	20 VDC/15 VDC/9 VDC/5 VDC	20 VDC/15 VDC/9 VDC/5 VDC	20 VDC/15 VDC/9 VDC/5 VDC
Temperature range:				
Operating	0°C to 40°C (32°F to 104°F)	0°C to 40°C (32°F to 104°F)	0°C to 40°C (32°F to 104°F)	0°C to 40°C (32°F to 104°F)
Storage	-20°C to 70°C (-4°F to 158°F)	-20°C to 70°C (-4°F to 158°F)	-40°C to 70°C (-40°F to 158°F)	-40°C to 70°C (-40°F to 158°F)
CAUTION: Operating and storage temperature ranges may differ among components, so operating or storing the device outside these ranges may impact the performance of specific components.				

Battery

The following table lists the battery specifications of your Latitude 5330.

Table 19. Battery specifications

Description	Option one	Option two	Option three	Option four
Battery type	3 cell rechargeable Li-ion battery, 41 WHr, ExpressCharge Boost	3 cell rechargeable Li-ion battery, 41 WHr, Long Cycle Life	4 cell rechargeable Li-ion battery, 58	4 cell rechargeable Li-ion battery, 58 WHr, Long Cycle Life

Table 19. Battery specifications (continued)

Description		Option one	Option two	Option three	Option four
				WHr, ExpressCharge Boost	
Battery voltage		11.25 VDC	11.25 VDC	15.2 VDC	15.2 VDC
Battery weight (minimum)		0.177 kg (0.38 lbs)	0.177 kg (0.38 lbs)	0.23 kg (0.51 lbs)	0.23 kg (0.51 lbs)
Battery dimensions:					
	Height	5.70 mm (0.22 in.)	5.70 mm (0.22 in.)	5.70 mm (0.22 in.)	5.70 mm (0.22 in.)
	Width	206.4 mm (8.12 in.)	206.4 mm (8.12 in.)	242.0 mm (9.52 in.)	242.0 mm (9.52 in.)
	Depth	89.4 mm (3.51 in.)	89.4 mm (3.51 in.)	89.4 mm (3.51 in.)	89.4 mm (3.51 in.)
Temperature range:					
	Operating	• Charge: 0 °C to 45 °C (32 °F to 113 °F) • Discharge: 0 °C to 70 °C (32 °F to 158 °F)	• Charge: 0 °C to 45 °C (32 °F to 113 °F) • Discharge: 0 °C to 70 °C (32 °F to 158 °F)	• Charge: 0 °C to 45 °C (32 °F to 113 °F) • Discharge: 0 °C to 70 °C (32 °F to 158 °F)	• Charge: 0 °C to 45 °C (32 °F to 113 °F) • Discharge: 0 °C to 70 °C (32 °F to 158 °F)
	Storage	-40 °C to 65 °C (-40 °F to 149 °F)	-40 °C to 65 °C (-40 °F to 149 °F)	-40 °C to 65 °C (-40 °F to 149 °F)	-40 °C to 65 °C (-40 °F to 149 °F)
Battery operating time		Varies depending on operating conditions and can significantly reduce under certain power-intensive conditions.	Varies depending on operating conditions and can significantly reduce under certain power-intensive conditions.	Varies depending on operating conditions and can significantly reduce under certain power-intensive conditions.	Varies depending on operating conditions and can significantly reduce under certain power-intensive conditions.
Battery charging time (approximate) **NOTE:** Control the charging time, duration, start and end time, and so on using the Dell Power Manager application. For more information on the Dell Power Manager see, *Me and My Dell* on Dell Support Site.		**Express Charge Method:** • 0 - 15°C maximum allowable charge time from 0 to 100% RSOC is 4 hours • 16 - 45°C normal express charge • 46 - 50°C maximum allowable charge time from 0 to 100% RSOC is 3 hours **Standard Charge/ Predominately AC User Charge Method:** • 0 - 15°C maximum allowable charge time from 0 to 100% RSOC is 4 hours • 16 - 50°C maximum allowable charge time from 0 to 100% RSOC is 3 hours **Express Charge Boost Charge Method (Fast**	**Standard Charge/ Predominately AC User Charge Method:** • 0 - 15°C maximum allowable charge time from 0 to 100% RSOC is 4 hours • 16 - 50°C maximum allowable charge time from 0 to 100% RSOC is 3 hours	**Express Charge Method:** • 0 - 15°C maximum allowable charge time from 0 to 100% RSOC is 4 hours • 16 - 45°C normal express charge • 46 - 50°C maximum allowable charge time from 0 to 100% RSOC is 3 hours **Standard Charge/ Predominately AC User Charge Method:** • 0 - 15°C maximum allowable charge time from 0 to	**Standard Charge/ Predominately AC User Charge Method:** • 0 - 15°C maximum allowable charge time from 0 to 100% RSOC is 4 hours • 16 - 50°C maximum allowable charge time from 0 to 100% RSOC is 3 hours

Table 19. Battery specifications (continued)

Description	Option one	Option two	Option three	Option four
	Charge for Initial 35%): • 16 - 45°C target charge time from 0 to 35% RSOC is 20 mins for Accelerated Charge		100% RSOC is 4 hours • 16 - 50°C maximum allowable charge time from 0 to 100% RSOC is 3 hours **Express Charge Boost Charge Method (Fast Charge for Initial 35%):** • 16 - 45°C target charge time from 0 to 35% RSOC is 20 mins for Accelerated Charge	
Coin-cell battery	Yes	Yes	Yes	Yes

CAUTION: Operating and storage temperature ranges may differ among components, so operating or storing the device outside these ranges may impact the performance of specific components.

CAUTION: Dell recommends that you charge the battery regularly for optimal power consumption. If your battery charge is completely depleted, connect the power adapter, turn on your computer, and then restart your computer to reduce the power consumption.

Display

The following table lists the display specifications of your Latitude 5330.

Table 20. Display specifications

Description		Option one	Option two	Option three	Option for 2-in-1 only
Display type		Full High Definition (FHD)	Full High Definition (FHD), low blue light	Full High Definition (FHD)	Full High Definition (FHD)
Display-panel technology		Wide Viewing Angle (WVA)	Wide-Viewing Angle (WVA)	Wide Viewing Angle (WVA)	Wide-Viewing Angle (WVA)
Display-panel dimensions (active area):					
	Height	165.24 mm (6.51 in.)	165.24 mm (6.51 in.)	165.24 mm (6.51 in.)	165.24 mm (6.51 in.)
	Width	293.76 mm (11.57 in.)	293.76 mm (11.57 in.)	293.76 mm (11.57 in.)	293.76 mm (11.57 in.)
	Diagonal	337.08 mm (13.27 in.)	337.08 mm (13.27 in.)	337.08 mm (13.27 in.)	337.08 mm (13.27 in.)
Display-panel native resolution		1920 x 1080	1920 x 1080	1920 x 1080	1920 x 1080

Table 20. Display specifications (continued)

Description	Option one	Option two	Option three	Option for 2-in-1 only
Luminance (typical)	250 nits	400 nits	300 nits	270 nits
Megapixels	2073600	2073600	2073600	2073600
Color gamut	45% NTSC typ.	100% sRGB typ.	72% NTSC typ.	100% sRGB typ.
Pixels Per Inch (PPI)	166	166	166	166
Contrast ratio (typical)	800:1	1000:1	700:1	600:1
Response time (max)	35 ms	35 ms	35 ms	35 ms
Refresh rate	60 Hz	60 Hz	60 Hz	60 Hz
Horizontal view angle	80/80 min. 85/85 typ. +/- degrees	80/80 min. 85/85 typ. +/- degrees	80/80 min. 85/85 typ. +/- degrees	80/80 min. 85/85 typ. +/- degrees
Vertical view angle	80/80 min. 85/85 typ. +/- degrees	80/80 min. 85/85 typ. +/- degrees	80/80 min. 85/85 typ. +/- degrees	80/80 min. 85/85 typ. +/- degrees
Pixel pitch	0.153 x 0.153 mm	0.153 x 0.153 mm	0.153 x 0.153 mm	0.153 x 0.153 mm
Power consumption (maximum)	3.5 W@Mosaic	2.52 W@Mosaic	4.4 W@Mosaic	4.5 W@Mosaic
Anti-glare vs glossy finish	Anti-glare	Anti-glare	Anti-glare	(DXC) Anti-reflection/Anti-smudge
Touch options	No	No	Yes	Yes

Fingerprint reader (optional)

The following table lists the specifications of the optional fingerprint-reader of your Latitude 5330.

Table 21. Fingerprint reader specifications

Description	Values
Fingerprint-reader sensor technology	Capacitive
Fingerprint-reader sensor resolution	508 dpi
Fingerprint-reader sensor pixel size	256 x 360

Sensor

The following table lists the sensor of your Latitude 5330.

Table 22. Sensor

Sensor support
Ambient Light Sensor on the hinge-up (optional)
P-sensor on the hinge-up (optional)

Table 22. Sensor (continued)

Sensor support
1 Accelerometer in the base (system board) for both Clamshell and 2-in-1
1 Accelerometer (Accelerometer + Gyro) in the hinge-up sensor board (Upsell on clamshell with Proximity/ALS/IR camera and 100% attached on 2-in-1)

GPU—Integrated

The following table lists the specifications of the integrated Graphics Processing Unit (GPU) supported by your Latitude 5330.

Table 23. GPU—Integrated

Controller	Memory size	Processor
Intel Iris Xe Graphics	Shared system memory	12th Generation Intel Core i5/i7 processors
Intel UHD Graphics	Shared system memory	12th Generation Intel Core i3 processor

Hardware security

The following table lists the hardware security of your Latitude 5330.

Table 24. Hardware security

Hardware security
Windows Hello - Fingerprint Reader (optional)
Trusted Platform Module (TPM) 2.0 FIPS 140-2 Certified
TCG Certification for TPM (Trusted Computing Group)
One wedge-shaped lock slot
Fingerprint Reader in Power Button tied to ControlVault 3
ControlVault 3 Advanced Authentication (optional) FIPS 140-2 Level 3 Certified
Contacted Smartcard reader with Control Vault 3 (optional) FIPS 201 Certified
Contactless Smartcard, NFC/FPR with CV3 (optional)
SED SSD NVMe, SSD and HDD (Opal and non-Opal) per SDL

Smart-card reader

Contactless smart-card reader

This section lists the contactless smart-card reader specifications of your Latitude 5330. This module is only available in computers shipped with Smart-card readers.

Table 25. Contactless smart-card reader specifications

Title	Description	Dell ControlVault 3 Contactless Smart-card reader with NFC
Felica Card Support	Reader and software capable of supporting Felica contactless cards	Yes

Table 25. Contactless smart-card reader specifications (continued)

Title	Description	Dell ControlVault 3 Contactless Smart-card reader with NFC
Prox (Proximity) (125 kHz) Card support	Reader and software capable of supporting Prox/Proximity/125 kHz contactless cards	No
ISO 14443 Type A Card Support	Reader and software capable of supporting ISO 14443 Type A contactless cards	Yes
ISO 14443 Type B Card Support	Reader and software capable of supporting ISO 14443 Type B contactless cards	Yes
ISO/IEC 21481	Reader and software capable of supporting ISO/IEC 21481 compliant contactless cards and tokens	Yes
ISO/IEC 18092	Reader and software capable of supporting ISO/IEC 21481 compliant contactless cards and tokens	Yes
ISO 15693 Card Support	Reader and software capable of supporting ISO15693 contactless cards	Yes
NFC Tag Support	Supports reading and processing of NFC compliant tag information	Yes
NFC Reader Mode	Support for NFC Forum Defined Reader mode	Yes
NFC Writer Mode	Support for NFC Forum Defined Writer mode	Yes
NFC Peer-to-Peer Mode	Support for NFC Forum Defined Peer to Peer mode	Yes
NFC Proximity OS Interface	Enumerates NFP (Near Field Proximity) device for OS to utilize	Yes
PC/SC OS interface	Personal Computer/Smart-Card specification for integration of hardware readers into personal computer environments	Yes
CCID driver compliance	Common driver support for Integrated Circuit Card Interface Device for OS level drivers	Yes
Windows Certified	Device certified by Microsoft WHCK	Yes
Dell ControlVault support	Device connects to Dell ControlVault for usage and processing	Yes

NOTE: 125 Khz proximity cards are not supported.

Table 26. Supported cards

Manufacturer	Card	Supported
HID	jCOP readertest3 A card (14443a)	Yes
	1430 1L	
	DESFire D8H	
	iClass (Legacy)	

Table 26. Supported cards (continued)

Manufacturer	Card	Supported
	iClass SEOS	
NXP/Mifare	Mifare DESFire 8K White PVC Cards	Yes
	Mifare Classic 1K White PVC Cards	
	NXP Mifare Classic S50 ISO Card	
G&D	idOnDemand - SCE3.2 144K	Yes
	SCE6.0 FIPS 80K Dual+ 1 K Mifare	
	SCE6.0 nonFIPS 80K Dual+ 1 K Mifare	
	SCE6.0 FIPS 144K Dual + 1K Mifare	
	SCE6.0 nonFIPS 144K Dual + 1 K Mifare	
	SCE7.0 FIPS 144K	
Oberthur	idOnDemand - OCS5.2 80K	Yes
	ID-One Cosmo 64 RSA D V5.4 T=0 card	
	ID-One Cosmo 128K V5.5 card	
Gemalto	TOP DL GX4 144K card	Yes
Sony	Felica RC-S962	Yes
	Felica RC-S966	Yes
PIVKey	C910 PKI	Yes
IDENTIV	PIV programmed cards	Yes

Contacted smart-card reader

The following table lists the contacted smart-card reader specifications of your Latitude 5330.

Table 27. Contacted smart-card reader specifications

Title	Description	Dell ControlVault 3 smart-card reader
ISO 7816 -3 Class A Card Support	Reader capable of reading 5V powered smart mcard	Yes
ISO 7816 -3 Class B Card Support	Reader capable of reading 3V powered smart card	Yes
ISO 7816 -3 Class C Card support	Reader capable of reading 1.8V powered smart card	Yes
ISO 7816-1 Compliant	Specification for the reader	Yes
ISO 7816 -2 Compliant	Specification for smart card device physical characteristics (size, location of connection points, etc.)	Yes
T=0 support	Cards support character level transmission	Yes
T=1 support	Cards support block level transmission	Yes
EMVCo Compliant	Compliant with EMVCo (for electronic payment standards) smart card standards as posted to www.emvco.com	Yes

Table 27. Contacted smart-card reader specifications (continued)

Title	Description	Dell ControlVault 3 smart-card reader
EMVCo Certified	Formally certified based on EMVCO smart card standards	Yes
PC/SC OS interface	Personal Computer/Smart Card specification for integration of hardware readers into personal computer environments	Yes
CCID driver compliance	Common driver support for Integrated Circuit Card Interface Device for OS level drivers.	Yes
Windows Certified	Device certified by WHCK	Yes
FIPS 201 (PIV/HSPD-12) Compliant via GSA	Device compliant with FIPS 201/PIV/ HSPD-12 requirements	Yes
FIDO2 compliance	Dell ControlVault 3 Smart-card reader is compliant with the FIDO SPEC	Yes

Operating and storage environment

This table lists the operating and storage specifications of your Latitude 5330.

Airborne contaminant level: G1 as defined by ISA-S71.04-1985

Table 28. Computer environment

Description	Operating	Storage
Temperature range	0°C to 35°C (32°F to 95°F)	-40°C to 65°C (-40°F to 149°F)
Relative humidity (maximum)	10% to 90% (non-condensing)	0% to 95% (non-condensing)
Vibration (maximum)*	0.66 GRMS	1.30 GRMS
Shock (maximum)	110 G†	160 G†
Altitude range	-15.2 m to 3048 m (-49.87 ft to 10000 ft)	-15.2 m to 10668 m (-49.87 ft to 35000 ft)
CAUTION: Operating and storage temperature ranges may differ among components, so operating or storing the device outside these ranges may impact the performance of specific components.		

* Measured using a random vibration spectrum that simulates the user environment.

† Measured using a 2 ms half-sine pulse.

4

ComfortView Plus

WARNING: Prolonged exposure to blue light from the display may lead to long-term effects such as eye strain, eye fatigue, or damage to the eyes.

Blue light is a color in the light spectrum which has a short wavelength and high energy. Chronic exposure to blue light, particularly from digital sources, may disrupt sleep patterns and cause long-term effects such as eye strain, eye fatigue, or damage to the eyes.

The display on this computer is designed to minimize blue light and complies with TÜV Rheinland's requirement for low blue light displays.

Low blue light mode is enabled at the factory, so no further configuration is necessary.


To reduce the risk of eye strain, it is also recommended that you:

- Position the display at a comfortable viewing distance between 20 and 28 inches (50 cm and 70 cm) from your eyes.
- Blink frequently to moisten your eyes, wet your eyes with water, or apply suitable eye drops.
- Look away from your display, and gaze at a distant object at 20 ft (609.60 cm) away for at least 20 seconds during each break.
- Take an extended break for 20 minutes every two hours.

5

Using the privacy shutter

1. Slide the privacy shutter to the left to access the camera lens.
2. Slide the privacy shutter to the right to cover the camera lens.



6

Dell Optimizer

This section details the Dell Optimizer specifications of your Latitude 5330.

On Latitude 5330 with Dell Optimizer, the following features are supported:

- **ExpressConnect**—Automatically joins the access point with the strongest signal, and directs bandwidth to conferencing applications when in use.
- **ExpressSign-in**—The Intel Context Sensing Technology's proximity sensor detects your presence to instantly wake up the computer and login using the IR camera and Windows Hello feature. Windows locks when you walk away.
- **ExpressResponse**—Prioritizes the most important applications. Applications open faster and perform better.
- **ExpressCharge**—Extends the battery runtime and improves battery performance by adapting to your patterns.
- **Intelligent Audio**—Collaborate like you're in the same room. Intelligent Audio enhances your audio quality and reduces background noises, so you can hear and be heard, creating a better conference experience for all.

For more information about configuring and using these features, see Dell Optimizer User Guide.

7

Keyboard shortcuts of Latitude 5330

NOTE: Keyboard characters may differ depending on the keyboard language configuration. Keys used for shortcuts remain the same across all language configurations.

Some keys on your keyboard have two symbols on them. These keys can be used to type alternate characters or to perform secondary functions. The symbol shown on the lower part of the key refers to the character that is typed out when the key is pressed. If you press shift and the key, the symbol shown on the upper part of the key is typed out. For example, if you press **2**, **2** is typed out; if you press **Shift** + **2**, **@** is typed out.

The keys F1-F12 at the top row of the keyboard are function keys for multi-media control, as indicated by the icon at the bottom of the key. Press the function key to invoke the task represented by the icon. For example, pressing F1 mutes the audio (refer to the table below).

However, if the function keys F1-F12 are needed for specific software applications, multi-media functionality can be disabled by pressing **Fn** + **Esc**. Subsequently, multi-media control can be invoked by pressing **Fn** and the respective function key. For example, mute audio by pressing **Fn** + **F1**.

NOTE: You can also define the primary behavior of the function keys (F1–F12) by changing **Function Key Behavior** in BIOS setup program.

Table 29. List of keyboard shortcuts

Function key	Primary behavior
F1	Mute audio
F2	Decrease volume
F3	Increase volume
F4	Mic mute
F5	Keyboard backlight **NOTE:** Non-backlight keyboards have F5 function key without the backlight icon and do not support toggle keyboard backlight function. **NOTE:** Toggle to cycle the keyboard backlight status through off, low-backlight, and high-backlight
F6	Decrease screen brightness
F7	Increase screen brightness
F8	Switch to external display
F9	Operating system and application specific F9 behavior
F10	Print Screen
F11	Home
F12	End

The **Fn** key is also used with selected keys on the keyboard to invoke other secondary functions.

Table 30. Secondary behavior

Function key	Secondary behavior
Fn + F1	Operating system and application specific F1 behavior
Fn + F2	Operating system and application specific F2 behavior
Fn + F3	Operating system and application specific F3 behavior

Table 30. Secondary behavior (continued)

Function key	Secondary behavior
Fn + F4	Operating system and application specific F4 behavior
Fn + F5	Operating system and application specific F5 behavior
Fn + F6	Operating system and application specific F6 behavior
Fn + F8	Operating system and application specific F8 behavior
Fn + F9	Operating system and application specific F9 behavior
Fn + F10	Operating system and application specific F10 behavior
Fn + F11	Operating system and application specific F11 behavior
Fn + F12	Operating system and application specific F12 behavior
Fn + PrtScr	Turn off/on wireless
Fn + B	Pause/Break
Fn + Insert	Sleep
Fn + S	Toggle scroll lock
Fn + H	Toggle between power and battery-status light/hard-drive activity light
Fn + R	System request
Fn + Ctrl	Open application menu
Fn + Esc	Toggle Fn-key lock
Fn + PgUp	Page up
Fn + PgDn	Page down
Fn + Left Arrow	Home
Fn + Right Arrow	End

8

Getting help and contacting Dell Technologies

Self-help resources

You can get information and help on Dell Technologies products and services using these self-help resources:

Table 31. Self-help resources

Self-help resources	Resource location
Information about Dell Technologies products and services	Dell Site
My Dell app	
Tips	
Contact Support	In Windows search, type `Contact Support`, and press Enter.
Online help for operating system	Windows Support Site
Access top solutions, diagnostics, drivers and downloads, and learn more about your computer through videos, manuals, and documents.	Your Dell Technologies computer is uniquely identified using a Service Tag or Express Service Code. To view relevant support resources for your Dell Technologies computer, enter the Service Tag or Express Service Code at Dell Support Site. For more information about how to find the Service Tag for your computer, see Instructions on how to find your Service Tag or Serial Number.
Dell Technologies knowledge base articles	1. Go to Dell Support Site. 2. On the menu bar at the top of the Support page, select **Support** > **Support Library**. 3. In the Search field on the Support Library page, type the keyword, topic, or model number, and then click or tap the search icon to view the related articles.

Contacting Dell Technologies

To contact Dell Technologies for sales, technical support, or customer service issues, see Contact Support at Dell Support Site.

NOTE: Availability of the services may vary depending on the country or region, and product.

NOTE: If you do not have an active Internet connection, you can find contact information about your purchase invoice, packing slip, bill, or Dell Technologies product catalog.