


## USB to 4 X HDMI Display Adapter

### Product Diagram (USB32HD4 & USBC2HD4)



Component	Function
1 (USB32HD4) USB-A Host Connector	<ul style="list-style-type: none"> <li>• SuperSpeed USB 5Gbps (USB 3.2 Gen 1)</li> <li>• (USB32HD4) Connect to a <b>USB-A Enabled Host Computer</b></li> </ul>
2 (USBC2HD4) USB-C Host Connector	<ul style="list-style-type: none"> <li>• SuperSpeed USB 5Gbps (USB 3.2 Gen 1)</li> <li>• (USBC2HD4) Connect to a <b>USB-C Enabled Host Computer</b></li> </ul>
3 HDMI Ports x 4	<ul style="list-style-type: none"> <li>• Connect up to 4 <b>HDMI Enabled Display Devices</b></li> </ul>

### Product Information

“For the latest product information, technical specifications, manuals, and Declarations of Conformance please visit: [www.StarTech.com/USB32HD4](http://www.StarTech.com/USB32HD4) or [www.StarTech.com/USBC2HD4](http://www.StarTech.com/USBC2HD4)”

### Package Contents

#### USB32HD4

- USB-A to HDMI Adapter x 1
- Quick-Start Guide x 1

#### USBC2HD4

- USB-C to HDMI Adapter x 1
- Quick-Start Guide x 1

### Driver Installation

Installation is automatic for Windows 10 in most situations. If the drivers do not auto-install, contact your IT administrator or department to allow the driver installation. Visit [www.startech.com/USB32HD4](http://www.startech.com/USB32HD4) or [www.startech.com/USBC2HD4](http://www.startech.com/USBC2HD4) to locate the latest drivers.

**Note:** This USB video adapter uses a Trigger family chipset. If you're connecting this device to a computer along with additional USB video adapters or docking stations, avoid using devices with different family chipsets, such as DisplayLink® or Fresco Logic

**Note:** ®Operating system requirements are subject to change. For the latest requirements, please visit [www.StarTech.com/USB32HD4](http://www.StarTech.com/USB32HD4) or [www.StarTech.com/USBC2HD4](http://www.StarTech.com/USBC2HD4)

### Installation

#### Connect a Host

##### USB32HD4

- Connect the **USB-A Host Connector** of the **USB-A to HDMI Adapter** to a **USB-A Port** on a **USB-A Enabled Host Computer**.

##### USBC2HD4

- Connect the **USB-C Host Connector** of the **USB-C to HDMI Adapter** to a **USB-C Port** on a **USB-C Enabled Host Computer**.

#### Connect the Display Devices

- Connect an **HDMI Enabled Display Device** to the **HDMI Port** of the **USB to 4 X HDMI Display Adapter** using an **HDMI Cable**.
  - (Optional) Repeat to connect up to 4 x extended or mirrored **HDMI Enabled Display Devices**.

#### Arrange Display Devices

- Arrange connected **Display Devices** using **Windows Display Settings** on the **Host Computer**.

### FCC Compliance Statement

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:

(1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation. Changes or modifications not expressly approved by StarTech.com could void the user's authority to operate the equipment.

### Industry Canada Statement

This Class B digital apparatus complies with Canadian ICES-003. Cet appareil numérique de la classe [B] est conforme à la norme NMB-003 du Canada. CAN ICES-3 (B)/NMB-3(B)

This device complies with Industry Canada licence-exempt RSS standard(s). Operation is subject to the following two conditions: (1) This device may not cause interference, and (2) This device must accept any interference, including interference that may cause undesired operation of the device.

Le présent appareil est conforme aux CNR d'Industrie Canada applicables aux appareils radio exempts de licence. L'exploitation est autorisée aux deux conditions suivantes:

(1) l'appareil ne doit pas produire de brouillage, et (2) l'utilisateur de l'appareil doit accepter tout brouillage radioélectrique subi, même si le brouillage est susceptible d'en compromettre le fonctionnement.

### Use of Trademarks, Registered Trademarks, and other Protected Names and Symbols

This manual may make reference to trademarks, registered trademarks, and other protected names and/or symbols of third-party companies not related in any way to StarTech.com. Where they occur these references are for illustrative purposes only and do not represent an endorsement of a product or service by StarTech.com, or an endorsement of the product(s) to which this manual applies by the third-party company in question. StarTech.com hereby acknowledges that all trademarks, registered trademarks, service marks, and other protected names and/or symbols contained in this manual and related documents are the property of their respective holders.

### Warranty Information

This product is backed by a three-year warranty.

For further information on product warranty terms and conditions, please refer to [www.startech.com/warranty](http://www.startech.com/warranty).

### Limitation of Liability

In no event shall the liability of StarTech.com Ltd. and StarTech.com USA LLP (or their officers, directors, employees or agents) for any damages (whether direct or indirect, special, punitive, incidental, consequential, or otherwise), loss of profits, loss of business, or any pecuniary loss, arising out of or related to the use of the product exceed the actual price paid for the product. Some states do not allow the exclusion or limitation of incidental or consequential damages. If such laws apply, the limitations or exclusions contained in this statement may not apply to you.

### Safety Measures

- Cables (including power and charging cables) should be placed and routed to avoid creating electric, tripping or safety hazards.

### Mesures de sécurité

- Les câbles (y compris les câbles d'alimentation et de chargement) doivent être placés et acheminés de façon à éviter tout risque électrique, de chute ou de sécurité

### 安全対策

- ケーブル（電源ケーブルと充電ケーブルを含む）は、適切な配置と引き回しを行い、電気障害やつまづきの危険性など、安全上のリスクを回避するようにしてください。

### Misure di sicurezza

- I cavi (inclusi i cavi di alimentazione e di ricarica) devono essere posizionati e stesi in modo da evitare pericoli di inciampo, rischi di scosse elettriche o pericoli per la sicurezza.

### Säkerhetsåtgärder

- Kablar (inklusive elkablar och laddningskablar) ska dras och placeras på så sätt att risk för snubblingsolyckor och andra olyckor kan undvikas.

### StarTech.com Ltd.

45 Artisans Crescent  
London, Ontario  
N5V 5E9  
Canada

### StarTech.com LLP

4490 South Hamilton  
Road  
Groveport, Ohio  
43125  
U.S.A.

### StarTech.com Ltd.

Unit B, Pinnacle 15  
Gowerton Road  
Brackmills,  
Northampton  
NN4 7BW  
United Kingdom

### StarTech.com Ltd.

Siriusdreef 17-27  
2132 WT Hoofddorp  
The Netherlands

FR: startech.com/fr  
DE: startech.com/de  
ES: startech.com/es  
NL: startech.com/nl  
IT: startech.com/it  
JP: startech.com/jp