

### Overview

#### HPE SimpliVity 380 Gen10

HPE SimpliVity 380, based on the HPE ProLiant DL380 Gen10 Servers, is a compact, scalable, 2U rack-mounted building block that delivers integrated server, storage, and storage networking services. Adaptable for diverse virtualized workloads, the secure 2U HPE SimpliVity 380 Gen10 delivers world-class performance with the right balance of expandability and scalability. It also provides a complete set of advanced functionality that enables dramatic improvements to the efficiency, management, protection, and performance—at a fraction of the cost and complexity of today's traditional infrastructure stack.



#### What's New

- HPE SimpliVity 380 G now offers support for 2nd Generation **Intel®** Xeon® Scalable Processors
- HPE SimpliVity 380 G now supports for 12x or 16x SSD kits offering higher capacity software-optimized nodes
- HPE SimpliVity 380 H SFF is now available, supporting hybrid storage for general purpose virtualized workloads.
- HPE SimpliVity now supports HPE StoreOnce, for customers who need a simple, cost effective, efficient, archiving solution to centralize data, lower costs, or adhere to long term backup policies

**NOTE:** For VMware and HW compatibility and software details, please visit <https://www.hpe.com/info/simplivity-interop-doc> or <http://www.hpe.com/docs/simplivity-library>.

<https://support.hpe.com/hpsc/public/km/search?q=Simplivity&t=DriversandSoftware&sort=%40hpscuniversaldate%20descending&layout=table>

## Standard Features

### Scalable and Configurable

- Expandable in 1 node increments up to 96 total nodes
- Processor - Choice of Intel® Xeon® Scalable Processors
- Memory - 128GB to 3072GB (Per node depending on configuration)
- Network – 10/25Gb, 1Gb
- Power – Redundant
- Virtualization Software and Licensing
- All in a compact 2U form factor

**NOTE:** It is strongly recommended that an HPE SimpliVity 380 Gen10 cluster have a minimum of two nodes to realize the full benefits of the high availability hyperconverged solution.

**NOTE:** A single cluster supports up to 16 nodes. A single federation supports up to 96 nodes. Scalability varies by Hypervisor. See product documentation for details.

### Software Features

- VMware vSphere
- HPE SimpliVity management plugin for VMware vCenter
- Microsoft Hyper-V
- HPE SimpliVity management plugin for Microsoft System Center
- Optional Data Encryption support
- Optional RapidDR support

**NOTE:** The HPE SimpliVity 380 supports VMware vSphere & vCenter 6.5 and 6.7

**NOTE:** For VMware and HW compatibility, please see the HPE SimpliVity OmniStack Interoperability Guide <https://www.hpe.com/info/simplivity-interop-doc> or [www.hpe.com/docs/simplivity-library](http://www.hpe.com/docs/simplivity-library)

### Hardware Availability Features

- Cluster expansion without downtime
- Hot-pluggable SSD
- Redundant power supplies
- Integrated storage controller with battery-backed cache
- HPE ProLiant Integrated Lights-Out Advanced (iLO) 5 Remote Management

### Services

- HPE Pointnext full suite of support offerings (Foundation Care, Proactive Care and Datacenter Care).
- Remote support technology to provide 24x7 secure remote support

**NOTE:** For the best support experience, HPE Pointnext Installation Services and 24x7x365 support recommended.

## Standard Features

### HPE SimpliVity 380 Gen10: At-a-Glance

<b>Node Size</b>	2U
<b>Processors</b>	2x Intel® Xeon® Scalable Processors 8 to 28 cores selectable, 1 or 2CPU options
<b>Memory</b>	144GB to 1536GB per node selectable
<b>Storage</b>	Two All Flash Storage Options (4000/6000 Series) and Five Capacity Points: Extra Small - 5 x 960GB SSD Kit Small - 5 x 1.92TB SSD Kit Medium - 9x 1.92TB SSD Kit Large - 12 x 1.92TB SSD Kit Extra Large – 12 x 3.84TB SSD Kit (4000 Series only)
<b>Network Ports</b>	Ethernet 1Gb LOM embedded, 10Gb FLOM
<b>Power Supplies</b>	HPE 800W FS Plat Hot Plug Power Supply Kit HPE 800W FS -48VDC Hot Plug Power Supply Kit HPE 800W FS Titanium Hot Plug Power Supply Kit HPE 800W FS Universal Hot Plug Power Supply Kit HPE 1600W FS Platinum Hot Plug LH Power Supply Kit
<b>Hardware Warranty</b>	Server Warranty includes 3-Year Parts, 3-Year Labor, 3-Year Onsite support with next business day response
<b>Hardware Support</b>	3-year HPE SimpliVity 380 Gen10 solution support (required)

**NOTE:** Warranty for SSDs is subject to maximum usage limitations. Maximum usage limit is the maximum amount of data that can be written to the drive. Drives that have reached this limit will not be eligible for replacement.

**NOTE:** Two power supplies per node are required for redundancy. 800W power supplies are only supported with specific configurations.

### HPE SimpliVity 380 Gen10 G: At-a-Glance

<b>Node Size</b>	2U
<b>Processors</b>	2x Intel® Xeon® Scalable Processors 8 to 28 cores selectable, 1 or 2CPU options
<b>Memory</b>	128GB to 3072GB per node selectable
<b>Storage</b>	Four Capacity Options: 6 x 1.92TB SSD Kit – 7.5TB (usable) 8 x 1.92TB SSD Kit – 10.6TB (usable) 12 x 1.92TB SSD Kit- 15TB (usable) 16 x 1.92TB SSD Kit- 20TB (usable)
<b>Network Ports</b>	Ethernet 1Gb LOM embedded, 10Gb FLOM
<b>Power Supplies</b>	HPE 800W FS Plat Hot Plug Power Supply Kit HPE 800W FS -48VDC Hot Plug Power Supply Kit HPE 800W FS Titanium Hot Plug Power Supply Kit HPE 800W FS Universal Hot Plug Power Supply Kit HPE 1600W FS Platinum Hot Plug LH Power Supply Kit
<b>Hardware Warranty</b>	Server Warranty includes 3-Year Parts, 3-Year Labor, 3-Year Onsite support with next business day response
<b>Hardware Support</b>	3-year HPE SimpliVity 380 Gen10 solution support (required)

**NOTE:** Warranty for SSDs is subject to maximum usage limitations. Maximum usage limit is the maximum amount of data that can be written to the drive. Drives that have reached this limit will not be eligible for replacement.

**NOTE:** Two power supplies per node are required for redundancy. 800W power supplies are only supported with specific configurations.

## Standard Features

### HPE SimpliVity 380 Gen10 H: At-a-Glance

<b>Node Size</b>	2U LFF 2U SFF
<b>Processors</b>	2x Intel® Xeon® Scalable Processors 8 to 28 cores selectable, 1 or 2CPU options
<b>Memory</b>	192GB to 3072GB per node selectable
<b>Storage</b>	LFF Backup and Archive: 4 x 1.92TB SSD, 8 x 4.0TB HDD Kit – 25TB (usable) SFF General Purpose Virtualization: 4x 1.92TB, 20 x 1.2TB HDD- 20TB (usable)
<b>Network Ports</b>	Ethernet 1Gb LOM embedded, 10Gb FLOM
<b>Power Supplies</b>	HPE 800W FS Plat Hot Plug Power Supply Kit HPE 800W FS -48VDC Hot Plug Power Supply Kit HPE 800W FS Titanium Hot Plug Power Supply Kit HPE 800W FS Universal Hot Plug Power Supply Kit HPE 1600W FS Platinum Hot Plug LH Power Supply Kit
<b>Hardware Warranty</b>	Server Warranty includes 3-Year Parts, 3-Year Labor, 3-Year Onsite support with next business day response
<b>Hardware Support</b>	3-year HPE SimpliVity 380 Gen10 solution support (required)
<p><b>NOTE:</b> Warranty for SSDs is subject to maximum usage limitations. Maximum usage limit is the maximum amount of data that can be written to the drive. Drives that have reached this limit will not be eligible for replacement.</p> <p><b>NOTE:</b> Two power supplies per node are required for redundancy. 800W power supplies are only supported with specific configurations.</p>	

### Features and Benefits

#### HPE InfoSight for HPE SimpliVity enables predictive data analytics

For HPE SimpliVity nodes HPE InfoSight provides system details at the federation, cluster, and host level for historic capacity utilization, trends, resource consumption and prediction. Alleviates support issues and reduces operational expenses with automated wellness alerts and case creation. Provides a unified view of HPE SimpliVity assets such as Datastore, VM, Backups, Capacity, and IOPS.

#### Fully integrated system

Combines x86 resources, storage, and storage networking in a single hyperconverged system. Simplifies management and delivers great cost efficiency and agility with increased visibility and control.

#### Peak and predictable performance

The all-flash solution provides predictable and linear performance at near-wire speeds with reduced latency. Hardware-assisted inline deduplication, compression, and optimization helps minimize I/O and network traffic, improving performance while delivering great storage and bandwidth efficiency.

#### Scale in and scale out

Easily expand or shrink configurations as your needs change. Each node supports a large number of fully protected virtual machines (VMs), with the networked collection of nodes at both local and remote sites managed as a single entity.

#### VM centricity and mobility

Enables all actions, policies, and management at the VM level. Global unified management and integration with established administrative systems streamline operations and improve IT agility.

#### Dramatic TCO reduction

Drastically reduce the need to purchase multiple discrete components, optimize storage capacity with guaranteed 10:1 data efficiency, and prevent over-provisioning for performance and capacity with on-demand expansion.

## Standard Features

### Software Overview

#### Pre-integrated software

- HPE SimpliVity Startup Wizard

#### Virtualization Platform Software and Licenses

**NOTE:** HPE SimpliVity 380 Gen10 supports VMware vSphere ESXi and Microsoft Hyper-V Server.

- VMware vSphere installation is performed by HPE when ordering HPE SimpliVity 380 Gen10
- Valid licenses for the following VMware software components are available when ordering HPE SimpliVity 380 Gen10
  - (1 or 2) VMware vSphere license(s) per node depending on CPU count
  - (1) VMware vCenter license
- Microsoft Hyper-V Server installation is performed by HPE when ordering HPE SimpliVity 380 Gen10
- Valid licenses for the following Microsoft software components are available when ordering HPE SimpliVity 380 Gen10
  - (1 or 2) Microsoft Hyper-V Server 2016 license(s) per node depending on CPU and core count
  - (1) Microsoft Systems Center 2016 Virtual Machine Manager license
  - (1) Microsoft Active Directory Server

**NOTE:** The HPE SimpliVity 380 supports VMware vSphere & vCenter 6.5 and 6.7

**NOTE:** For VMware and HW compatibility, please visit [www.hpe.com/docs/simplivity-library](http://www.hpe.com/docs/simplivity-library) or <https://www.hpe.com/info/simplivity-interop-doc>

**NOTE:** HPE SimpliVity 380 Gen10 for VMware vSphere requires valid VMware vSphere, and vCenter licenses. VMware licenses can only be removed from the order if it is confirmed that the end-customer has valid licenses in place (Enterprise License Agreement (ELA), vCloud Air Partner or unused Enterprise Purchasing Program tokens).

Purchasing VMware licenses from Hewlett Packard Enterprise allows Hewlett Packard Enterprise to be the single point of contact for the entire solution, inclusive of the virtualization software, and is recommended.

**NOTE:** HPE SimpliVity 380 Gen10 for Microsoft Hyper-V requires valid Microsoft Hyper-V Server, and Systems Center Virtual Machine Manager licenses. Microsoft licenses can only be removed from the order if it is confirmed that the end-customer has valid licenses in place.

**NOTE:** Purchasing Microsoft licenses from Hewlett Packard Enterprise allows Hewlett Packard Enterprise to be the single point of contact for the entire solution inclusive of the virtualization software and is recommended.

#### Management

- HPE InfoSight
- VMware vCenter
- HPE SimpliVity management plugin for VMware vCenter
- Microsoft System Center
- HPE SimpliVity management plugin for Microsoft System Center

**NOTE:** The HPE SimpliVity 380 supports VMware vCenter 6.5 and 6.7

**NOTE:** For VMware and HW compatibility, please visit <http://www.hpe.com/docs/simplivity-library> or <https://www.hpe.com/info/simplivity-interop-doc>

---

## Service and Support

Services for customers purchasing from Hewlett Packard Enterprise or an enterprise reseller are quoted using Hewlett Packard Enterprise order configuration tools.

### **HPE Proactive Care for HPE SimpliVity (choose the response level that meets your needs)**

HPE Proactive Care for HPE SimpliVity was designed to help meet your support needs effectively and efficiently. Receive all the benefits of HPE Proactive Care (details are below) plus access specific self-serve tools, usage support, predictive notifications, and technical expertise that will give you control to manage your HPE SimpliVity solution and keep it reliable, stable, and at peak performance. Use the HPE SimpliVity forums with committed response time to answer questions or for questions where you where want community feedback. Access how to videos, best practices from support experts to address common challenges, or find out about beneficial hints and tips. Ask HPE SimpliVity solution operational questions with HPE Proactive Care for HPE SimpliVity.

HPE Proactive Care gives customers an enhanced call experience. When your products are connected to HPE, Proactive Care helps prevent problems and maintains IT stability by utilizing personalized proactive reports with recommendations and advice. HPE Proactive Care is available in 3, 4, and 5 year terms with a choice of response levels: Next Business day (NBD), 24x7 with a 4 hour response, and 24x7 with 6 hour call to repair (CTR). This Service combines both reactive support when there is a problem with an enhanced call experience and start to finish case management with proactive reporting and advice. This service also includes collaborative software support for Independent Software Vendors (ISVs), (Red Hat, VMWare, Microsoft, etc.).

<https://www.hpe.com/h20195/v2/GetPDF.aspx/4AA3-8855ENW.pdf>

HPE Proactive Care Advanced incorporates all the deliverables of HPE Proactive Care for HPE SimpliVity plus includes personalized support from a local, assigned Account Support Manager who will share best practice advice and personalized recommendations designed to help improve availability and performance to help increase stability and reduce unplanned downtime. Leverage your system's ability to connect to HPE for pre-failure alerts, automatic call logging and parts dispatch. For business-critical incidents, Proactive Care Advanced offers critical event management to help reduce mean time to resolution. HPE Service Credits are included to redeem for technical and operational services. HPE Proactive Care Advanced is offered in 3, 4, and 5 year terms with a choice of response levels: Next Business day (NBD), 24x7 with a 4 hour response, and 24x7 with 6 hour call to repair (CTR).

<https://www.hpe.com/h20195/v2/getdocument.aspx?docname=4AA5-3259ENW>

**NOTE:** HPE Proactive Care and HPE Proactive Care Advanced require that the customer connect their devices to HPE to help make the most of these services and receive all the deliverables.

---

### **HPE Foundation Care – (choose the response level that meets your needs)**

HPE Foundation Care helps when there is a problem and is available in 3, 4, and 5 year terms with a choice of response levels: Next Business day (NBD), 24x7 with a 4 hour response, and 24x7 with 6 hour call to repair (CTR). Note that Call-To-Repair Service connects you to HPE 24 hours a day, seven days a week for assistance on resolving issues -this includes our highest level commitment to repair hardware within six hours after opening your case and respond to software questions within two hours. In addition, Collaborative software support is included and provides troubleshooting assistance on industry leading software running on your server. Simplify your support experience and make HPE your first call to help resolve hardware or software problems.

<https://www.hpe.com/h20195/V2/GetDocument.aspx?docname=4AA4-8876ENW&cc=us&lc=en>

---

---

## Service and Support

### Other Related Services

#### HPE Server Hardware Installation

Provides for the basic hardware installation of HPE branded servers, storage devices and networking options to assist you in bringing your new hardware into operation in a timely and professional manner.

<http://h20195.www2.hp.com/V2/GetPDF.aspx/5981-9356EN.pdf>

---

#### HPE Installation and Startup Service

Provides for the installation of your HPE hardware according to product specifications including options. The HPE service delivery technician will connect the product to a LAN as appropriate and enable remote support to allow for automatic case creation for hardware failures. Installation and start up services also includes the installation of one supported operating system type (Windows® or Linux)

---

#### HPE Service Credits

Offers flexible services and technical skills to meet your IT demands as your business evolves. With a menu of services, you can access additional resources and specialist skills to help you maintain peak performance of your IT. HPE Service Credits help you proactively respond to your dynamic IT and business needs.

---

#### HPE Education Services

Provides comprehensive training designed to expand the skills of your IT staff and keep them up to speed with the latest technologies.

Consult your HPE Sales Representative or Authorized Channel Partner of choice for any additional questions and support options.

---

#### Parts and Materials

Hewlett Packard Enterprise will provide HPE-supported replacement parts and materials necessary to maintain the covered hardware product in operating condition, including parts and materials for available and recommended engineering improvements.

Parts and components that have reached their maximum supported lifetime and/or the maximum usage limitations as set forth in the manufacturer's operating manual, product quick-specs, or the technical product data sheet will not be provided, repaired, or replaced as part of these services.

The defective media retention service feature option applies only to Disk or eligible SSD/Flash Drives replaced by Hewlett Packard Enterprise due to malfunction.

## Configuration Information

### HPE SimpliVity 380 Gen10: Overview for New System

Use the following steps to order a new SimpliVity 380 Gen10 system:

Step 1: Begin with the base node and select a hypervisor option

Step 2: Select the hardware options to add to the base node: processors, memory, storage, networking, power, other optional HW

Step 3: The software license that corresponds to the node configuration will be automatically added

Step 4: Select service and support

#### Base Node

Action	Description	Part #
Select the base node	HPE SimpliVity 380 Gen10 Node	Q8D81A
Select Hypervisor	VMware ESXi Option	#001
Option	Microsoft Hyper-V Option	#002

#### Processors

##### CPU Configurations

Action	Details	Description	CPU SKU
Select CPUs for the node	<b>Primary</b> 8C 2.1GHz 85W	HPE DL380 Gen10 Intel Xeon-Silver 4110 (2.1GHz/8-core/85W) FIO Processor Kit	826846-L21
	8C 1.8GHz 85W	HPE DL380 Gen10 Intel Xeon-Silver 4108 (1.8GHz/8-core/85W) FIO Processor Kit	826848-L21
1st Generation Intel® Xeon® Scalable Processors	10C 2.2GHz 85W	HPE DL380 Gen10 Intel Xeon-Silver 4114 (2.2GHz/10-core/85W) FIO Processor Kit	826850-L21
	12C 2.1GHz 85W	HPE DL380 Gen10 Intel Xeon-Silver 4116 (2.1GHz/12-core/85W) FIO Processor Kit	826852-L21
In the case of Single CPU only L21 SKU will be included by the configurator.	12C 2.3GHz 105W	HPE DL380 Gen10 Intel Xeon-Gold 5118 (2.3GHz/12-core/105W) FIO Processor Kit	826854-L21
	14C 2.2GHz 105W	HPE DL380 Gen10 Intel Xeon-Gold 5120 (2.2GHz/14-core/105W) FIO Processor Kit	826856-L21
In the case of dual CPU: both the L21 and the B21 SKU will be included by the configurator	12C 2.6GHz 125W	HPE DL380 Gen10 Intel Xeon-Gold 6126 (2.6GHz/12-core/120W) FIO Processor Kit	826862-L21
	16C 2.1GHz 125W	HPE DL380 Gen10 Intel Xeon-Gold 6130 (2.1GHz/16-core/120W) FIO Processor Kit	826866-L21
	14C 2.6GHz 140W	HPE DL380 Gen10 Intel Xeon-Gold 6132 (2.6GHz/14-core/140W) FIO Processor Kit	826870-L21
	18C 2.3GHz 140W	HPE DL380 Gen10 Intel Xeon-Gold 6140 (2.3GHz/18-core/140W) FIO Processor Kit	826878-L21
	18C 2.7GHz 165W	HPE DL380 Gen10 Intel Xeon-Gold 6150 (2.7GHz/18-core/165W) FIO Processor Kit	826884-L21
	18C 3.0GHz 200W	HPE DL380 Gen10 Intel Xeon-Gold 6154 (3.0GHz/18-core/200W) FIO Processor Kit	826888-L21
	10C 2.4GHz 85W	HPE DL380 Gen10 Intel Xeon-Gold 5115 (2.4GHz/10-core/85W) FIO Processor Kit	876562-L21
	22C 2.1GHz 140W	HPE DL380 Gen10 Intel Xeon-Gold 6152 (2.1GHz/22-core/140W) FIO Processor Kit	826886-L21
	8C 3.2GHz 130W	HPE DL380 Gen10 Intel Xeon-Gold 6134 (3.2GHz/8-core/130W) FIO Processor Kit	826872-L21
	16C 2.6GHz 150W	HPE DL380 Gen10 Intel Xeon-Gold 6142 (2.6GHz/16-core/150W) FIO Processor Kit	826880-L21
	8C 3.5GHz 150W	HPE DL380 Gen10 Intel Xeon-Gold 6144 (3.5GHz/8-core/150W) FIO Processor Kit	826860-L21
	12C 3.2GHz 165W	HPE DL380 Gen10 Intel Xeon-Gold 6146 (3.2GHz/12-core/165W) FIO Processor Kit	826868-L21

## Configuration Information

12C 3.0GHz 150W	HPE DL380 Gen10 Intel Xeon-Gold 6136 (3.0GHz/12-core/150W) FIO Processor Kit	826874-L21
12C 3.0GHz 150W	HPE DL380 Gen10 Intel Xeon-Platinum 8158 (3.0GHz/12-core/150W) FIO Processor Kit	869090-L21
16C 2.0GHz 125W	HPE DL380 Gen10 Intel Xeon-Platinum 8153 (2.0GHz/16-core/125W) FIO Processor Kit	826890-L21
20C 2.0GHz 125W	HPE DL380 Gen10 Intel Xeon-Gold 6138 (2.0GHz/20-core/125W) FIO Processor Kit	826876-L21
20C 2.4GHz 150W	HPE DL380 Gen10 Intel Xeon-Gold 6148 (2.4GHz/20-core/150W) FIO Processor Kit	826882-L21
28C 2.5GHz 205W	HPE DL380 Gen10 Intel Xeon-Platinum 8180 (2.5GHz/28-core/205W) FIO Processor Kit	871619-L21
24C 2.7GHz 205W	HPE DL380 Gen10 Intel Xeon-Platinum 8168 (2.7GHz/24-core/205W) FIO Processor Kit	869089-L21
24C, 2.3GHz, 205W	HPE DL380 Gen10 Intel Xeon-Platinum 8165 (2.3GHz/24-core/205W) FIO Processor Kit	879423-L21
26C 2.1GHz 165W	HPE DL380 Gen10 Intel Xeon-Platinum 8170 (2.1GHz/26-core/165W) FIO Processor Kit	871617-L21
28C 2.1GHz 165W	HPE DL380 Gen10 Intel Xeon-Platinum 8176 (2.1GHz/28-core/165W) FIO Processor Kit	871618-L21
14C 2.0GHz 105W	HPE DL380 Gen10 Intel Xeon-Gold 5117 (2.0GHz/14-core/105W) FIO Processor Kit	P00756-L21
16C 2.8GHz 205W	HPE DL380 Gen10 Intel Xeon-Gold 6143 (2.8GHz/16-core/205W) FIO Processor Kit	879424-L21
24C 2.1GHz 150W	HPE DL380 Gen10 Intel Xeon-Platinum 8160 (2.1GHz/24-core/150W) FIO Processor Kit	869086-L21
26C 2.0GHz 150W	HPE DL380 Gen10 Intel Xeon-Platinum 8164 (2.0GHz/26-core/145W) FIO Processor Kit	869088-L21

### Secondary

8C 2.1GHz 85W	HPE DL380 Gen10 Intel Xeon-Silver 4110 (2.1GHz/8-core/85W) Processor Kit	826846-B21
8C 1.8GHz 85W	HPE DL380 Gen10 Intel Xeon-Silver 4108 (1.8GHz/8-core/85W) Processor Kit	826848-B21
10C 2.2GHz 85W	HPE DL380 Gen10 Intel Xeon-Silver 4114 (2.2GHz/10-core/85W) Processor Kit	826850-B21
12C 2.1GHz 85W	HPE DL380 Gen10 Intel Xeon-Silver 4116 (2.1GHz/12-core/85W) Processor Kit	826852-B21
12C 2.3GHz 105W	HPE DL380 Gen10 Intel Xeon-Gold 5118 (2.3GHz/12-core/105W) Processor Kit	826854-B21
14C 2.2GHz 105W	HPE DL380 Gen10 Intel Xeon-Gold 5120 (2.2GHz/14-core/105W) Processor Kit	826856-B21
12C 2.6GHz 125W	HPE DL380 Gen10 Intel Xeon-Gold 6126 (2.6GHz/12-core/120W) Processor Kit	826862-B21
16C 2.1GHz 125W	HPE DL380 Gen10 Intel Xeon-Gold 6130 (2.1GHz/16-core/120W) Processor Kit	826866-B21
14C 2.6GHz 140W	HPE DL380 Gen10 Intel Xeon-Gold 6132 (2.6GHz/14-core/140W) Processor Kit	826870-B21
18C 2.3GHz 140W	HPE DL380 Gen10 Intel Xeon-Gold 6140 (2.3GHz/18-core/140W) Processor Kit	826878-B21
18C 2.7GHz 165W	HPE DL380 Gen10 Intel Xeon-Gold 6150 (2.7GHz/18-core/165W) Processor Kit	826884-B21
18C 3.0GHz 200W	HPE DL380 Gen10 Intel Xeon-Gold 6154 (3.0GHz/18-core/200W) Processor Kit	826888-B21
10C 2.4GHz 85W	HPE DL380 Gen10 Intel Xeon-Gold 5115 (2.4GHz/10-core/85W) Processor Kit	876562-B21

## Configuration Information

22C 2.1GHz 140W	HPE DL380 Gen10 Intel Xeon-Gold 6152 (2.1GHz/22-core/140W) Processor Kit	826886-B21
8C 3.2GHz 130W	HPE DL380 Gen10 Intel Xeon-Gold 6134 (3.2GHz/8-core/130W) Processor Kit	826872-B21
16C 2.6GHz 150W	HPE DL380 Gen10 Intel Xeon-Gold 6142 (2.6GHz/16-core/150W) Processor Kit	826880-B21
8C 3.5GHz 150W	HPE DL380 Gen10 Intel Xeon-Gold 6144 (3.5GHz/8-core/150W) Processor Kit	826860-B21
12C 3.2GHz 165W	HPE DL380 Gen10 Intel Xeon-Gold 6146 (3.2GHz/12-core/165W) Processor Kit	826868-B21
12C 3.0GHz 150W	HPE DL380 Gen10 Intel Xeon-Gold 6136 (3.0GHz/12-core/150W) Processor Kit	826874-B21
12C 3.0GHz 150W	HPE DL380 Gen10 Intel Xeon-Platinum 8158 (3.0GHz/12-core/150W) Processor Kit	869090-B21
16C 2.0GHz 125W	HPE DL380 Gen10 Intel Xeon-Platinum 8153 (2.0GHz/16-core/125W) Processor Kit	826890-B21
20C 2.0GHz 125W	HPE DL380 Gen10 Intel Xeon-Gold 6138 (2.0GHz/20-core/125W) Processor Kit	826876-B21
20C 2.4GHz 150W	HPE DL380 Gen10 Intel Xeon-Gold 6148 (2.4GHz/20-core/150W) Processor Kit	826882-B21
28C 2.5GHz 205W	HPE DL380 Gen10 Intel Xeon-Platinum 8180 (2.5GHz/28-core/205W) Processor Kit	871619-B21
24C 2.7GHz 205W	HPE DL380 Gen10 Intel Xeon-Platinum 8168 (2.7GHz/24-core/205W) Processor Kit	869089-B21
24C, 2.3GHz, 205W	HPE DL380 Gen10 Intel Xeon-Platinum 8165 (2.3GHz/24-core/205W) Processor Kit	879423-B21
26C 2.1GHz 165W	HPE DL380 Gen10 Intel Xeon-Platinum 8170 (2.1GHz/26-core/165W) Processor Kit	871617-B21
28C 2.1GHz 165W	HPE DL380 Gen10 Intel Xeon-Platinum 8176 (2.1GHz/28-core/165W) Processor Kit	871618-B21
14C 2.0GHz 105W	HPE DL380 Gen10 Intel Xeon-Gold 5117 (2.0GHz/14-core/105W) Processor Kit	P00756-B21
16C 2.8GHz 205W	HPE DL380 Gen10 Intel Xeon-Gold 6143 (2.8GHz/16-core/205W) Processor Kit	879424-B21
24C 2.1GHz 150W	HPE DL380 Gen10 Intel Xeon-Platinum 8160 (2.1GHz/24-core/150W) Processor Kit	869086-B21
26C 2.0GHz 150W	HPE DL380 Gen10 Intel Xeon-Platinum 8164 (2.0GHz/26-core/145W) Processor Kit	869088-B21

## Configuration Information

### Memory

Action	Details	Description	SKU
Select a memory capacity for the node	6x 8GB AND 6x 16GB RDIMMs	HPE SimpliVity 144G 12 DIMM FIO Kit	Q8D82A
The appropriate memory and quantity will be included by the configurator	12x 16GB RDIMMs	HPE SimpliVity 192G 12 DIMM FIO Kit	Q8D83A
	6x 32GB RDIMMs	HPE SimpliVity 192G 6 DIMM FIO Kit	Q8D84A
	6x 32GB AND 6x 8GB RDIMMs	HPE SimpliVity 240G 12 DIMM FIO Kit	Q8D85A
	6x 32GB AND 6x 16GB RDIMMs	HPE SimpliVity 288G 12 DIMM FIO Kit	Q8D86A
	1 Kit required per CPU	12x 32GB RDIMMs	HPE SimpliVity 384G 12 DIMM FIO Kit
	6x 64GB LRDIMMs	HPE SimpliVity 384G 6 DIMM FIO Kit	Q8D88A
	12x 64GB LRDIMMs	HPE SimpliVity 768G 12 DIMM FIO Kit	Q8D89A

**NOTE:** For more information go to: <http://www.hpe.com/docs/memory-population-rules>

### Storage

Effective capacity varies by environment and is a function of realized deduplication and compression rates. The capacities in this table offer a conservative range based on compression and deduplication rates found in standard, primary storage use cases.

Action	Effective Capacity	Description	Part #
Select one storage kit for the node	3-6TB	HPE SimpliVity 380 for 4000 Series Extra Small Storage Kit	Q8D90A
	6-12 TB	HPE SimpliVity 380 for 4000 Series Small Storage Kit	Q8D91A
	12-25TB	HPE SimpliVity 380 for 4000 Series Medium Storage Kit	Q8D92A
The appropriate OmniStack software will be included by the configurator	20-40TB	HPE SimpliVity 380 for 4000 Series Large Storage Kit	Q8D93A
	40-80TB	HPE SimpliVity 380 for 4000 Series Extra Large Storage Kit	Q9J90A
	3-6TB	HPE SimpliVity 380 for 6000 Series Extra Small Storage Kit	Q8D94A
	6-12 TB	HPE SimpliVity 380 for 6000 Series Small Storage Kit	Q5V86A
	12-25TB	HPE SimpliVity 380 for 6000 Series Medium Storage Kit	Q5V87A
	20-40TB	HPE SimpliVity 380 for 6000 Series Large Storage Kit	Q5V88A

### Networking

Action	Description	Part #
A 10GbE FlexLOM is required. This is in addition to the standard 4 port 1GbE LOM included in the base node	HPE FlexFabric 10Gb 2-port 534FLR-SFP+ Adapter	700751-B21
	HPE FlexFabric 10Gb 2-port 533FLR-T Adapter	700759-B21
	HPE Ethernet 10/25Gb 2-port 640FLR-SFP28 Adapter	817749-B21
	HPE FlexFabric 10Gb 4-port 536FLR-T Adapter	764302-B21

### PCI Adapter

Action	System Max	Description	Part #
Additional PCI Adapters can be added in the case of dual socket with secondary riser.	3	HPE Ethernet 1Gb 4-port 331T Adapter	647594-B21
	3	HPE Ethernet 10Gb 2-port 530SFP Adapter	652503-B21
	3	HPE Ethernet 10Gb 2-port 530T Adapter	656596-B21
	3	HPE Ethernet 1Gb 4-port 366T Adapter	811546-B21
	3	HPE Ethernet 10/25Gb 2-port 640SFP28 Adapter	817753-B21

## Configuration Information

### Optional Fibre Channel HBA cards

Action	System Max	Description	Part #
Optional FC HBAs may be added if slots are available	3	HPE StoreFabric SN1100Q 16Gb Dual Port Fibre Channel Host Bus Adapter	P9D94A
	3	HPE StoreFabric SN1600Q 32Gb Dual Port Fibre Channel Host Bus Adapter	P9M76A

### Optional GPUs

Action	System Max	Description	Part #
Optional Graphic Accelerator (1) may be added in the case of dual CPU with secondary riser	1	NVIDIA Tesla M10 Quad GPU Module	Q0J62A
	1	HPE NVIDIA Tesla P40 24GB Computational Accelerator	Q0V80A
	1	HPE NVIDIA Tesla T4 16GB Computational Accelerator	ROW29A

## Configuration Information

### Power Supplies

Action	Description	Part #
Two power supplies are required.	HPE 800W Flex Slot Platinum Hot Plug Low Halogen Power Supply Kit	865414-B21
	HPE 800W Flex Slot Universal Hot Plug Low Halogen Power Supply Kit	865428-B21
	HPE 800W Flex Slot -48VDC Hot Plug Low Halogen Power Supply Kit	865434-B21
	HPE 800W Flex Slot Titanium Hot Plug Low Halogen Power Supply Kit	865438-B21
	HPE 1600W Flex Slot Platinum Hot Plug Low Halogen Power Supply Kit	830272-B21

**NOTE:** The power supply requirement can vary based configuration and environment. 800W Power Supply is only supported with specific configurations. Please refer to HPE Power Advisor for proper power sizing.

**NOTE:** All configured nodes ship with a standard 6-foot IEC C-13/C-14 jumper cord (A0K02A). This jumper cord is also included with each standard AC power supply option kit. If a different power cord is required, please check the ProLiant Power Cables web page. <https://h20195.www2.hpe.com/v2/getpdf.aspx/4AA6-6836ENW.pdf>

### Power Cord Options

Action	Description	Part #
Additional hardware options are available	HPE C13 - GB-1002 CN 250V 10Amp 1.83m Power Cord	AF557A
	HPE C13 - KSC- 8305 KR 250V 10Amp 1.83m Power Cord	AF560A
	HPE C13 - CNS-690 TW 110V 13Amp 1.83m Power Cord	AF561A
	HPE C13 - IS-1293 IN 240V 6Amp LV 2.0m Power Cord	AF562A
	HPE SAFDGRID-SAFDGRID 277V 15Amp DC 2.0m Jumper Cord	J6X00A
	HPE SAFDGRID-LS-25 277V 15Amp AC 2.0m Jumper Cord	J6X03A
	HPE No Plug 12AWG 48V DC 3.0m Power Cord	J6X43A
	HPE 48VDC 2.85m Power Cable	QOH80A
	HPE C13 - IS-1293 IN 250V 10Amp HV 2.5m Power Cord	SG579A
	HPE C13 - Nema 5-15P US/CA 110V 10Amp 1.83m Power Cord	AF556A
	HPE C13 - IRAM -2073 AR 250V 10A 2.5m Power Cord	AF558A
	HPE C13 - Nema 5-15P TH/PH 250V 10Amp 1.83m Power Cord	AF559A
	HPE C13 - SEV 1011 CH 250V 10Amp 1.83m Power Cord	AF565A
	HPE C13 - DK-2.5A DK 250V 10Amp 1.83m Power Cord	AF566A
	HPE C13 - CEE-VII EU 250V 10Amp 1.83m Power Cord	AF568A
	HPE C13 - AS3112-3 AU 250V 10Amp 2.5m Power Cord	AF569A
	HPE C13 - SI-32 IL 250V 10Amp 1.83m Power Cord	AF564A
HPE C13 - JIS C8303 JP 100V 12Amp 2.0m Power Cord	AF572A	
HPE C13 - BS-1363A UK/HK/SG 250V 10Amp 1.83m Power Cord	AF570A	

**NOTE:** Network cables and transceivers are available in the Aruba and DataCenter Networking menus.

**NOTE:** Information on interoperability between network adapters, transceivers, and cables is available in network adapter QuickSpecs.

**NOTE:** For more information on HPE rack enclosures, review the QuickSpecs at: <https://www.hpe.com/us/en/product-catalog/servers/server-racks.hits-12.html>.

### Additional Server Options

Action	Description	Part #
Additional hardware options are available	HPE DL380 Gen10 SFF Systems Insight Display Kit	826703-B21
	HPE DL3XX Gen10 Rear Serial Cable and Enablement Kit	873770-B21
	HPE 2U Small Form Factor Ball Bearing Rail Kit	720863-B21
	HPE 2U Cable Management Arm for Ball Bearing Rail Kit	720865-B21
	HPE 2U Small Form Factor Easy Install Rail Kit	733660-B21

## Configuration Information

### HPE OmniStack Software

Action	Description	Part #
Based on the hardware configurations selected, the appropriate software will be included by the configurator.	HPE OmniStack 1P Extra Small SW	Q8A57A
	HPE OmniStack 2P Extra Small SW	Q8A58A
	HPE OmniStack 1P Small SW	Q8A59A
	HPE OmniStack 2P Small SW	Q8A60A
	HPE OmniStack 1P Medium SW	Q8A61A
	HPE OmniStack 2P Medium SW	Q8A62A
The software is determined by CPU and storage configuration and is required.	HPE OmniStack 1P Large SW	Q8A63A
	HPE OmniStack 2P Large SW	Q8A64A
	HPE OmniStack 1P Extra Large SW	Q9J86A
	HPE OmniStack 2P Extra Large SW	Q9J87A

### VMware Software

#### vSphere

**NOTE:** The HPE SimpliVity 380 supports VMware vSphere 6.5 and 6.7

**NOTE:** For VMware and HW compatibility, please see the interoperability guide [HPE SimpliVity OmniStack Interoperability Guide](#) or [www.hpe.com/docs/simplivity-library](http://www.hpe.com/docs/simplivity-library)

Action	Description	Part #
A valid VMware vSphere license is required for each CPU to complete deployment.	VMware vSphere Standard 1 Processor 3yr E-LTU	BD711AAE
	VMware vSphere Enterprise Plus 1 Processor 3yr Software	BD715A
	VMware vSphere Enterprise Plus 1 Processor 3yr E-LTU	BD715AAE
	VMware vSphere Remote Office Branch Office Standard 25VM 3yr E-LTU	P9A82AAE
	VMware vSphere Remote Office Branch Office Advanced 25VM 3yr E-LTU	P9A85AAE
	VMware vSphere Standard 1 Processor 5yr Software	BD512A
If an order is placed without VMware licenses, the user agrees to supply the necessary license.	VMware vSphere Standard 1 Processor 5yr E-LTU	BD512AAE
	VMware vSphere Enterprise Plus 1 Processor 5yr Software	BD514A
	VMware vSphere Enterprise Plus 1 Processor 5yr E-LTU	BD514AAE

**NOTE:** HPE SimpliVity 380 Gen10 for VMware vSphere requires valid VMware vSphere, and vCenter licenses. VMware licenses can only be removed from the order if it is confirmed that the end-customer has a valid licenses in place (Enterprise License Agreement (ELA), vCloud Air Partner or unused Enterprise Purchasing Program tokens).

**NOTE:** Purchasing VMware licenses from Hewlett Packard Enterprise allows Hewlett Packard Enterprise to be the single point of contact for the entire solution inclusive of the virtualization software and is recommended. When the VMware license is not included on the order the solution level support experience is impacted.

## Configuration Information

### vCenter

Action	Description	Part #
Optional vCenter License	VMware vCenter Server Standard for vSphere (per Instance) 3yr E-LTU	P9U41AAE
	VMware vCenter Server Standard for vSphere (per Instance) 5yr E-LTU	P9U42AAE

**NOTE:** The HPE SimpliVity 380 supports VMware vCenter 6.5 and 6.7

**NOTE:** For VMware and HW compatibility, please see the <https://www.hpe.com/info/simplivity-interop-doc> or <http://www.hpe.com/docs/simplivity-library>

**NOTE:** The customer is responsible for ensuring licensing compliance on all running virtual machines. Licenses may be added to the order as standalone items from the catalog. Licenses added at the node level will be cloned with the node.

**NOTE:** Information on available licenses for non-preinstalled Operating Systems can be found on the relevant product pages:

- Microsoft Windows Server 2016: <https://www.hpe.com/us/en/product-catalog/detail/pip.microsoft-windows-server-2016.1009480090.html>
- Red Hat Enterprise Linux: <https://www.hpe.com/us/en/product-catalog/detail/pip.5393115.html>
- SUSE Linux Enterprise Server: <https://www.hpe.com/us/en/product-catalog/detail/pip.5379857.html>

---

### HPE Integrated Lights Out Advanced Software (iLO Advanced)

Action	Description	Part #
The HPE iLO Advanced license is required	HPE iLO Advanced 1-server License with 3yr Support on iLO Licensed Features	BD505A

---

## Configuration Information

### HPE SimpliVity 380 Gen10 G: Overview for New System

Use the following steps to order a new SimpliVity 380 Gen10 system:

Step 1: Begin with the base node and select a hypervisor option

Step 2: Select the hardware options to add to the base node: processors, memory, storage, networking, power, other optional HW

Step 3: The software license that corresponds to the node configuration will be automatically added

Step 4: Select service and support

#### Base Node

Action	Description	Part #
Select the base node	HPE SimpliVity 380 Gen10 G Node	R2G96A
Hypervisor tracking SKU added automatically	HPE SimpliVity 380 Gen10 VMware Node Tracking	R2G97A

#### Processors

##### CPU Configurations

Action	Details	Description	CPU SKU
Select CPUs for the node	<b>Primary</b> 8C 2.1GHz 85W	HPE DL380 Gen10 Intel Xeon-Silver 4110 (2.1GHz/8-core/85W) FIO Processor Kit	826846-L21
1st Generation Intel® Xeon® Scalable Processors	8C 1.8GHz 85W	HPE DL380 Gen10 Intel Xeon-Silver 4108 (1.8GHz/8-core/85W) FIO Processor Kit	826848-L21
	10C 2.2GHz 85W	HPE DL380 Gen10 Intel Xeon-Silver 4114 (2.2GHz/10-core/85W) FIO Processor Kit	826850-L21
In the case of Single CPU only L21 SKU will be included by the configurator.	12C 2.1GHz 85W	HPE DL380 Gen10 Intel Xeon-Silver 4116 (2.1GHz/12-core/85W) FIO Processor Kit	826852-L21
	12C 2.3GHz 105W	HPE DL380 Gen10 Intel Xeon-Gold 5118 (2.3GHz/12-core/105W) FIO Processor Kit	826854-L21
	14C 2.2GHz 105W	HPE DL380 Gen10 Intel Xeon-Gold 5120 (2.2GHz/14-core/105W) FIO Processor Kit	826856-L21
In the case of dual CPU: both the L21 and the B21 SKU will be included by the configurator	12C 2.6GHz 125W	HPE DL380 Gen10 Intel Xeon-Gold 6126 (2.6GHz/12-core/120W) FIO Processor Kit	826862-L21
	16C 2.1GHz 125W	HPE DL380 Gen10 Intel Xeon-Gold 6130 (2.1GHz/16-core/120W) FIO Processor Kit	826866-L21
	14C 2.6GHz 140W	HPE DL380 Gen10 Intel Xeon-Gold 6132 (2.6GHz/14-core/140W) FIO Processor Kit	826870-L21
	18C 2.3GHz 140W	HPE DL380 Gen10 Intel Xeon-Gold 6140 (2.3GHz/18-core/140W) FIO Processor Kit	826878-L21
	18C 2.7GHz 165W	HPE DL380 Gen10 Intel Xeon-Gold 6150 (2.7GHz/18-core/165W) FIO Processor Kit	826884-L21
	18C 3.0GHz 200W	HPE DL380 Gen10 Intel Xeon-Gold 6154 (3.0GHz/18-core/200W) FIO Processor Kit	826888-L21
	10C 2.4GHz 85W	HPE DL380 Gen10 Intel Xeon-Gold 5115 (2.4GHz/10-core/85W) FIO Processor Kit	876562-L21
	22C 2.1GHz 140W	HPE DL380 Gen10 Intel Xeon-Gold 6152 (2.1GHz/22-core/140W) FIO Processor Kit	826886-L21
	8C 3.2GHz 130W	HPE DL380 Gen10 Intel Xeon-Gold 6134 (3.2GHz/8-core/130W) FIO Processor Kit	826872-L21
	16C 2.6GHz 150W	HPE DL380 Gen10 Intel Xeon-Gold 6142 (2.6GHz/16-core/150W) FIO Processor Kit	826880-L21
	8C 3.5GHz 150W	HPE DL380 Gen10 Intel Xeon-Gold 6144 (3.5GHz/8-core/150W) FIO Processor Kit	826860-L21

## Configuration Information

12C 3.2GHz 165W	HPE DL380 Gen10 Intel Xeon-Gold 6146 (3.2GHz/12-core/165W) FIO Processor Kit	826868-L21
12C 3.0GHz 150W	HPE DL380 Gen10 Intel Xeon-Gold 6136 (3.0GHz/12-core/150W) FIO Processor Kit	826874-L21
12C 3.0GHz 150W	HPE DL380 Gen10 Intel Xeon-Platinum 8158 (3.0GHz/12-core/150W) FIO Processor Kit	869090-L21
16C 2.0GHz 125W	HPE DL380 Gen10 Intel Xeon-Platinum 8153 (2.0GHz/16-core/125W) FIO Processor Kit	826890-L21
20C 2.0GHz 125W	HPE DL380 Gen10 Intel Xeon-Gold 6138 (2.0GHz/20-core/125W) FIO Processor Kit	826876-L21
20C 2.4GHz 150W	HPE DL380 Gen10 Intel Xeon-Gold 6148 (2.4GHz/20-core/150W) FIO Processor Kit	826882-L21
28C 2.5GHz 205W	HPE DL380 Gen10 Intel Xeon-Platinum 8180 (2.5GHz/28-core/205W) FIO Processor Kit	871619-L21
24C 2.7GHz 205W	HPE DL380 Gen10 Intel Xeon-Platinum 8168 (2.7GHz/24-core/205W) FIO Processor Kit	869089-L21
24C, 2.3GHz, 205W	HPE DL380 Gen10 Intel Xeon-Platinum 8165 (2.3GHz/24-core/205W) FIO Processor Kit	879423-L21
26C 2.1GHz 165W	HPE DL380 Gen10 Intel Xeon-Platinum 8170 (2.1GHz/26-core/165W) FIO Processor Kit	871617-L21
28C 2.1GHz 165W	HPE DL380 Gen10 Intel Xeon-Platinum 8176 (2.1GHz/28-core/165W) FIO Processor Kit	871618-L21
14C 2.0GHz 105W	HPE DL380 Gen10 Intel Xeon-Gold 5117 (2.0GHz/14-core/105W) FIO Processor Kit	P00756-L21
16C 2.8GHz 205W	HPE DL380 Gen10 Intel Xeon-Gold 6143 (2.8GHz/16-core/205W) FIO Processor Kit	879424-L21
24C 2.1GHz 150W	HPE DL380 Gen10 Intel Xeon-Platinum 8160 (2.1GHz/24-core/150W) FIO Processor Kit	869086-L21
26C 2.0GHz 150W	HPE DL380 Gen10 Intel Xeon-Platinum 8164 (2.0GHz/26-core/145W) FIO Processor Kit	869088-L21
28C 2.5GHz 205W	HPE DL380 Gen10 Intel Xeon-Platinum 8180M (2.5GHz/28-core/205W) FIO Processor Kit	874752-L21
8C 3.2GHz 130W	HPE DL380 Gen10 Intel Xeon-Gold 6134M (3.2GHz/8-core/130W) FIO Processor Kit	873645-L21
24C, 2.3GHz, 205W	HPE DL380 Gen10 Intel Xeon-Platinum 8165 (2.3GHz/24-core/205W) FIO Processor Kit	879423-L21
<b>Secondary</b>		
8C 2.1GHz 85W	HPE DL380 Gen10 Intel Xeon-Silver 4110 (2.1GHz/8-core/85W) Processor Kit	826846-B21
8C 1.8GHz 85W	HPE DL380 Gen10 Intel Xeon-Silver 4108 (1.8GHz/8-core/85W) Processor Kit	826848-B21
10C 2.2GHz 85W	HPE DL380 Gen10 Intel Xeon-Silver 4114 (2.2GHz/10-core/85W) Processor Kit	826850-B21
12C 2.1GHz 85W	HPE DL380 Gen10 Intel Xeon-Silver 4116 (2.1GHz/12-core/85W) Processor Kit	826852-B21
12C 2.3GHz 105W	HPE DL380 Gen10 Intel Xeon-Gold 5118 (2.3GHz/12-core/105W) Processor Kit	826854-B21
14C 2.2GHz 105W	HPE DL380 Gen10 Intel Xeon-Gold 5120 (2.2GHz/14-core/105W) Processor Kit	826856-B21
12C 2.6GHz 125W	HPE DL380 Gen10 Intel Xeon-Gold 6126 (2.6GHz/12-core/120W) Processor Kit	826862-B21
16C 2.1GHz 125W	HPE DL380 Gen10 Intel Xeon-Gold 6130 (2.1GHz/16-core/120W) Processor Kit	826866-B21
14C 2.6GHz 140W	HPE DL380 Gen10 Intel Xeon-Gold 6132 (2.6GHz/14-core/140W) Processor Kit	826870-B21

## Configuration Information

18C 2.3GHz 140W	HPE DL380 Gen10 Intel Xeon-Gold 6140 (2.3GHz/18-core/140W) Processor Kit	826878-B21
18C 2.7GHz 165W	HPE DL380 Gen10 Intel Xeon-Gold 6150 (2.7GHz/18-core/165W) Processor Kit	826884-B21
18C 3.0GHz 200W	HPE DL380 Gen10 Intel Xeon-Gold 6154 (3.0GHz/18-core/200W) Processor Kit	826888-B21
10C 2.4GHz 85W	HPE DL380 Gen10 Intel Xeon-Gold 5115 (2.4GHz/10-core/85W) Processor Kit	876562-B21
22C 2.1GHz 140W	HPE DL380 Gen10 Intel Xeon-Gold 6152 (2.1GHz/22-core/140W) Processor Kit	826886-B21
8C 3.2GHz 130W	HPE DL380 Gen10 Intel Xeon-Gold 6134 (3.2GHz/8-core/130W) Processor Kit	826872-B21
16C 2.6GHz 150W	HPE DL380 Gen10 Intel Xeon-Gold 6142 (2.6GHz/16-core/150W) Processor Kit	826880-B21
8C 3.5GHz 150W	HPE DL380 Gen10 Intel Xeon-Gold 6144 (3.5GHz/8-core/150W) Processor Kit	826860-B21
12C 3.2GHz 165W	HPE DL380 Gen10 Intel Xeon-Gold 6146 (3.2GHz/12-core/165W) Processor Kit	826868-B21
12C 3.0GHz 150W	HPE DL380 Gen10 Intel Xeon-Gold 6136 (3.0GHz/12-core/150W) Processor Kit	826874-B21
12C 3.0GHz 150W	HPE DL380 Gen10 Intel Xeon-Platinum 8158 (3.0GHz/12-core/150W) Processor Kit	869090-B21
16C 2.0GHz 125W	HPE DL380 Gen10 Intel Xeon-Platinum 8153 (2.0GHz/16-core/125W) Processor Kit	826890-B21
20C 2.0GHz 125W	HPE DL380 Gen10 Intel Xeon-Gold 6138 (2.0GHz/20-core/125W) Processor Kit	826876-B21
20C 2.4GHz 150W	HPE DL380 Gen10 Intel Xeon-Gold 6148 (2.4GHz/20-core/150W) Processor Kit	826882-B21
28C 2.5GHz 205W	HPE DL380 Gen10 Intel Xeon-Platinum 8180 (2.5GHz/28-core/205W) Processor Kit	871619-B21
24C 2.7GHz 205W	HPE DL380 Gen10 Intel Xeon-Platinum 8168 (2.7GHz/24-core/205W) Processor Kit	869089-B21
24C, 2.3GHz, 205W	HPE DL380 Gen10 Intel Xeon-Platinum 8165 (2.3GHz/24-core/205W) Processor Kit	879423-B21
26C 2.1GHz 165W	HPE DL380 Gen10 Intel Xeon-Platinum 8170 (2.1GHz/26-core/165W) Processor Kit	871617-B21
28C 2.1GHz 165W	HPE DL380 Gen10 Intel Xeon-Platinum 8176 (2.1GHz/28-core/165W) Processor Kit	871618-B21
14C 2.0GHz 105W	HPE DL380 Gen10 Intel Xeon-Gold 5117 (2.0GHz/14-core/105W) Processor Kit	P00756-B21
16C 2.8GHz 205W	HPE DL380 Gen10 Intel Xeon-Gold 6143 (2.8GHz/16-core/205W) Processor Kit	879424-B21
24C 2.1GHz 150W	HPE DL380 Gen10 Intel Xeon-Platinum 8160 (2.1GHz/24-core/150W) Processor Kit	869086-B21
26C 2.0GHz 150W	HPE DL380 Gen10 Intel Xeon-Platinum 8164 (2.0GHz/26-core/145W) Processor Kit	869088-B21
28C 2.5GHz 205W	HPE DL380 Gen10 Intel Xeon-Platinum 8180M (2.5GHz/28-core/205W) Processor Kit	874752-B21
8C 3.2GHz 130W	HPE DL380 Gen10 Intel Xeon-Gold 6134M (3.2GHz/8-core/130W) Processor Kit	873645-B21
24C, 2.3GHz, 205W	HPE DL380 Gen10 Intel Xeon-Platinum 8165 (2.3GHz/24-core/205W) Processor Kit	879423-B21

## Configuration Information

### Processors

#### CPU Configurations

Action	Details	Description	CPU SKU	
<b>Select CPUs for the node</b>	<b>Primary</b>			
	8C 2.1GHz 85W	HPE DL380 Gen10 Intel Xeon-Silver 4208 (2.1GHz/8-core/85W) FIO Processor Kit	P02491-L21	
<b>2nd Generation Intel® Xeon® Scalable Processors</b>	10C 2.2GHz 85W	HPE DL380 Gen10 Intel Xeon-Silver 4210 (2.2GHz/10-core/85W) FIO Processor Kit	P02492-L21	
	12C 2.2GHz 85W	HPE DL380 Gen10 Intel Xeon-Silver 4214 (2.2GHz/12-core/85W) FIO Processor Kit	P02493-L21	
<b>In the case of Single CPU only L21 SKU will be included by the configurator.</b>	8C 2.5GHz 85W	HPE DL380 Gen10 Intel Xeon-Silver 4215 (2.5GHz/8-core/85W) FIO Processor Kit	P02494-L21	
	16C 2.1GHz 100W	HPE DL380 Gen10 Intel Xeon-Silver 4216 (2.1GHz/16-core/100W) FIO Processor Kit	P02495-L21	
	10C 2.5GHz 85W	HPE DL380 Gen10 Intel Xeon-Gold 5215 (2.5GHz/10-core/85W) FIO Processor Kit	P02496-L21	
	8C 3.0GHz 125W	HPE DL380 Gen10 Intel Xeon-Gold 5217 (3.0GHz/8-core/115W) FIO Processor Kit	P02497-L21	
	<b>In the case of dual CPU: both the L21 and the B21 SKU will be included by the configurator</b>	16C 2.3GHz 125W	HPE DL380 Gen10 Intel Xeon-Gold 5218 (2.3GHz/16-core/125W) FIO Processor Kit	P02498-L21
		18C 2.2GHz 125W	HPE DL380 Gen10 Intel Xeon-Gold 5220 (2.2GHz/18-core/125W) FIO Processor Kit	P02499-L21
12C 2.7GHz 125W		HPE DL380 Gen10 Intel Xeon-Gold 6226 (2.7GHz/12-core/125W) FIO Processor Kit	P02501-L21	
20C 2.1GHz 125W		HPE DL380 Gen10 Intel Xeon-Gold 6230 (2.1GHz/20-core/125W) FIO Processor Kit	P02502-L21	
8C 3.3GHz 130W		HPE DL380 Gen10 Intel Xeon-Gold 6234 (3.3GHz/8-core/130W) FIO Processor Kit	P02503-L21	
22C 2.1GHz 140W		HPE DL380 Gen10 Intel Xeon-Gold 6238 (2.1GHz/22-core/140W) FIO Processor Kit	P02504-L21	
18C 2.6GHz 150W		HPE DL380 Gen10 Intel Xeon-Gold 6240 (2.6GHz/18-core/150W) FIO Processor Kit	P02509-L21	
16C 2.8GHz 150W		HPE DL380 Gen10 Intel Xeon-Gold 6242 (2.8GHz/16-core/150W) FIO Processor Kit	P02510-L21	
8C 3.7GHz 150W		HPE DL380 Gen10 Intel Xeon-Gold 6244 (3.6GHz/8-core/150W) FIO Processor Kit	P02512-L21	
20C 2.5GHz 150W		HPE DL380 Gen10 Intel Xeon-Gold 6248 (2.5GHz/20-core/150W) FIO Processor Kit	P02514-L21	
<b>In the case of dual CPU: both the L21 and the B21 SKU will be included by the configurator</b>	24C 2.1GHz 150W	HPE DL380 Gen10 Intel Xeon-Gold 6252 (2.1GHz/24-core/150W) FIO Processor Kit	P02516-L21	
	18C 3.1GHz 200W	HPE DL380 Gen10 Intel Xeon-Gold 6254 (3.1GHz/18-core/200W) FIO Processor Kit	P02517-L21	
	16C 2.2GHz 125W	HPE DL380 Gen10 Intel Xeon-Platinum 8253 (2.2GHz/16-core/125W) FIO Processor Kit	P02518-L21	
	24C 2.4GHz 165W	HPE DL380 Gen10 Intel Xeon-Platinum 8260 (2.4GHz/24-core/165W) FIO Processor Kit	P02521-L21	
	24C 2.9GHz 205W	HPE DL380 Gen10 Intel Xeon-Platinum 8268 (2.9GHz/24-core/205W) FIO Processor Kit	P02524-L21	
	26C 2.6GHz 205W	HPE DL380 Gen10 Intel Xeon-Platinum 8270 (2.7GHz/26-core/205W) FIO Processor Kit	P02525-L21	
	28C 2.2GHz 165W	HPE DL380 Gen10 Intel Xeon-Platinum 8276 (2.2GHz/28-core/165W) FIO Processor Kit	P02526-L21	
	28C 2.7GHz 205W	HPE DL380 Gen10 Intel Xeon-Platinum 8280 (2.7GHz/28-core/205W) FIO Processor Kit	P02527-L21	

## Configuration Information

18C 2.6GHz 150W (M-Series)	HPE DL380 Gen10 Intel Xeon-Gold 6240M (2.6GHz/18-core/150W) FIO Processor Kit	P02528-L21
22C 2.1GHz 140W (M-Series)	HPE DL380 Gen10 Intel Xeon-Gold 6238M (2.1GHz/22-core/140W) FIO Processor Kit	P02529-L21
10C 2.6GHz 85W (M-Series)	HPE DL380 Gen10 Intel Xeon-Gold 5215M (2.5GHz/10-core/85W) FIO Processor Kit	P02530-L21
24C 2.4GHz 165W (M-Series)	HPE DL380 Gen10 Intel Xeon-Platinum 8260M (2.4GHz/24-core/165W) FIO Processor Kit	P02532-L21
28C 2.2GHz 165W (M-Series)	HPE DL380 Gen10 Intel Xeon-Platinum 8276M (2.2GHz/28-core/165W) FIO Processor Kit	P02534-L21
28C 2.7GHz 205W (M-Series)	HPE DL380 Gen10 Intel Xeon-Platinum 8280M (2.7GHz/28-core/205W) FIO Processor Kit	P02535-L21
12C 3.3GHz 165W	HPE DL380 Gen10 Intel Xeon-Gold 6246 (3.3GHz/12-core/165W) FIO Processor Kit	P15758-L21

### Secondary

8C 2.1GHz 85W	HPE DL380 Gen10 Intel Xeon-Silver 4208 (2.1GHz/8-core/85W) Processor Kit	P02491-B21
10C 2.2GHz 85W	HPE DL380 Gen10 Intel Xeon-Silver 4210 (2.2GHz/10-core/85W) Processor Kit	P02492-B21
12C 2.2GHz 85W	HPE DL380 Gen10 Intel Xeon-Silver 4214 (2.2GHz/12-core/85W) Processor Kit	P02493-B21
8C 2.5GHz 85W	HPE DL380 Gen10 Intel Xeon-Silver 4215 (2.5GHz/8-core/85W) Processor Kit	P02494-B21
16C 2.1GHz 100W	HPE DL380 Gen10 Intel Xeon-Silver 4216 (2.1GHz/16-core/100W) Processor Kit	P02495-B21
10C 2.5GHz 85W	HPE DL380 Gen10 Intel Xeon-Gold 5215 (2.5GHz/10-core/85W) Processor Kit	P02496-B21
8C 3.0GHz 125W	HPE DL380 Gen10 Intel Xeon-Gold 5217 (3.0GHz/8-core/115W) Processor Kit	P02497-B21
16C 2.3GHz 125W	HPE DL380 Gen10 Intel Xeon-Gold 5218 (2.3GHz/16-core/125W) Processor Kit	P02498-B21
18C 2.2GHz 125W	HPE DL380 Gen10 Intel Xeon-Gold 5220 (2.2GHz/18-core/125W) Processor Kit	P02499-B21
12C 2.7GHz 125W	HPE DL380 Gen10 Intel Xeon-Gold 6226 (2.7GHz/12-core/125W) Processor Kit	P02501-B21
20C 2.1GHz 125W	HPE DL380 Gen10 Intel Xeon-Gold 6230 (2.1GHz/20-core/125W) Processor Kit	P02502-B21
8C 3.3GHz 130W	HPE DL380 Gen10 Intel Xeon-Gold 6234 (3.3GHz/8-core/130W) Processor Kit	P02503-B21
22C 2.1GHz 140W	HPE DL380 Gen10 Intel Xeon-Gold 6238 (2.1GHz/22-core/140W) Processor Kit	P02504-B21
18C 2.6GHz 150W	HPE DL380 Gen10 Intel Xeon-Gold 6240 (2.6GHz/18-core/150W) Processor Kit	P02509-B21
16C 2.8GHz 150W	HPE DL380 Gen10 Intel Xeon-Gold 6242 (2.8GHz/16-core/150W) Processor Kit	P02510-B21
8C 3.7GHz 150W	HPE DL380 Gen10 Intel Xeon-Gold 6244 (3.6GHz/8-core/150W) Processor Kit	P02512-B21
20C 2.5GHz 150W	HPE DL380 Gen10 Intel Xeon-Gold 6248 (2.5GHz/20-core/150W) Processor Kit	P02514-B21
24C 2.1GHz 150W	HPE DL380 Gen10 Intel Xeon-Gold 6252 (2.1GHz/24-core/150W) Processor Kit	P02516-B21
18C 3.1GHz 200W	HPE DL380 Gen10 Intel Xeon-Gold 6254 (3.1GHz/18-core/200W) Processor Kit	P02517-B21
16C 2.2GHz 125W	HPE DL380 Gen10 Intel Xeon-Platinum 8253 (2.2GHz/16-core/125W) Processor Kit	P02518-B21

## Configuration Information

24C 2.4GHz 165W	HPE DL380 Gen10 Intel Xeon-Platinum 8260 (2.4GHz/24-core/165W) Processor Kit	P02521-B21
24C 2.9GHz 205W	HPE DL380 Gen10 Intel Xeon-Platinum 8268 (2.9GHz/24-core/205W) Processor Kit	P02524-B21
26C 2.6GHz 205W	HPE DL380 Gen10 Intel Xeon-Platinum 8270 (2.7GHz/26-core/205W) Processor Kit	P02525-B21
28C 2.2GHz 165W	HPE DL380 Gen10 Intel Xeon-Platinum 8276 (2.2GHz/28-core/165W) Processor Kit	P02526-B21
28C 2.7GHz 205W	HPE DL380 Gen10 Intel Xeon-Platinum 8280 (2.7GHz/28-core/205W) Processor Kit	P02527-B21
18C 2.6GHz 150W (M-Series)	HPE DL380 Gen10 Intel Xeon-Gold 6240M (2.6GHz/18-core/150W) Processor Kit	P02528-B21
22C 2.1GHz 140W (M-Series)	HPE DL380 Gen10 Intel Xeon-Gold 6238M (2.1GHz/22-core/140W) Processor Kit	P02529-B21
10C 2.6GHz 85W (M-Series)	HPE DL380 Gen10 Intel Xeon-Gold 5215M (2.5GHz/10-core/85W) Processor Kit	P02530-B21
24C 2.4GHz 165W (M-Series)	HPE DL380 Gen10 Intel Xeon-Platinum 8260M (2.4GHz/24-core/165W) Processor Kit	P02532-B21
28C 2.2GHz 165W (M-Series)	HPE DL380 Gen10 Intel Xeon-Platinum 8276M (2.2GHz/28-core/165W) Processor Kit	P02534-B21
28C 2.7GHz 205W (M-Series)	HPE DL380 Gen10 Intel Xeon-Platinum 8280M (2.7GHz/28-core/205W) Processor Kit	P02535-B21
12C 3.3GHz 165W	HPE DL380 Gen10 Intel Xeon-Gold 6246 (3.3GHz/12-core/165W) Processor Kit	P15758-B21

## Configuration Information

Action	Type	Details	Memory	SKU
			Description	
Select a memory capacity for the node	DDR4-2666	8x 16GB RDIMMs	HPE SimpliVity 128GB 8 RDIMM Slots Memory Kit	R2G99A
The appropriate memory and quantity will be included by the configurator	DDR4-2666	6x 8GB AND 6x 16GB RDIMMs	HPE SimpliVity 144G 12 DIMM Slots Memory Kit	R1Q89A
	DDR4-2666	12x 16GB RDIMMs	HPE SimpliVity 192G 12 DIMM Slots Memory Kit	R1Q90A
1 Kit required per CPU	DDR4-2666	6x 32GB RDIMMs	HPE SimpliVity 192G 6 DIMM Slots Memory Kit	R1Q91A
	DDR4-2666	6x 32GB AND 6x 8GB RDIMMs	HPE SimpliVity 240G 12 DIMM Slots Memory Kit	R1Q92A
	DDR4-2666	4x 64GB LRDIMMs	HPE SimpliVity 256GB 4 LRDIMM Slots Memory Kit	R2H00A
	DDR4-2666	8x 32GB RDIMMs	HPE SimpliVity 256GB 8 RDIMM Slots Memory Kit	R2H01A
	DDR4-2666	6x 32GB AND 6x 16GB RDIMMs	HPE SimpliVity 288G 12 DIMM Slots Memory Kit	R1Q93A
	DDR4-2666	12x 32GB RDIMMs	HPE SimpliVity 384G 12 DIMM Slots Memory Kit	R1Q94A
	DDR4-2666	6x 64GB LRDIMMs	HPE SimpliVity 384G 6 DIMM Slots Memory Kit	R1Q95A
	DDR4-2666	8x 64GB LRDIMMs	HPE SimpliVity 512GB 8 LRDIMM Slots Memory Kit	R2H02A
	DDR4-2666	6x 128GB LRDIMMs	HPE SimpliVity 768G 6 LRDIMM Slots Memory Kit	R2H03A
	DDR4-2666	12x 64GB LRDIMMs	HPE SimpliVity 768G 12 DIMM Slots Memory Kit	R1Q96A
	DDR4-2666	12x 128GB LRDIMMs	HPE SimpliVity 1.5TB 12 LRDIMM Slots Memory Kit	R2H04A
	DDR4-2933	8x P00920-B21	HPE SimpliVity 128GB (8x16GB) DDR4-2933 Registered Memory Kit	R4C17A
	DDR4-2933	6x P00918-B21,6xP00920-B21	HPE SimpliVity 144GB (6x8GB/6x16GB) DDR4-2933 Registered Memory Kit	R4C18A
DDR4-2933	12x P00920-B21	HPE SimpliVity 192GB (12x16GB) DDR4-2933 Registered Memory Kit	R4C19A	
DDR4-2933	6x P00924-B21	HPE SimpliVity 192GB (6x32GB) DDR4-2933 Registered Memory Kit	R4C20A	
DDR4-2933	6x P00924-B21, 6x P00918-B21	HPE SimpliVity 240GB (6x32GB/6x8GB) DDR4-2933 Registered Memory Kit	R4C21A	
DDR4-2933	4x P00930-B21	HPE SimpliVity 256GB (4x64GB) DDR4-2933 Load Reduced Memory Kit	R4C22A	

## Configuration Information

DDR4-2933	8x P00924-B21	HPE SimpliVity 256GB (8x32GB) DDR4-2933 Registered Memory Kit	R4C23A
DDR4-2933	6x P00924-B21, 6x P00922-B21	HPE SimpliVity 288GB (6x32GB/6x16GB) DDR4-2933 Registered Memory Kit	R4C26A
DDR4-2933	12x P00924-B21	HPE SimpliVity 384GB (12x32GB) DDR4-2933 Registered Memory Kit	R4C27A
DDR4-2933	6x P00930-B21	HPE SimpliVity 384GB (6x64GB) DDR4-2933 Load Reduced Memory Kit	R4C28A
DDR4-2933	8x P00930-B21	HPE SimpliVity 512GB (8x64GB) DDR4-2933 Load Reduced Memory Kit	R4C24A
DDR4-2933	6x P11040-B21	HPE SimpliVity 768GB (6x128GB) DDR4-2933 Load Reduced Memory Kit	R4C30A
DDR4-2933	12x P00930-B21	HPE SimpliVity 768GB (12x64GB) DDR4-2933 Load Reduced Memory Kit	R4C29A
DDR4-2933	12x P11040-B21	HPE SimpliVity 1.5TB (12x128GB) DDR4-2933 Load Reduced Memory Kit	R4C25A

**NOTE:** For more information go to <http://www.hpe.com/docs/memory-population-rules>

**NOTE:** DDR4-2933 Memory Kits are only supported with 2nd Generation Intel Xeon Scalable Series Processors and DDR4-2666 Memory Kits are only supported with 1st Generation Intel Xeon Scalable Series Processors

## Storage

Effective capacity varies by environment and is a function of realized deduplication and compression rates. The capacities in this table offer a conservative range based on compression and deduplication rates found in standard, primary storage use cases.

Action	Usable Capacity	Description	Part #
Select one the following storage kit(s) for the nodes			
Qty1 of Q9Y49A (6x1.92TB) is required for HPE SimpliVity 380 G 6x SSD	7.5TB	HPE SimpliVity 6x1.92TB SFF SSD Kit	Q9Y49A
Qty3 of R2Z28A (4x1.92TB) is required for HPE SimpliVity 380 G 12x SSD	10.6TB	HPE SimpliVity 4x1.92TB SFF SSD Kit	R2Z28A
Qty2 of R2Z28A (4x1.92TB) is required for HPE SimpliVity 380 G 8x SSD	15TB	HPE SimpliVity 4x1.92TB SFF SSD Kit	R2Z28A
Qty4 of R2Z28A (4x1.92TB) is required for HPE SimpliVity 380 G 16x SSD	21TB	HPE SimpliVity 4x1.92TB SFF SSD Kit	R2Z28A

The appropriate OmniStack software will be included by the configurator

**NOTE:** Usable capacity is the capacity available after RAID and system overheads have been removed, before deduplication and compression is applied

---

## Configuration Information

---

## Configuration Information

### Networking

Action	System Max	Description	Part #
One FlexLOM is required. This is in addition to the standard 4 port 1GbE LOM included in the base node	1	HPE Ethernet 1Gb 4-port 331FLR Adapter	629135-B22
	1	HPE Ethernet 1Gb 4-port 366FLR Adapter	665240-B21
	1	HPE FlexFabric 10Gb 2-port 533FLR-T Adapter	700759-B21
	1	HPE FlexFabric 10Gb 2-port 534FLR-SFP+ Adapter	700751-B21
	1	HPE FlexFabric 10Gb 4-port 536FLR-T Adapter	764302-B21
	1	HPE Ethernet 10/25Gb 2-port 631FLR-SFP28 Adapter	817709-B21
	1	HPE Ethernet 10/25Gb 2-port 640FLR-SFP28 Adapter	817749-B21

### PCIe Adapter

Action	System Max	Description	Part #
Optional PCIe Adapters can be added if slots are available. Additional PCIe slots are available in the case of dual CPU with secondary riser	5	HPE Ethernet 1Gb 4-port 331T Adapter	647594-B21
	5	HPE Ethernet 1Gb 4-port 366T Adapter	811546-B21
	5	HPE Ethernet 10Gb 2-port 530SFP Adapter	652503-B21
	5	HPE Ethernet 10Gb 2-port 530T Adapter	656596-B21
	5	HPE Ethernet 10/25Gb 2-port 621SFP28 Adapter	867328-B21
	5	HPE Ethernet 10/25Gb 2-port 631SFP28 Adapter	817718-B21
	5	HPE Ethernet 10/25Gb 2-port 640SFP28 Adapter	817753-B21
	5	HPE Ethernet 1Gb 4-port 331T Adapter	647594-B21

### Optional Fibre Channel HBA cards

Action	System Max	Description	Part #
Optional FC HBAs may be added if slots are available	5	HPE StoreFabric SN1100Q 16Gb Dual Port Fibre Channel Host Bus Adapter	P9D94A
	5	HPE StoreFabric SN1600Q 32Gb Dual Port Fibre Channel Host Bus Adapter	P9M76A

**NOTE:** Additional network cables and transceivers are available in the Aruba and DataCenter Networking menus.

**NOTE:** Information on interoperability between network adapters, transceivers, and cables is available in network adapter QuickSpecs.

### Optional GPUs

Action	System Max	Description	Part #
Optional Graphic Accelerator (2) may be added in the case of dual CPU with secondary riser	2	NVIDIA Tesla M10 Quad GPU Module	Q0J62A
	2	HPE NVIDIA Tesla P40 24GB Computational Accelerator	Q0V80A
	2	HPE NVIDIA Tesla T4 16GB Computational Accelerator	ROW29A

### Power Supplies

Action	Description	Part #
Two power supplies are required.	HPE 800W Flex Slot Platinum Hot Plug Low Halogen Power Supply Kit	865414-B21
	HPE 800W Flex Slot Universal Hot Plug Low Halogen Power Supply Kit	865428-B21
	HPE 800W Flex Slot -48VDC Hot Plug Low Halogen Power Supply Kit	865434-B21
	HPE 800W Flex Slot Titanium Hot Plug Low Halogen Power Supply Kit	865438-B21
	HPE 1600W Flex Slot Platinum Hot Plug Low Halogen Power Supply Kit	830272-B21

**NOTE:** The power supply requirement can vary based configuration and environment. 800W Power Supply is only supported with specific configurations. Please refer to HPE Power Advisor for proper power sizing.

## Configuration Information

**NOTE:** All configured nodes ship with a standard 6-foot IEC C-13/C-14 jumper cord (A0K02A). This jumper cord is also included with each standard AC power supply option kit. If a different power cord is required, please check the ProLiant Power Cables web page: <https://h20195.www2.hp.com/v2/getpdf.aspx/4AA6-6836ENW.pdf>

### Additional Server Options

Action	Description	Part #
Additional hardware options are available	HPE DL380 Gen10 SFF Systems Insight Display Kit	826703-B21
	HPE DL3XX Gen10 Rear Serial Cable and Enablement Kit	873770-B21
	HPE 2U Small Form Factor Ball Bearing Rail Kit	720863-B21
	HPE 2U Cable Management Arm for Ball Bearing Rail Kit	720865-B21
	HPE 2U Small Form Factor Easy Install Rail Kit	733660-B21

### HPE SimpliVity Software

Action	Description	Part #
Based on the number of CPUs in the node, the appropriate software will be included by the configurator.	HPE SimpliVity 380 G 1 Processor 7.5TB Software	R4D13A
	HPE SimpliVity 380 G 2 Processors 7.5TB Software	R4D14A
	HPE SimpliVity 380 1P 10TB SW	R3V05A
	HPE SimpliVity 380 2P 10TB SW	R3V06A
	HPE SimpliVity 380 G 1 Processor 15TB Software	R4D15A
	HPE SimpliVity 380 G 2 Processors 15TB Software	R4D16A
	HPE SimpliVity 380 G 1 Processor 21TB Software	R4D17A
HPE SimpliVity 380 G 2 Processors 21TB Software	R4D18A	

### VMware Software

#### vSphere

Action	Description	Part #
A valid VMware vSphere license is required for each CPU to complete deployment.	VMware vSphere Remote Office Branch Office Standard 25VM 3yr E-LTU	P9A82AAE
	VMware vSphere Remote Office Branch Office Standard 25VM 5yr E-LTU	P9A83AAE
	VMware vSphere Remote Office Branch Office Advanced 25VM 3yr E-LTU	P9A85AAE
	VMware vSphere Remote Office Branch Office Advanced 25VM 5yr E-LTU	P9A86AAE
	VMware vSphere Standard 1 Processor 3yr Software	BD711A
If an order is placed without VMware licenses, the user agrees to supply the necessary license.	VMware vSphere Standard 1 Processor 3yr E-LTU	BD711AAE
	VMware vSphere Enterprise Plus 1 Processor 3yr Software	BD715A
	VMware vSphere Enterprise Plus 1 Processor 3yr E-LTU	BD715AAE
	VMware vSphere Standard 1 Processor 5yr Software	BD512A
	VMware vSphere Standard 1 Processor 5yr E-LTU	BD512AAE
	VMware vSphere Enterprise Plus 1 Processor 5yr Software	BD514A
	VMware vSphere Enterprise Plus 1 Processor 5yr E-LTU	BD514AAE

**NOTE:** HPE SimpliVity 380 Gen10 for VMware vSphere requires valid VMware vSphere and vCenter licenses. VMware licenses can only be removed from the order if it is confirmed that the end-customer has valid licenses in place (Enterprise License Agreement (ELA), vCloud Air Partner or unused Enterprise Purchasing Program tokens).

**NOTE:** Purchasing VMware licenses from Hewlett Packard Enterprise allows Hewlett Packard Enterprise to be the single point of contact for the entire solution inclusive of the virtualization software and is recommended. When the VMware license is not included on the order the solution level support experience is impacted.

### HPE Integrated Lights Out Advanced Software (iLO Advanced)

Action	Description	Part #
The HPE iLO Advanced license is required	HPE iLO Advanced 1-server License with 3yr Support on iLO Licensed Features	BD505A
	HPE iLO Advanced Flexible Quantity License with 3yr Support on iLO Licensed Features	BD506A
	HPE iLO Advanced AKA Tracking License with 3yr Support on iLO Licensed Features	BD507A
	HPE iLO Advanced Electronic License with 3yr Support on iLO Licensed Features	E6U64ABE

## Configuration Information

### HPE SimpliVity 380 Gen10 H: Overview for New System

Use the following steps to order a new SimpliVity 380 Gen10 system:

Step 1: Begin with the base node and select a hypervisor option

Step 2: Select the hardware options to add to the base node: processors, memory, storage, networking, power, other optional HW

Step 3: The software license that corresponds to the node configuration will be automatically added

Step 4: Select service and support

#### Base Node

Action	Description	Part #
Select the base node	HPE SimpliVity 380 Gen10 H Node HPE SimpliVity 380 Gen10 SFF H Node	R2Z00A R4D36A
Hypervisor tracking SKU added automatically	HPE SimpliVity 380 Gen10 VMware Node Tracking	R2G97A

#### Processors

##### CPU Configurations

Action	Details	Description	CPU SKU
Select CPUs for the node	<b>Primary</b> 8C 2.1GHz 85W	HPE DL380 Gen10 Intel Xeon-Silver 4110 (2.1GHz/8-core/85W) FIO Processor Kit	826846-L21
1st Generation Intel® Xeon® Scalable Processors	8C 1.8GHz 85W	HPE DL380 Gen10 Intel Xeon-Silver 4108 (1.8GHz/8-core/85W) FIO Processor Kit	826848-L21
	10C 2.2GHz 85W	HPE DL380 Gen10 Intel Xeon-Silver 4114 (2.2GHz/10-core/85W) FIO Processor Kit	826850-L21
In the case of Single CPU only L21 SKU will be included by the configurator.	12C 2.1GHz 85W	HPE DL380 Gen10 Intel Xeon-Silver 4116 (2.1GHz/12-core/85W) FIO Processor Kit	826852-L21
	12C 2.3GHz 105W	HPE DL380 Gen10 Intel Xeon-Gold 5118 (2.3GHz/12-core/105W) FIO Processor Kit	826854-L21
	14C 2.2GHz 105W	HPE DL380 Gen10 Intel Xeon-Gold 5120 (2.2GHz/14-core/105W) FIO Processor Kit	826856-L21
In the case of dual CPU: both the L21 and the B21 SKU will be included by the configurator	12C 2.6GHz 125W	HPE DL380 Gen10 Intel Xeon-Gold 6126 (2.6GHz/12-core/120W) FIO Processor Kit	826862-L21
	16C 2.1GHz 125W	HPE DL380 Gen10 Intel Xeon-Gold 6130 (2.1GHz/16-core/120W) FIO Processor Kit	826866-L21
	14C 2.6GHz 140W	HPE DL380 Gen10 Intel Xeon-Gold 6132 (2.6GHz/14-core/140W) FIO Processor Kit	826870-L21
	18C 2.3GHz 140W	HPE DL380 Gen10 Intel Xeon-Gold 6140 (2.3GHz/18-core/140W) FIO Processor Kit	826878-L21
	18C 2.7GHz 165W	HPE DL380 Gen10 Intel Xeon-Gold 6150 (2.7GHz/18-core/165W) FIO Processor Kit	826884-L21
	18C 3.0GHz 200W	HPE DL380 Gen10 Intel Xeon-Gold 6154 (3.0GHz/18-core/200W) FIO Processor Kit	826888-L21
	10C 2.4GHz 85W	HPE DL380 Gen10 Intel Xeon-Gold 5115 (2.4GHz/10-core/85W) FIO Processor Kit	876562-L21
	22C 2.1GHz 140W	HPE DL380 Gen10 Intel Xeon-Gold 6152 (2.1GHz/22-core/140W) FIO Processor Kit	826886-L21
	8C 3.2GHz 130W	HPE DL380 Gen10 Intel Xeon-Gold 6134 (3.2GHz/8-core/130W) FIO Processor Kit	826872-L21
	16C 2.6GHz 150W	HPE DL380 Gen10 Intel Xeon-Gold 6142 (2.6GHz/16-core/150W) FIO Processor Kit	826880-L21
8C 3.5GHz 150W	HPE DL380 Gen10 Intel Xeon-Gold 6144 (3.5GHz/8-core/150W) FIO Processor Kit	826860-L21	

## Configuration Information

12C 3.2GHz 165W	HPE DL380 Gen10 Intel Xeon-Gold 6146 (3.2GHz/12-core/165W) FIO Processor Kit	826868-L21
12C 3.0GHz 150W	HPE DL380 Gen10 Intel Xeon-Gold 6136 (3.0GHz/12-core/150W) FIO Processor Kit	826874-L21
12C 3.0GHz 150W	HPE DL380 Gen10 Intel Xeon-Platinum 8158 (3.0GHz/12-core/150W) FIO Processor Kit	869090-L21
16C 2.0GHz 125W	HPE DL380 Gen10 Intel Xeon-Platinum 8153 (2.0GHz/16-core/125W) FIO Processor Kit	826890-L21
20C 2.0GHz 125W	HPE DL380 Gen10 Intel Xeon-Gold 6138 (2.0GHz/20-core/125W) FIO Processor Kit	826876-L21
20C 2.4GHz 150W	HPE DL380 Gen10 Intel Xeon-Gold 6148 (2.4GHz/20-core/150W) FIO Processor Kit	826882-L21
28C 2.5GHz 205W	HPE DL380 Gen10 Intel Xeon-Platinum 8180 (2.5GHz/28-core/205W) FIO Processor Kit	871619-L21
24C 2.7GHz 205W	HPE DL380 Gen10 Intel Xeon-Platinum 8168 (2.7GHz/24-core/205W) FIO Processor Kit	869089-L21
24C, 2.3GHz, 205W	HPE DL380 Gen10 Intel Xeon-Platinum 8165 (2.3GHz/24-core/205W) FIO Processor Kit	879423-L21
26C 2.1GHz 165W	HPE DL380 Gen10 Intel Xeon-Platinum 8170 (2.1GHz/26-core/165W) FIO Processor Kit	871617-L21
28C 2.1GHz 165W	HPE DL380 Gen10 Intel Xeon-Platinum 8176 (2.1GHz/28-core/165W) FIO Processor Kit	871618-L21
14C 2.0GHz 105W	HPE DL380 Gen10 Intel Xeon-Gold 5117 (2.0GHz/14-core/105W) FIO Processor Kit	P00756-L21
16C 2.8GHz 205W	HPE DL380 Gen10 Intel Xeon-Gold 6143 (2.8GHz/16-core/205W) FIO Processor Kit	879424-L21
24C 2.1GHz 150W	HPE DL380 Gen10 Intel Xeon-Platinum 8160 (2.1GHz/24-core/150W) FIO Processor Kit	869086-L21
26C 2.0GHz 150W	HPE DL380 Gen10 Intel Xeon-Platinum 8164 (2.0GHz/26-core/145W) FIO Processor Kit	869088-L21
28C 2.5GHz 205W	HPE DL380 Gen10 Intel Xeon-Platinum 8180M (2.5GHz/28-core/205W) FIO Processor Kit	874752-L21
8C 3.2GHz 130W	HPE DL380 Gen10 Intel Xeon-Gold 6134M (3.2GHz/8-core/130W) FIO Processor Kit	873645-L21
24C, 2.3GHz, 205W	HPE DL380 Gen10 Intel Xeon-Platinum 8165 (2.3GHz/24-core/205W) FIO Processor Kit	879423-L21
<b>Secondary</b>		
8C 2.1GHz 85W	HPE DL380 Gen10 Intel Xeon-Silver 4110 (2.1GHz/8-core/85W) Processor Kit	826846-B21
8C 1.8GHz 85W	HPE DL380 Gen10 Intel Xeon-Silver 4108 (1.8GHz/8-core/85W) Processor Kit	826848-B21
10C 2.2GHz 85W	HPE DL380 Gen10 Intel Xeon-Silver 4114 (2.2GHz/10-core/85W) Processor Kit	826850-B21
12C 2.1GHz 85W	HPE DL380 Gen10 Intel Xeon-Silver 4116 (2.1GHz/12-core/85W) Processor Kit	826852-B21
12C 2.3GHz 105W	HPE DL380 Gen10 Intel Xeon-Gold 5118 (2.3GHz/12-core/105W) Processor Kit	826854-B21
14C 2.2GHz 105W	HPE DL380 Gen10 Intel Xeon-Gold 5120 (2.2GHz/14-core/105W) Processor Kit	826856-B21
12C 2.6GHz 125W	HPE DL380 Gen10 Intel Xeon-Gold 6126 (2.6GHz/12-core/120W) Processor Kit	826862-B21
16C 2.1GHz 125W	HPE DL380 Gen10 Intel Xeon-Gold 6130 (2.1GHz/16-core/120W) Processor Kit	826866-B21
14C 2.6GHz 140W	HPE DL380 Gen10 Intel Xeon-Gold 6132 (2.6GHz/14-core/140W) Processor Kit	826870-B21

## Configuration Information

18C 2.3GHz 140W	HPE DL380 Gen10 Intel Xeon-Gold 6140 (2.3GHz/18-core/140W) Processor Kit	826878-B21
18C 2.7GHz 165W	HPE DL380 Gen10 Intel Xeon-Gold 6150 (2.7GHz/18-core/165W) Processor Kit	826884-B21
18C 3.0GHz 200W	HPE DL380 Gen10 Intel Xeon-Gold 6154 (3.0GHz/18-core/200W) Processor Kit	826888-B21
10C 2.4GHz 85W	HPE DL380 Gen10 Intel Xeon-Gold 5115 (2.4GHz/10-core/85W) Processor Kit	876562-B21
22C 2.1GHz 140W	HPE DL380 Gen10 Intel Xeon-Gold 6152 (2.1GHz/22-core/140W) Processor Kit	826886-B21
8C 3.2GHz 130W	HPE DL380 Gen10 Intel Xeon-Gold 6134 (3.2GHz/8-core/130W) Processor Kit	826872-B21
16C 2.6GHz 150W	HPE DL380 Gen10 Intel Xeon-Gold 6142 (2.6GHz/16-core/150W) Processor Kit	826880-B21
8C 3.5GHz 150W	HPE DL380 Gen10 Intel Xeon-Gold 6144 (3.5GHz/8-core/150W) Processor Kit	826860-B21
12C 3.2GHz 165W	HPE DL380 Gen10 Intel Xeon-Gold 6146 (3.2GHz/12-core/165W) Processor Kit	826868-B21
12C 3.0GHz 150W	HPE DL380 Gen10 Intel Xeon-Gold 6136 (3.0GHz/12-core/150W) Processor Kit	826874-B21
12C 3.0GHz 150W	HPE DL380 Gen10 Intel Xeon-Platinum 8158 (3.0GHz/12-core/150W) Processor Kit	869090-B21
16C 2.0GHz 125W	HPE DL380 Gen10 Intel Xeon-Platinum 8153 (2.0GHz/16-core/125W) Processor Kit	826890-B21
20C 2.0GHz 125W	HPE DL380 Gen10 Intel Xeon-Gold 6138 (2.0GHz/20-core/125W) Processor Kit	826876-B21
20C 2.4GHz 150W	HPE DL380 Gen10 Intel Xeon-Gold 6148 (2.4GHz/20-core/150W) Processor Kit	826882-B21
28C 2.5GHz 205W	HPE DL380 Gen10 Intel Xeon-Platinum 8180 (2.5GHz/28-core/205W) Processor Kit	871619-B21
24C 2.7GHz 205W	HPE DL380 Gen10 Intel Xeon-Platinum 8168 (2.7GHz/24-core/205W) Processor Kit	869089-B21
24C, 2.3GHz, 205W	HPE DL380 Gen10 Intel Xeon-Platinum 8165 (2.3GHz/24-core/205W) Processor Kit	879423-B21
26C 2.1GHz 165W	HPE DL380 Gen10 Intel Xeon-Platinum 8170 (2.1GHz/26-core/165W) Processor Kit	871617-B21
28C 2.1GHz 165W	HPE DL380 Gen10 Intel Xeon-Platinum 8176 (2.1GHz/28-core/165W) Processor Kit	871618-B21
14C 2.0GHz 105W	HPE DL380 Gen10 Intel Xeon-Gold 5117 (2.0GHz/14-core/105W) Processor Kit	P00756-B21
16C 2.8GHz 205W	HPE DL380 Gen10 Intel Xeon-Gold 6143 (2.8GHz/16-core/205W) Processor Kit	879424-B21
24C 2.1GHz 150W	HPE DL380 Gen10 Intel Xeon-Platinum 8160 (2.1GHz/24-core/150W) Processor Kit	869086-B21
26C 2.0GHz 150W	HPE DL380 Gen10 Intel Xeon-Platinum 8164 (2.0GHz/26-core/145W) Processor Kit	869088-B21
28C 2.5GHz 205W	HPE DL380 Gen10 Intel Xeon-Platinum 8180M (2.5GHz/28-core/205W) Processor Kit	874752-B21
8C 3.2GHz 130W	HPE DL380 Gen10 Intel Xeon-Gold 6134M (3.2GHz/8-core/130W) Processor Kit	873645-B21
24C, 2.3GHz, 205W	HPE DL380 Gen10 Intel Xeon-Platinum 8165 (2.3GHz/24-core/205W) Processor Kit	879423-B21

## Configuration Information

### Processors

#### CPU Configurations

Action	Details	Description	CPU SKU
Select CPUs for the node	Primary 8C 2.1GHz 85W	HPE DL380 Gen10 Intel Xeon-Silver 4208 (2.1GHz/8-core/85W) FIO Processor Kit	P02491-L21
2nd Generation Intel® Xeon® Scalable Processors	10C 2.2GHz 85W	HPE DL380 Gen10 Intel Xeon-Silver 4210 (2.2GHz/10-core/85W) FIO Processor Kit	P02492-L21
	12C 2.2GHz 85W	HPE DL380 Gen10 Intel Xeon-Silver 4214 (2.2GHz/12-core/85W) FIO Processor Kit	P02493-L21
	8C 2.5GHz 85W	HPE DL380 Gen10 Intel Xeon-Silver 4215 (2.5GHz/8-core/85W) FIO Processor Kit	P02494-L21
In the case of Single CPU only L21 SKU will be included by the configurator.	16C 2.1GHz 100W	HPE DL380 Gen10 Intel Xeon-Silver 4216 (2.1GHz/16-core/100W) FIO Processor Kit	P02495-L21
	10C 2.5GHz 85W	HPE DL380 Gen10 Intel Xeon-Gold 5215 (2.5GHz/10-core/85W) FIO Processor Kit	P02496-L21
	8C 3.0GHz 125W	HPE DL380 Gen10 Intel Xeon-Gold 5217 (3.0GHz/8-core/115W) FIO Processor Kit	P02497-L21
In the case of dual CPU: both the L21 and the B21 SKU will be included by the configurator	16C 2.3GHz 125W	HPE DL380 Gen10 Intel Xeon-Gold 5218 (2.3GHz/16-core/125W) FIO Processor Kit	P02498-L21
	18C 2.2GHz 125W	HPE DL380 Gen10 Intel Xeon-Gold 5220 (2.2GHz/18-core/125W) FIO Processor Kit	P02499-L21
	12C 2.7GHz 125W	HPE DL380 Gen10 Intel Xeon-Gold 6226 (2.7GHz/12-core/125W) FIO Processor Kit	P02501-L21
	20C 2.1GHz 125W	HPE DL380 Gen10 Intel Xeon-Gold 6230 (2.1GHz/20-core/125W) FIO Processor Kit	P02502-L21
	8C 3.3GHz 130W	HPE DL380 Gen10 Intel Xeon-Gold 6234 (3.3GHz/8-core/130W) FIO Processor Kit	P02503-L21
	22C 2.1GHz 140W	HPE DL380 Gen10 Intel Xeon-Gold 6238 (2.1GHz/22-core/140W) FIO Processor Kit	P02504-L21
	18C 2.6GHz 150W	HPE DL380 Gen10 Intel Xeon-Gold 6240 (2.6GHz/18-core/150W) FIO Processor Kit	P02509-L21
	16C 2.8GHz 150W	HPE DL380 Gen10 Intel Xeon-Gold 6242 (2.8GHz/16-core/150W) FIO Processor Kit	P02510-L21
	8C 3.7GHz 150W	HPE DL380 Gen10 Intel Xeon-Gold 6244 (3.6GHz/8-core/150W) FIO Processor Kit	P02512-L21
	20C 2.5GHz 150W	HPE DL380 Gen10 Intel Xeon-Gold 6248 (2.5GHz/20-core/150W) FIO Processor Kit	P02514-L21
	24C 2.1GHz 150W	HPE DL380 Gen10 Intel Xeon-Gold 6252 (2.1GHz/24-core/150W) FIO Processor Kit	P02516-L21
	18C 3.1GHz 200W	HPE DL380 Gen10 Intel Xeon-Gold 6254 (3.1GHz/18-core/200W) FIO Processor Kit	P02517-L21
	16C 2.2GHz 125W	HPE DL380 Gen10 Intel Xeon-Platinum 8253 (2.2GHz/16-core/125W) FIO Processor Kit	P02518-L21
	24C 2.4GHz 165W	HPE DL380 Gen10 Intel Xeon-Platinum 8260 (2.4GHz/24-core/165W) FIO Processor Kit	P02521-L21
	24C 2.9GHz 205W	HPE DL380 Gen10 Intel Xeon-Platinum 8268 (2.9GHz/24-core/205W) FIO Processor Kit	P02524-L21
	26C 2.6GHz 205W	HPE DL380 Gen10 Intel Xeon-Platinum 8270 (2.7GHz/26-core/205W) FIO Processor Kit	P02525-L21
	28C 2.2GHz 165W	HPE DL380 Gen10 Intel Xeon-Platinum 8276 (2.2GHz/28-core/165W) FIO Processor Kit	P02526-L21
	28C 2.7GHz 205W	HPE DL380 Gen10 Intel Xeon-Platinum 8280 (2.7GHz/28-core/205W) FIO Processor Kit	P02527-L21
	18C 2.6GHz 150W (M-Series)	HPE DL380 Gen10 Intel Xeon-Gold 6240M (2.6GHz/18-core/150W) FIO Processor Kit	P02528-L21

## Configuration Information

22C 2.1GHz 140W (M-Series)	HPE DL380 Gen10 Intel Xeon-Gold 6238M (2.1GHz/22-core/140W) FIO Processor Kit	P02529-L21
10C 2.6GHz 85W (M-Series)	HPE DL380 Gen10 Intel Xeon-Gold 5215M (2.5GHz/10-core/85W) FIO Processor Kit	P02530-L21
24C 2.4GHz 165W (M-Series)	HPE DL380 Gen10 Intel Xeon-Platinum 8260M (2.4GHz/24-core/165W) FIO Processor Kit	P02532-L21
28C 2.2GHz 165W (M-Series)	HPE DL380 Gen10 Intel Xeon-Platinum 8276M (2.2GHz/28-core/165W) FIO Processor Kit	P02534-L21
28C 2.7GHz 205W (M-Series)	HPE DL380 Gen10 Intel Xeon-Platinum 8280M (2.7GHz/28-core/205W) FIO Processor Kit	P02535-L21
12C 3.3GHz 165W	HPE DL380 Gen10 Intel Xeon-Gold 6246 (3.3GHz/12-core/165W) FIO Processor Kit	P15758-L21
<b>Secondary</b>		
8C 2.1GHz 85W	HPE DL380 Gen10 Intel Xeon-Silver 4208 (2.1GHz/8-core/85W) Processor Kit	P02491-B21
10C 2.2GHz 85W	HPE DL380 Gen10 Intel Xeon-Silver 4210 (2.2GHz/10-core/85W) Processor Kit	P02492-B21
12C 2.2GHz 85W	HPE DL380 Gen10 Intel Xeon-Silver 4214 (2.2GHz/12-core/85W) Processor Kit	P02493-B21
8C 2.5GHz 85W	HPE DL380 Gen10 Intel Xeon-Silver 4215 (2.5GHz/8-core/85W) Processor Kit	P02494-B21
16C 2.1GHz 100W	HPE DL380 Gen10 Intel Xeon-Silver 4216 (2.1GHz/16-core/100W) Processor Kit	P02495-B21
10C 2.5GHz 85W	HPE DL380 Gen10 Intel Xeon-Gold 5215 (2.5GHz/10-core/85W) Processor Kit	P02496-B21
8C 3.0GHz 125W	HPE DL380 Gen10 Intel Xeon-Gold 5217 (3.0GHz/8-core/115W) Processor Kit	P02497-B21
16C 2.3GHz 125W	HPE DL380 Gen10 Intel Xeon-Gold 5218 (2.3GHz/16-core/125W) Processor Kit	P02498-B21
18C 2.2GHz 125W	HPE DL380 Gen10 Intel Xeon-Gold 5220 (2.2GHz/18-core/125W) Processor Kit	P02499-B21
12C 2.7GHz 125W	HPE DL380 Gen10 Intel Xeon-Gold 6226 (2.7GHz/12-core/125W) Processor Kit	P02501-B21
20C 2.1GHz 125W	HPE DL380 Gen10 Intel Xeon-Gold 6230 (2.1GHz/20-core/125W) Processor Kit	P02502-B21
8C 3.3GHz 130W	HPE DL380 Gen10 Intel Xeon-Gold 6234 (3.3GHz/8-core/130W) Processor Kit	P02503-B21
22C 2.1GHz 140W	HPE DL380 Gen10 Intel Xeon-Gold 6238 (2.1GHz/22-core/140W) Processor Kit	P02504-B21
18C 2.6GHz 150W	HPE DL380 Gen10 Intel Xeon-Gold 6240 (2.6GHz/18-core/150W) Processor Kit	P02509-B21
16C 2.8GHz 150W	HPE DL380 Gen10 Intel Xeon-Gold 6242 (2.8GHz/16-core/150W) Processor Kit	P02510-B21
8C 3.7GHz 150W	HPE DL380 Gen10 Intel Xeon-Gold 6244 (3.6GHz/8-core/150W) Processor Kit	P02512-B21
20C 2.5GHz 150W	HPE DL380 Gen10 Intel Xeon-Gold 6248 (2.5GHz/20-core/150W) Processor Kit	P02514-B21
24C 2.1GHz 150W	HPE DL380 Gen10 Intel Xeon-Gold 6252 (2.1GHz/24-core/150W) Processor Kit	P02516-B21
18C 3.1GHz 200W	HPE DL380 Gen10 Intel Xeon-Gold 6254 (3.1GHz/18-core/200W) Processor Kit	P02517-B21
16C 2.2GHz 125W	HPE DL380 Gen10 Intel Xeon-Platinum 8253 (2.2GHz/16-core/125W) Processor Kit	P02518-B21
24C 2.4GHz 165W	HPE DL380 Gen10 Intel Xeon-Platinum 8260 (2.4GHz/24-core/165W) Processor Kit	P02521-B21

## Configuration Information

24C 2.9GHz 205W	HPE DL380 Gen10 Intel Xeon-Platinum 8268 (2.9GHz/24-core/205W) Processor Kit	P02524-B21
26C 2.6GHz 205W	HPE DL380 Gen10 Intel Xeon-Platinum 8270 (2.7GHz/26-core/205W) Processor Kit	P02525-B21
28C 2.2GHz 165W	HPE DL380 Gen10 Intel Xeon-Platinum 8276 (2.2GHz/28-core/165W) Processor Kit	P02526-B21
28C 2.7GHz 205W	HPE DL380 Gen10 Intel Xeon-Platinum 8280 (2.7GHz/28-core/205W) Processor Kit	P02527-B21
18C 2.6GHz 150W (M-Series)	HPE DL380 Gen10 Intel Xeon-Gold 6240M (2.6GHz/18-core/150W) Processor Kit	P02528-B21
22C 2.1GHz 140W (M-Series)	HPE DL380 Gen10 Intel Xeon-Gold 6238M (2.1GHz/22-core/140W) Processor Kit	P02529-B21
10C 2.6GHz 85W (M-Series)	HPE DL380 Gen10 Intel Xeon-Gold 5215M (2.5GHz/10-core/85W) Processor Kit	P02530-B21
24C 2.4GHz 165W (M-Series)	HPE DL380 Gen10 Intel Xeon-Platinum 8260M (2.4GHz/24-core/165W) Processor Kit	P02532-B21
28C 2.2GHz 165W (M-Series)	HPE DL380 Gen10 Intel Xeon-Platinum 8276M (2.2GHz/28-core/165W) Processor Kit	P02534-B21
28C 2.7GHz 205W (M-Series)	HPE DL380 Gen10 Intel Xeon-Platinum 8280M (2.7GHz/28-core/205W) Processor Kit	P02535-B21
12C 3.3GHz 165W	HPE DL380 Gen10 Intel Xeon-Gold 6246 (3.3GHz/12-core/165W) Processor Kit	P15758-B21

Action	Type	Details	Description	SKU
Select a memory capacity for the node	DDR4-2666	8x 16GB RDIMMs	HPE SimpliVity 128GB 8 RDIMM Slots Memory Kit	R2G99A
	DDR4-2666	6x 8GB AND 6x 16GB RDIMMs	HPE SimpliVity 144G 12 DIMM Slots Memory Kit	R1Q89A
The appropriate memory and quantity will be included by the configurator	DDR4-2666	12x 16GB RDIMMs	HPE SimpliVity 192G 12 DIMM Slots Memory Kit	R1Q90A
	DDR4-2666	6x 32GB RDIMMs	HPE SimpliVity 192G 6 DIMM Slots Memory Kit	R1Q91A
1 Kit required per CPU	DDR4-2666	6x 32GB AND 6x 8GB RDIMMs	HPE SimpliVity 240G 12 DIMM Slots Memory Kit	R1Q92A
	DDR4-2666	4x 64GB LRDIMMs	HPE SimpliVity 256GB 4 LRDIMM Slots Memory Kit	R2H00A
	DDR4-2666	8x 32GB RDIMMs	HPE SimpliVity 256GB 8 RDIMM Slots Memory Kit	R2H01A
	DDR4-2666	6x 32GB AND 6x 16GB RDIMMs	HPE SimpliVity 288G 12 DIMM Slots Memory Kit	R1Q93A
	DDR4-2666	12x 32GB RDIMMs	HPE SimpliVity 384G 12 DIMM Slots Memory Kit	R1Q94A
	DDR4-2666	6x 64GB LRDIMMs	HPE SimpliVity 384G 6 DIMM Slots Memory Kit	R1Q95A
	DDR4-2666	8x 64GB LRDIMMs	HPE SimpliVity 512GB 8 LRDIMM Slots Memory Kit	R2H02A
	DDR4-2666	6x 128GB LRDIMMs	HPE SimpliVity 768G 6 LRDIMM Slots Memory Kit	R2H03A
	DDR4-2666	12x 64GB LRDIMMs	HPE SimpliVity 768G 12 DIMM Slots Memory Kit	R1Q96A

## Configuration Information

DDR4-2666	12x 128GB LRDIMMs	HPE SimpliVity 1.5TB 12 LRDIMM Slots Memory Kit	R2H04A
DDR4-2933	8x P00920-B21	HPE SimpliVity 128GB (8x16GB) DDR4-2933 Registered Memory Kit	R4C17A
DDR4-2933	6x P00918-B21,6xP00920-B21	HPE SimpliVity 144GB (6x8GB/6x16GB) DDR4-2933 Registered Memory Kit	R4C18A
DDR4-2933	12x P00920-B21	HPE SimpliVity 192GB (12x16GB) DDR4-2933 Registered Memory Kit	R4C19A
DDR4-2933	6x P00924-B21	HPE SimpliVity 192GB (6x32GB) DDR4-2933 Registered Memory Kit	R4C20A
DDR4-2933	6x P00924-B21, 6x P00918-B21	HPE SimpliVity 240GB (6x32GB/6x8GB) DDR4-2933 Registered Memory Kit	R4C21A
DDR4-2933	4x P00930-B21	HPE SimpliVity 256GB (4x64GB) DDR4-2933 Load Reduced Memory Kit	R4C22A
DDR4-2933	8x P00924-B21	HPE SimpliVity 256GB (8x32GB) DDR4-2933 Registered Memory Kit	R4C23A
DDR4-2933	6x P00924-B21, 6x P00922-B21	HPE SimpliVity 288GB (6x32GB/6x16GB) DDR4-2933 Registered Memory Kit	R4C26A
DDR4-2933	12x P00924-B21	HPE SimpliVity 384GB (12x32GB) DDR4-2933 Registered Memory Kit	R4C27A
DDR4-2933	6x P00930-B21	HPE SimpliVity 384GB (6x64GB) DDR4-2933 Load Reduced Memory Kit	R4C28A
DDR4-2933	8x P00930-B21	HPE SimpliVity 512GB (8x64GB) DDR4-2933 Load Reduced Memory Kit	R4C24A
DDR4-2933	6x P11040-B21	HPE SimpliVity 768GB (6x128GB) DDR4-2933 Load Reduced Memory Kit	R4C30A
DDR4-2933	12x P00930-B21	HPE SimpliVity 768GB (12x64GB) DDR4-2933 Load Reduced Memory Kit	R4C29A
DDR4-2933	12x P11040-B21	HPE SimpliVity 1.5TB (12x128GB) DDR4-2933 Load Reduced Memory Kit	R4C25A

## Configuration Information

**NOTE:** For more information go to: <http://www.hpe.com/docs/memory-population-rules>

**NOTE:** DDR4-2933 Memory Kits are only supported with 2nd Generation Intel Xeon Scalable Series Processors and DDR4-2666 Memory Kits are only supported with 1st Generation Intel Xeon Scalable Series Processors

### Storage

Effective capacity varies by environment and is a function of realized deduplication and compression rates. The capacities in this table offer a conservative range based on compression and deduplication rates found in standard, primary storage use cases.

Action	Useable	Description	Part #
Select SSD + HDD storage kit for the node	25TB	HPE SimpliVity 4x1.92TB LFF SSD Kit	R2Z04A
The appropriate OmniStack software will be included by the configurator	20TB	HPE SimpliVity 8x4TB LFF HDD Kit HPE SimpliVity 1.92T SATA MU SFF 4pk SSD HPE SimpliVity 1.2TB SATA SFF 20pk HDD	R2Z01A R4D38A R4D37A

**NOTE:** Usable capacity is the capacity available after RAID and system overheads have been removed, before deduplication and compression is applied

### Networking

Action	System Max	Description	Part #
One FlexLOM is required. This is in addition to the standard 4 port 1GbE LOM included in the base node	1	HPE Ethernet 1Gb 4-port 331FLR Adapter	629135-B22
	1	HPE Ethernet 1Gb 4-port 366FLR Adapter	665240-B21
	1	HPE FlexFabric 10Gb 2-port 533FLR-T Adapter	700759-B21
	1	HPE FlexFabric 10Gb 2-port 534FLR-SFP+ Adapter	700751-B21
	1	HPE FlexFabric 10Gb 4-port 536FLR-T Adapter	764302-B21
	1	HPE Ethernet 10/25Gb 2-port 631FLR-SFP28 Adapter	817709-B21
	1	HPE Ethernet 10/25Gb 2-port 640FLR-SFP28 Adapter	817749-B21

### PCIe Adapter

Action	System Max	Description	Part #
Optional PCIe Adapters can be added if slots are available. Additional PCIe slots are available in the case of dual CPU with secondary riser	5	HPE Ethernet 1Gb 4-port 331T Adapter	647594-B21
	5	HPE Ethernet 1Gb 4-port 366T Adapter	811546-B21
	5	HPE Ethernet 10Gb 2-port 530SFP Adapter	652503-B21
	5	HPE Ethernet 10Gb 2-port 530T Adapter	656596-B21
	5	HPE Ethernet 10/25Gb 2-port 621SFP28 Adapter	867328-B21
	5	HPE Ethernet 10/25Gb 2-port 631SFP28 Adapter	817718-B21
	5	HPE Ethernet 10/25Gb 2-port 640SFP28 Adapter	817753-B21
	5	HPE Ethernet 1Gb 4-port 331T Adapter	647594-B21

### Optional Fibre Channel HBA cards

Action	System Max	Description	Part #
Optional FC HBAs may be added if slots are available	5	HPE StoreFabric SN1100Q 16Gb Dual Port Fibre Channel Host Bus Adapter	P9D94A
	5	HPE StoreFabric SN1600Q 32Gb Dual Port Fibre Channel Host Bus Adapter	P9M76A

**NOTE:** Additional network cables and transceivers are available in the Aruba and DataCenter Networking menus.

**NOTE:** Information on interoperability between network adapters, transceivers, and cables is available in network adapter QuickSpecs.

## Configuration Information

### Power Supplies

Action	Description	Part #
Two power supplies are required.	HPE 800W Flex Slot Platinum Hot Plug Low Halogen Power Supply Kit	865414-B21
	HPE 800W Flex Slot Universal Hot Plug Low Halogen Power Supply Kit	865428-B21
	HPE 800W Flex Slot -48VDC Hot Plug Low Halogen Power Supply Kit	865434-B21
	HPE 800W Flex Slot Titanium Hot Plug Low Halogen Power Supply Kit	865438-B21
	HPE 1600W Flex Slot Platinum Hot Plug Low Halogen Power Supply Kit	830272-B21

**NOTE:** The power supply requirement can vary based configuration and environment. 800W Power Supply is only supported with specific configurations. Please refer to HPE Power Advisor for proper power sizing.

[https://support.hpe.com/hpsc/doc/public/display?docId=emr\\_na-c01510445](https://support.hpe.com/hpsc/doc/public/display?docId=emr_na-c01510445)

**NOTE:** All configured nodes ship with a standard 6-foot IEC C-13/C-14 jumper cord (A0K02A). This jumper cord is also included with each standard AC power supply option kit. If a different power cord is required, please check the ProLiant Power Cables web page. <https://h20195.www2.hpe.com/v2/getpdf.aspx/4AA6-6836ENW.pdf>

### Additional Server Options

Action	Description	Part #
	HPE DL3XX Gen10 Rear Serial Cable and Enablement Kit	873770-B21
	HPE 2U Large Form Factor Ball Bearing Rail Kit	720864-B21
	HPE 2U Cable Management Arm for Ball Bearing Rail Kit	720865-B21
	HPE 2U Large Form Factor Easy Install Rail Kit	733662-B21
	HPE 2U Cable Management Arm for Easy Install Rail Kit	733664-B21

### HPE OmniStack Software

Action	Description	Part #
Based on the number of CPUs in the node, the appropriate software will be included by the configurator.	HPE SimpliVity 380 H OmniStack 1 Processor 25TB Software	R2Z79A
	HPE SimpliVity 380 H 2 Processors 25TB Software	R2Z80A
	HPE SimpliVity 380 H 1P 20TB SW	R4D19A
	HPE SimpliVity 380 H 2P 20TB SW	R4D20A

### VMware Software

#### vSphere

Action	Description	Part #
A valid VMware vSphere license is required for each CPU to complete deployment.	VMware vSphere Remote Office Branch Office Standard 25VM 3yr E-LTU	P9A82AAE
	VMware vSphere Remote Office Branch Office Standard 25VM 5yr E-LTU	P9A83AAE
	VMware vSphere Remote Office Branch Office Advanced 25VM 3yr E-LTU	P9A85AAE
	VMware vSphere Remote Office Branch Office Advanced 25VM 5yr E-LTU	P9A86AAE
If an order is placed without VMware licenses, the user agrees to supply the necessary license.	VMware vSphere Standard 1 Processor 3yr Software	BD711A
	VMware vSphere Standard 1 Processor 3yr E-LTU	BD711AAE
	VMware vSphere Enterprise Plus 1 Processor 3yr Software	BD715A
	VMware vSphere Enterprise Plus 1 Processor 3yr E-LTU	BD715AAE
	VMware vSphere Standard 1 Processor 5yr Software	BD512A
	VMware vSphere Standard 1 Processor 5yr E-LTU	BD512AAE
	VMware vSphere Enterprise Plus 1 Processor 5yr Software	BD514A
VMware vSphere Enterprise Plus 1 Processor 5yr E-LTU	BD514AAE	

**NOTE:** The HPE SimpliVity 380 supports VMware vSphere 6.5 and 6.7

**NOTE:** For VMware and HW compatibility, please see the interoperability guide [HPE SimpliVity OmniStack Interoperability Guide](#) or [www.hpe.com/docs/simplivity-library](http://www.hpe.com/docs/simplivity-library)

**NOTE:** HPE SimpliVity 380 Gen10 for VMware vSphere requires valid VMware vSphere and vCenter licenses. VMware licenses can only be removed from the order if it is confirmed that the end-customer has valid licenses in place (Enterprise License Agreement (ELA), vCloud Air Partner or unused Enterprise Purchasing Program tokens).

## Configuration Information

**NOTE:** Purchasing VMware licenses from Hewlett Packard Enterprise allows Hewlett Packard Enterprise to be the single point of contact for the entire solution inclusive of the virtualization software and is recommended. When the VMware license is not included on the order the solution level support experience is impacted.

---

### HPE Integrated Lights Out Advanced Software (iLO Advanced)

Action	Description	Part #
The HPE iLO Advanced license is required	HPE iLO Advanced 1-server License with 3yr Support on iLO Licensed Features	BD505A
	HPE iLO Advanced Flexible Quantity License with 3yr Support on iLO Licensed Features	BD506A
	HPE iLO Advanced AKA Tracking License with 3yr Support on iLO Licensed Features	BD507A
	HPE iLO Advanced Electronic License with 3yr Support on iLO Licensed Features	E6U64ABE

## Configuration Information

### HPE SimpliVity 380 Gen10: Storage Expansion/CPU add-on Overview

Use the following steps to expand Storage or perform a CPU add-on for your existing SimpliVity 380 Gen10 node:

Step 1: Start with the Expansion SKU

Step 2: Add the SW license that correlates to either a storage expansion or a CPU add-on configuration

Step 3: Select the hardware options to add either the storage drive kits or additional CPU and memory

Step 4: Select service and support to perform the storage upgrade, migration, install and redeployment

---

#### Step 1: Start with the Expansion Kit SKU

Action	Description	Part #
Select the Expansion SKU	HPE SimpliVity 380 Gen10 Expansion Kit	R1F85A

---

#### Step 2: If Storage expansion is needed, add the SW license from below that correlates to the desired expansion configuration

Action	Description	Part #
Select the appropriate SW license according to the desired storage expansion configuration	HPE SimpliVity 380 1 Processor Small to Medium Storage Upgrade E-LTU	R1F86AAE
	HPE SimpliVity 380 2 Processors Small to Medium Storage Upgrade E-LTU	R1F88AAE
	HPE SimpliVity 380 1 Processor Medium to Large Storage Upgrade E-LTU	R1F87AAE
	HPE SimpliVity 380 2 Processors Medium to Large Storage Upgrade E-LTU	R1F89AAE

If a CPU add-on is needed, choose from the SW license below that correlates to the desired configuration for adding a second CPU

Action	Description	Part #
Select the appropriate SW license if you would like to add a second CPU to an existing 1P SimpliVity 380 node	HPE SimpliVity 380 Additional Processor Extra Small Storage Upgrade E-LTU	R1F90AAE
	HPE SimpliVity 380 Additional Processor Small Storage Upgrade E-LTU	R1F91AAE
	HPE SimpliVity 380 Additional Processor Medium Storage Upgrade E-LTU	R1F92AAE
	HPE SimpliVity 380 Additional Processor Large Storage Upgrade E-LTU	R1F93AAE
	HPE SimpliVity 380 Additional Processor Extra Large Storage Upgrade E-LTU	R1F94AAE

---

#### Step 3: Select the hardware options to add either the storage drive kits or additional CPU and memory

Action	Description	Part #
Select the appropriate storage upgrade kits based on the desired storage expansion configuration	HPE SimpliVity 380 Upgrade to Medium 4000 Series Storage Kit	R1F81A
	HPE SimpliVity 380 Upgrade to Large 4000 Series Storage Kit	R1F82A
	HPE SimpliVity 380 Upgrade to Medium 6000 Series Storage Kit	R1F83A
	HPE SimpliVity 380 Upgrade to Large 6000 Series Storage Kit	R1F84A

Action	Description	Part #
Select these storage option if upgrading from a Small to a Medium configuration	HPE Smart Array P816i-a SR Gen10 (16 Internal Lanes/4GB Cache/SmartCache) 12G SAS Modular Controller	804338-B21
	HPE DL38X Gen10 SFF Box1/2 Cage/Backplane Kit	826691-B21

Action	Description	Part #
Select the appropriate CPU for performing the CPU add-on to your existing 1P SimpliVity 380 nodes	HPE DL380 Gen10 Intel Xeon-Silver 4110 (2.1GHz/8-core/85W) Processor Kit	826846-B21
	HPE DL380 Gen10 Intel Xeon-Silver 4108 (1.8GHz/8-core/85W) Processor Kit	826848-B21
	HPE DL380 Gen10 Intel Xeon-Silver 4114 (2.2GHz/10-core/85W) Processor Kit	826850-B21
	HPE DL380 Gen10 Intel Xeon-Silver 4116 (2.1GHz/12-core/85W) Processor Kit	826852-B21
	HPE DL380 Gen10 Intel Xeon-Gold 5118 (2.3GHz/12-core/105W) Processor Kit	826854-B21
	HPE DL380 Gen10 Intel Xeon-Gold 5120 (2.2GHz/14-core/105W) Processor Kit	826856-B21
	HPE DL380 Gen10 Intel Xeon-Gold 6126 (2.6GHz/12-core/120W) Processor Kit	826862-B21
	HPE DL380 Gen10 Intel Xeon-Gold 6130 (2.1GHz/16-core/120W) Processor Kit	826866-B21
	HPE DL380 Gen10 Intel Xeon-Gold 6132 (2.6GHz/14-core/140W) Processor Kit	826870-B21
	HPE DL380 Gen10 Intel Xeon-Gold 6140 (2.3GHz/18-core/140W) Processor Kit	826878-B21

## Configuration Information

HPE DL380 Gen10 Intel Xeon-Gold 6150 (2.7GHz/18-core/165W) Processor Kit	826884-B21
HPE DL380 Gen10 Intel Xeon-Gold 6154 (3.0GHz/18-core/200W) Processor Kit	826888-B21
HPE DL380 Gen10 Intel Xeon-Gold 5115 (2.4GHz/10-core/85W) Processor Kit	876562-B21
HPE DL380 Gen10 Intel Xeon-Gold 6152 (2.1GHz/22-core/140W) Processor Kit	826886-B21
HPE DL380 Gen10 Intel Xeon-Gold 6134 (3.2GHz/8-core/130W) Processor Kit	826872-B21
HPE DL380 Gen10 Intel Xeon-Gold 6144 (3.5GHz/8-core/150W) Processor Kit	826860-B21
HPE DL380 Gen10 Intel Xeon-Gold 6146 (3.2GHz/12-core/165W) Processor Kit	826868-B21
HPE DL380 Gen10 Intel Xeon-Gold 6136 (3.0GHz/12-core/150W) Processor Kit	826874-B21
HPE DL380 Gen10 Intel Xeon-Platinum 8158 (3.0GHz/12-core/150W) Processor Kit	869090-B21
HPE DL380 Gen10 Intel Xeon-Platinum 8153 (2.0GHz/16-core/125W) Processor Kit	826890-B21
HPE DL380 Gen10 Intel Xeon-Gold 6138 (2.0GHz/20-core/125W) Processor Kit	826876-B21
HPE DL380 Gen10 Intel Xeon-Gold 6148 (2.4GHz/20-core/150W) Processor Kit	826882-B21
HPE DL380 Gen10 Intel Xeon-Platinum 8180 (2.5GHz/28-core/205W) Processor Kit	871619-B21
HPE DL380 Gen10 Intel Xeon-Platinum 8168 (2.7GHz/24-core/205W) Processor Kit	869089-B21
HPE DL380 Gen10 Intel Xeon-Platinum 8165 (2.3GHz/24-core/205W) Processor Kit	879423-B21
HPE DL380 Gen10 Intel Xeon-Platinum 8170 (2.1GHz/26-core/165W) Processor Kit	871617-B21
HPE DL380 Gen10 Intel Xeon-Platinum 8176 (2.1GHz/28-core/165W) Processor Kit	871618-B21
HPE DL380 Gen10 Intel Xeon-Gold 6143 (2.8GHz/16-core/205W) Processor Kit	879424-B21
HPE DL380 Gen10 Intel Xeon-Platinum 8160 (2.1GHz/24-core/150W) Processor Kit	869086-B21
HPE DL380 Gen10 Intel Xeon-Platinum 8164 (2.0GHz/26-core/145W) Processor Kit	869088-B21
HPE DL380 Gen10 Intel Xeon-Gold 5117 (2.0GHz/14-core/105W) Processor Kit	P00756-B21

Action	Description	Part #
Select the Processor Heat Sink	HPE DL380 Gen10 High Performance Heat Sink Kit	826706-B21

Action	Description	Part #
Select the appropriate memory kit for your second CPU	HPE SimpliVity 144G 12 DIMM Slots Memory Kit	R1Q89A
	HPE SimpliVity 192G 12 DIMM Slots Memory Kit	R1Q90A
	HPE SimpliVity 192G 6 DIMM Slots Memory Kit	R1Q91A
	HPE SimpliVity 240G 12 DIMM Slots Memory Kit	R1Q92A
	HPE SimpliVity 288G 12 DIMM Slots Memory Kit	R1Q93A
	HPE SimpliVity 384G 12 DIMM Slots Memory Kit	R1Q94A
	HPE SimpliVity 384G 6 DIMM Slots Memory Kit	R1Q95A
	HPE SimpliVity 768G 12 DIMM Slots Memory Kit	R1Q96A

### Step 4: Select service and support to perform the storage upgrade, migration, install and redeployment

HPE provides a full range of support offers for these products. Foundation Care NBD is the minimum level of support, but Proactive Care, Data center Care and GreenLake are also available.

Contact your local sales representative or channel partner for more details.

Installation services are required for these products. HA124A1#5ZD needs to be ordered in a quantity matching the sum of the software SKUs from Step 2.

---

## Technical Specifications

### Physical Dimensions

2U form factor: 3.44 x 26.75 x 17.54 in (8.73 x 67.94 x 44.54 cm)

---

### End-of-life Management and Recycling

Hewlett-Packard offers end-of-life Hewlett Packard Enterprise product return, trade-in, and recycling programs in many geographic areas. For trade-in information, please go to: <http://www.hp.com/go/green>. To recycle your product, please go to: <http://www.hp.com/go/green> or contact your nearest Hewlett Packard Enterprise sales office. Products returned to Hewlett Packard Enterprise will be recycled, recovered or disposed of in a responsible manner.

The EU WEEE directive (2002/95/EC) requires manufacturers to provide treatment information for each product type for use by treatment facilities. This information (product disassembly instructions) is posted on the Hewlett Packard Enterprise web site at: <http://www.hpe.com/recycle>. These instructions may be used by recyclers and other WEEE treatment facilities as well as Hewlett Packard Enterprise OEM customers who integrate and re-sell Hewlett Packard Enterprise equipment.

## Summary of Changes

Date	Version History	Action	Description of Change
03-Feb-2020	Version 16	Changed	Overview, Standard Features and Configuration Information sections were updated.
04-Nov-2019	Version 15	Changed	Overview, Standard Features, and Configuration Information sections were updated. Added HPE SimpliVity 380 Gen10 G Model with 8x SSD drivers, added new 10TB SW Licenses and features for OmniStack Software v3.7.10
24-Oct-2019	Version 14	Added	Updated HPE SimpliVity 380 Gen10 sections
01-Jul-2019	Version 13	Changed	Overview and Configuration Information sections were updated
03-Jun-2019	Version 12	Changed	Added HPE SimpliVity 380 Gen10 G Model., Standard Features section was updated., obsolete SKUs were removed from the QuickSpecs. Service and Support section was updated.
18-Mar-2019	Version 11	Changed	Configuration Information section was updated.
		Added	SKUs added in Configuration Information: Q8A57A, Q8A58A, Q8A59A, Q8A60A, Q8A61A, Q8A62A, Q8A63A, Q8A64A, Q9J86A, Q9J87A.
		Removed	SKUs deleted in Configuration Information: Q8A57A, Q8A58A, Q8A59A, Q8A60A, Q8A61A, Q8A62A, Q8A63A, Q8A64A, Q9J86A, Q9J87A, Q8A65A, Q8A66A, Q8A67A, Q8A68A, Q8A69A, Q8A70A, Q8A71A, Q8A72A, Q9J88A, Q9J89A.
04-Mar-2019	Version 10	Changed	Overview, Standard Features, and Configuration sections were updated.
		Added	SKUs added in Configuration Information section (additional processors): 871619-L21, 869089-L21, 879423-L21, 871617-L21, 871618-L21, P00756-L21, 879424-L21, 869086-L21, 869088-L21, 871619-B21, 869089-B21, 879423-B21, 871617-B21, 871618-B21, P00756-B21, 879424-B21, 874752-B21, 873645-B21
04-Feb-2019	Version 9	Changed	Overview and Configuration Information sections were updated.
		Added	SKUs added in Configuration Information section: R1F85AAE, R1F86AAE, R1F88AAE, R1F87AAE, R1F89AAE, R1F90AAE, R1F91AAE, R1F92AAE, R1F93AAE, R1F94AAE, R1F81AAE, R1F82AAE, R1F83AAE, R1F84AAE, 804338-B21, 826691-B21, 826846-B21, 826848-B21, 826850-B21, 826852-B21, 826854-B21, 826856-B21, 826862-B21, 826866-B21, 826870-B21, 826878-B21, 826884-B21, 826888-B21, 876562-B21, 826886-B21, 826872-B21, 826860-B21, 826868-B21, 826874-B21, 869090-B21, 826890-B21, 826876-B21, 826882-B21, 826706-B21, R1Q89A, R1Q90A, R1Q91A, R1Q92A, R1Q93A, R1Q94A, R1Q95A, R1Q96A.
07-Jan-2018	Version 8	Changed	Configuration Information section was updated.
		Removed	SKUs were deleted: 871619-L21, 869089-L21, 879423-L21, 874762-L21, 871617-L21, 871618-L21.
05-Nov-2018	Version 7	Changed	Overview, and Configuration Information sections were updated.
		Added	SKUs added in Configuration Information: 764302-B21, Q0V80A.
		Removed	Obsolete SKUs were deleted in Configuration Information: J2R02A, J2R04A
07-May-2018	Version 6	Added	Standard Features and Configuration Information sections were updated.
05-Mar-2018	Version 5	Changed	Overview, Standard Features and Configuration Information sections were updated.
		Added	SKUs were added in Configuration Information section: 826872-B21, 826872-L21, 874762-B21, 874762-L21, Q9J90A, 700759-B21, 817749-B21, Q8A61A, Q8A62A, Q8A63A, Q8A64A, Q9J86A, Q9J87A, Q8A69A, Q8A70A, Q8A71A, Q8A72A, Q9J88A, Q9J89A.
04-Dec-2017	Version 4	Changed	Standard Features, Configuration Information, Service and Support, and Technical Specifications sections were updated.
		Added	SKUs were added in Configuration Information: 874762-L21, Q8D94A, Q5V86A, Q5V87A, Q5V88A, 811546-B21.
06-Nov-2017	Version 3	Changed	Changes made to the document
02-Oct-2017	Version 2	Changed	Changes made to the entire document
25-Sept-2017	Version 1	New	QuickSpecs created.

## Summary of Changes



**Sign up for updates**

© Copyright 2020 Hewlett Packard Enterprise Development LP. The information contained herein is subject to change without notice. The only warranties for Hewlett Packard Enterprise products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. Hewlett Packard Enterprise shall not be liable for technical or editorial errors or omissions contained herein.

Microsoft and Windows NT are US registered trademarks of Microsoft Corporation. Intel is a US registered trademark of Intel Corporation. Unix is a registered trademark of The Open Group.

a00021989enw - 16060 - Worldwide - V16 - 03-February-2020

