

PowerChute™ Network Shutdown v5.1

Operating System, Processor, JRE and Browser Compatibility Chart

OPERATING SYSTEM	LICENSE REQUIRED	VERSION	Edge	Firefox	Chrome
Dell® VxRail (see Note 3)	Yes	VxRail 7.0.482 , ESXi 7.0 U3 (VCSA 7.0 U3)	✓	✓	✓
		VxRail 8.0.101 , ESXi 8.0 U1 (VCSA 8.0 U1)	✓	✓	✓
Nutanix® (see Note 4)	Yes	AHV - AOS 6.5 LTS	✓	✓	✓
		ESXi - AOS 6.5.5 LTS , ESXi 7.0 U3 , 6.5.3.5 LTS , ESXi 7.0 U3 (VCSA 7.0 U3)	✓	✓	✓
Cisco® HyperFlex	Yes	Cisco HyperFlex 4.0(2f) , ESXi 7.0 U3	✓	✓	✓
HPE® SimpliVity	Yes	HPE SimpliVity Omnistack 4.1.0 (ESXi 7.0 U3, vCenter 7.0 U3)	✓	✓	✓
		HPE SimpliVity Omnistack 5.0.0 (ESXi 8.0 U2, vCenter 8.0 U2c)	✓	✓	✓
VMware® ESXi	Unmanaged Host Shutdown - No Managed Host/VM Shutdown - Yes	VMware ESXi 8.0 U3 (VCSA 8.0 U3), 8.0 U2 (VCSA 8.0 U2), 7.0 U3 (VCSA 7.0 U3)	✓	✓	✓
VMware® vSAN	Yes	VMware vSAN ESXi 8.0 U2 (vCenter 8.0 U2), 8.0 U1 (vCenter 8.0 U1)	✓	✓	✓
Microsoft® SCVMM	Yes	Windows® Hyper-V Server 2022 GUI	✓	✓	✓
Microsoft® Hyper-V	Unmanaged Host Shutdown - No Managed Host/VM Shutdown - Yes	Windows® Hyper-V Server Standard 2019	✓	✓	✓
Azure® Stack HCI	Yes	Azure® Stack HCI 22H2	✓	✓	✓
Windows® Server 2025	No	Windows® Server 2025 Datacenter, Standard (see Note 4)	✓	✓	✓
Windows® Server 2022	No	Windows® Server 2022 Datacenter, Standard (see Note 4)	✓	✓	✓
Windows® Server 2019	No	Windows® Server 2019 Datacenter, Essentials (see Note 4)	✓	✓	✓
Windows® 11	No	Windows® 11	✓	✓	✓
Windows® 10	No	Windows® 10	✓	✓	✓
Red Hat® Enterprise Linux®	No	Red Hat® Enterprise Linux 9, 8 (see Note 4)		✓	✓
Ubuntu® Linux®	No	Ubuntu® Linux Server 22.04.1 LTS		✓	✓
SuSE® Linux ®	No	SuSE® Linux Enterprise Server 15 SP5, SP4		✓	✓
Debian® Linux®	No	Debian® Linux® 11.5		✓	✓
Oracle® Linux®	No	Oracle® Linux® 9.3		✓	✓

Note 1: Please note APC do not support the free version of VMware ESXi. A VMware license is required. Please refer to Knowledge Base Answer ID #FA159705 at www.apc.com/support for further information.

Note 2: Supported with latest versions of Chrome, Firefox and Edge

Note 3: Dell VxRail is supported only with Network Management Card 3, with Smart-UPS firmware (SU) v2.2+, Smart-UPS Ultra v2.5+, Symmetra-LX (SY) v2.5+, Symmetra PX, PX2 v2.4+, Galaxy VS v6.101+, Galaxy VL v14.4+, Galaxy VXL v11.31+. Currently not supported with Easy UPS.

Note 4: All editions and minor updates for the major operating system versions published are reviewed and supported as part of our Operating System support policy.

Note 5: PowerChute Network Shutdown v5.1 is compatible with AdoptOpenJDK 11-LTS (<https://adoptium.net/temurin/releases/?version=11>) & OpenJDK 21 (21.0.4+7)

© 2025 Schneider Electric, All Rights Reserved. All Trademarks are owned by Schneider Electric, or its affiliated companies in the U.S and other countries.
All other trademarks are property of their respective owners.

Disclaimer: This information is accurate at the point of creation and may be subject to change

Last Updated: 7th April 2025