

# Combination Lock


## User Manual

Thank you for purchasing our Combo Lock Kit. It helps to protect your valuable devices from being stolen without having to use a key.

**Package Includes:**  
Combo Lock, Cable, Spacer, User Manual

### WARNING


To use the lock or reset the combination, you must set the lock to the correct combination.




#### How to reset the combination:

The starting dials are 0-0-0-0, please complete the following steps to set your own combination.

1. To set your lock to "open" status, turn the dials to the correct combination to align with the combination notching line.



2. Press down the reset button (as shown in the diagram below) using a small tool and do not release it until you finish the next step.




3. Set your combination by turning the dials (ex. 5-5-5-5) and make sure they are aligned with the combination notching line.

1

### IMPORTANT

The lock must be kept in this same status throughout the whole duration of setting your new combination. Failure to do so could cause you to accidentally set a random code instead of your intended code.



4. Release the reset button and now your code setting is completed. If you need to reset the combination, please repeat steps 1-4. Please remember to write down the combination you set.

#### Testing the Combination

Before you connect the combo lock to your device:

1. Turn the dials to random numbers.
2. Turn the dials to the correct numbers that you set as your combination and align them with the combination notching line.
3. Check if the opening button can be turned freely.

#### Using the Right Spacer

Due to the variation in the size of the security slots on various devices, you may find that there is some slack between the combo lock and the device. We provide 3 different sizes of spacers: 0.5mm, 1.0mm, 1.5mm.



1. Insert your lock into the device. Pull the lock away from the device and observe for excessive gaps.
2. Try each of the spacers to determine which one fits your device. Upon determining which one you are going to use, remove the adhesive strip from the back and put the spacer on the lock.



2

#### How to Use the Combination Lock

Look for a stable and firm object (eg. table, cabinet, etc.) Take the looped end of the cable and wrap it around the selected object.



#### How to Lock

1. Turn the dials using your code and set it to the combination notching line.
2. Turn the opening button to the position "O" and insert the lock to the device's lock slot. The close the opening button to the position "C".
3. Turn the dials at random. The device is now locked.

#### How to Unlock

**Tip:** Do not attempt to remove the lock by force without using the correct combination, or your device will be damaged.


1. Turn the dials using your code and set it to the combination notching line.
2. Turning the opening button to the position "O", you can now pull out the lock from your device.

3

#### Specifications

|                 |                    |
|-----------------|--------------------|
| Size:           | 55mm x 20mm x 18mm |
| Weight:         | 160.4g             |
| Cable Length:   | 2000mm             |
| Cable Diameter: | 5.0mm              |

#### Combination Notching Line



Please make sure the code is aligned with the notching line. And read the combination from left to right.

1. To avoid damaging your device, please do not try to pull out the locking device by force within using the correct combination.
2. Remember to write down the combination that you set. You cannot reset the combination lock if you forget the combination code.
3. ChargeTech reserves the right to amend the specifications, or characters of any product without prior warning.

4

[www.ChargeTech.com](http://www.ChargeTech.com)  
2017 ChargeTech Enterprises, LLC.  
All Rights Reserved.

CE RoHS  
Made in China