

## SD3500v 5Gbps USB 3.0 Dual 2K Docking Station - HDMI/DVI-I/VGA - Windows

Make a Windows Laptop or Convertible Ultra-Productive

K33972US



### Each information

Depth	6.6"
Width	3.3"
Height	9.8"
Gross weight	2.00lb
UPC#	085896339724
Unit quantity	1

### Case information

Depth	13.6"
Width	10.7"
Height	7.7"
Gross weight	8.00lb
UPC#	50085896339729

### Shipping Information

Country of origin	CN
-------------------	----

### Product Description

Ultra-thin laptops and 2-in-1 convertibles like the Microsoft Surface Pro offer great mobile productivity and sleek good looks. But that also means they usually come up short on connectivity ports. As a result, you're constantly plugging and unplugging peripherals. That's where the SD3500v USB 3.0 Universal Docking Station comes in. It turns one USB port into six so you have access to all your peripherals, including keyboard, mouse, printer and external hard drive. And with dual HD video output, you can add two external monitors to boost productivity. The dock's two USB 3.0 ports support super-speed data transfer of up to 5 Gbps.

### Features

- Best For: USB 3.0 Laptops, Ultrabooks & Windows Tablets, and Monitors that support up to 2K
- Connection Technology: USB 3.0 (DisplayLink)
- Compatibility: Windows 7 or above, macOS 10.14
- # of Monitors Supported: 2
- Video Ports: 1 x HDMI v1.2 and 1 x DVI-I (DVI-to-VGA and DVI-to-HDMI supported with included adapters)
- Maximum Resolution Supported: Single Monitor: 1920 x 1200 @ 60Hz and Dual Monitors: 2048 x 1152 @ 60Hz
- DisplayLink driver installation required. Download software from [kensington.com](http://kensington.com) or via Windows update.
- Warranty: Three-year limited warranty
- Optimized for your Windows 11 docking station needs, including support for Snap Layouts and Snap Groups
- Original Apple M1/M2/M3 – Our Hybrid USB-C DisplayLink docking stations are a great alternative if you are looking for multi-monitor support on your original M1/M2/M3 MacBook. NOTE: Newer Apple devices (M1/M2/M3 Max and M1/M2/M3 Pro, etc.) are not impacted and support multiple monitors without issue on Thunderbolt docking stations.

### Specifications

- **Connection Technology** USB-A (DisplayLink)
- **Driverless** No
- **Additional Screen Outputs** 2
- **Video Ports** DVI-I, HDMI, VGA
- **Maximum Resolution** 2K
- **Operating System(s)** macOS, Windows
- **Number of USB Ports** 6
- **USB Fast Charging** No