

# HP USB-C 100W G6 Dock

## Power every desk with the dock that redefines its class

Kickstart your day with less hassle and more hustle. The HP USB-C 100W G6 Dock boots your ecosystem as you arrive, connects instantly<sup>1</sup> via a single USB-C<sup>®</sup> cable, and streamlines your setup with ample ports and seamless, secure connectivity—all while staying up to date with remote manageability.



\*Product image may differ from actual product



### Power up before you sit down

Get to work instantly with HP Quick Connect<sup>1</sup> that wakes your workspace as you approach. The HP USB-C 100W G6 Dock delivers fast, seamless connectivity with ample ports and up to 100W power through a single cable<sup>2</sup> for instant productivity without the clutter.



### Hands-off manageability

Cloud manageability with Poly Lens<sup>3</sup> unlocks hands-off manageability from anywhere. Administer automatic firmware updates anytime and easily monitor telemetry and analytics to optimize workspaces and support users effectively.



HP WOLF SECURITY

### Everything, secured

Prevent potential threats with HP Wolf Security<sup>4</sup>, interlacing HP Sure Start<sup>5</sup> and Zero Trust Framework to provide complete end-to-end security. Work and rest easy knowing everything from the dock to the cloud is protected.

## Sustainability in action

### Built to last

Crafted<sup>6</sup> with replaceable parts to maximize your fleet's lifecycle. Built with a power consumption module to monitor your energy consumption. Delivered in plastic-free packaging<sup>7</sup>.



# HP USB-C 100W G6 Dock

## Featuring

### **More Ports. More Flexibility.**

More ports means more capabilities. With an HDMI 2.1, two DisplayPorts™ 1.4, two USB-C®, and three USB-A ports, you can connect all your devices.<sup>8</sup>

### **Intuitive, compact design**

Stay in the know about device status updates with intuitive LED lighting and on-screen-display notifications. Easily connect to rear-facing ports and declutter your desk with single cable connectivity, all in a compact design.

### **A full suite of manageability tools**

Empower your IT to manage and track your docks by product name, serial number, and MAC Address from anywhere with the time-saving, easy-to-use Electronic Tag (eTag) and HP CMSL management tools.<sup>9</sup>

### **3-year limited warranty**

Get added peace of mind with a 3-year limited warranty that includes technical support, diagnostic services, and hardware replacement.

### **Compatible with myHP**

Enable hardware and software innovations from HP with the myHP application. This single dashboard houses access to settings for your docking station and other devices.<sup>10</sup>



# HP USB-C 100W G6 Dock

## Specifications



|                                   |   |
|-----------------------------------|---|
| Product number                    | 9X3V1UT   |
| Supported platforms               | Tested and supported on select HP commercial PCs. For HP notebook compatibility please visit - <a href="https://pcb.inc.hp.com/webapp/#/!us-en">https://pcb.inc.hp.com/webapp/#/!us-en</a> and search by notebook. Tested and supported on select 3rd party PCs. Contact your local sales representative to learn more.                                       |
| UPC number                        | 198415314055  |
| Port and connectors               | Front:<br>1 USB Type-C® 10Gbps signaling rate (data and 15W USB Power Delivery)<br>Right side:<br>1 USB Type-A 10Gbps signaling rate (charging); 1 nano security lock slot<br>Rear:<br>2 USB Type-A 5Gbps signaling rate (charging); 1 HDMI 2.1; 2 DisplayPort™ 1.4; 1 RJ-45 (2.5 GbE); 1 USB Type-C® 10Gbps signaling rate (data and 15W USB Power Delivery) |
| Physical security                 | 1 nano security lock slot <sup>13</sup>   |
| Connection type                   | USB Type-C®   |
| Security management               | HP Wolf Security for Business <sup>2</sup> ; HP Sure Start <sup>3</sup> ; System network manageability in any power state (HP with HP);   |
| Certified collaboration software  | DisplayPort™  |
| Power to system                   | Up to 100 W via USB Type-C® (both HP and non-HP host devices)   |
| Power delivery (PD) profiles      | 12V/5A; 15V/5A; 20V/5A; 5V/3A; 9V/3A  |
| Current (max)                     | 6.15 A  |
| Operating voltage                 | 19.5 V  |
| Management software               | Poly Lens (Cloud, Desktop) <sup>9/10</sup>  |
| Manageability features            | HP CMSL<br>Disconnected Firmware updates<br>eTag<br>PXE Boot<br>Wake on LAN (from the Off, Sleep or Hibernation states)<br>MAC address pass-through (from the On, Off, Sleep or Hibernation states)<br>LAN/WLAN switching <sup>18</sup>   |
| Video connectors                  | HDMI; DisplayPort™-out  |
| Resolution (maximum)              | Up to 4K  |
| Resolutions supported             | Multi-function PCs: 1 x 4K (3840 x 2160 @ 120 Hz) <sup>1</sup> , 2 x QHD resolution (2560 x 1440 @ 120 Hz) <sup>1</sup> , 3 x FHD (1920 x 1080 @ 120 Hz) <sup>1</sup> ; High-resolution PCs with DisplayPort™ Alt Mode: 1 x 4K (3840 x 2160 @ 120 Hz) <sup>1</sup> , 2 x 4K (3840 x 2160 @ 120 Hz) <sup>1</sup> , 3 x 4K (3840 x 2160 @ 60 Hz) <sup>1</sup>   |
| Refresh rate (maximum)            | 120 Hz  |
| Cable length                      | 1 m   |
| External monitor support          | Up to 3 external displays and 1 PC display or up to 3 external displays   |
| Power button type                 | Mechanical power button with RGB LED indicator to power or wake host system <sup>5</sup>  |
| LED                               | Front LED bar: RGB LED (white, blue, amber, green, red); Power button: RGB LED (white, blue, amber, green, red) <sup>6</sup>  |
| Cable type                        | 1 back USB Type-C® cable to connect to host system (up to 100W USB Power Delivery)  |
| Product color                     | Jet black   |
| Software included                 | myHP; HP Quick Connect <sup>9/11</sup> ;  |
| Drivers included                  | Realtek NIC driver (ARM); Realtek NIC driver (Windows)  |
| Supported operating systems       | Windows 11; Windows 10; macOS; Linux; ThinPro; ChromeOS   |
| Wireless Technology               | WLAN Realtek RTL8721DM 802.11a/b/g/n; Bluetooth®  |
| Warranty                          | HP three-year limited warranty  |
| What's in the box                 | HP USB-C 100W G6 Dock; 120 W power adapter; Product notice; Warranty card   |
| Country of origin                 | China(UUZ, ABZ, ACQ, UUF, ABU, ABJ, ABG, AB2, ABB, ABT, ABO, ACJ, ABY, AR6, AB1); Thailand(UUZ, ABZ, ACQ, UUF, ABU, ABB, ABT, ABY)  |
| Dimensions (W x D x H)            | 12.1 x 12.1 x 5.1 cm  |
| Weight                            | 680 g   |
| Package dimensions (W x D x H)    | 39.6 x 95 x 171 cm  |
| Package weight                    | 1085.5 g  |
| Pallet dimensions (W x D x H)     | 120 x 100 x 14.5 cm   |
| Sustainable Impact specifications | Plastic-free packaging; At least 35% post-consumer recycled plastic; Packaged in at least 35% recycled corrugated material <sup>14/15</sup>   |
| Operating temperature range       |   |
| Non-operating temperature         | -20 to 60°C   |
| Operating altitude                | -15 to 3,048 m;   |
| Non-operating altitude            | -15 to 12,192 m;  |
| Operating humidity range          | 10 to 90% non-condensing  |
| Non-operating humidity range      | 5 to 95% non-condensing   |



# HP USB-C 100W G6 Dock

## Footnotes

### Messaging Footnotes

- <sup>1</sup> HP Quick Connect must be enabled on the PC's BIOS and on the dock. HP Quick Connect is available on select HP G11 Intel and G12 Intel and AMD PCs. Bluetooth required. Not available on TAA versions. Contact your local sales representative to learn more.
- <sup>2</sup> For full data and video capability, the PC must support either: DisplayPort™ alt mode, Thunderbolt™ 3 alt mode, or USB4 through its USB-C® port. Charging and port replication are supported on notebooks that have implemented the USB-C® Power Delivery specifications. HP Quick Connect, Wake-on LAN from warm and cold dock, Wake-on LAN from S4/S5, and MAC Address Pass-Through, S0, S3, S4, S5 warm and cold dock features only function on HP or HP supported notebooks. HP does not provide ethernet and audio drivers on Mac PCs. Power button to turn off or to wake the system depends on implementation of the related and optional Power Delivery specification.
- <sup>3</sup> Poly Lens is a cloud-based device management solution that provides actionable insights and analytics around unified communications endpoints like Poly voice, video, and headset devices and can be sold as a stand-alone service. Internet access is required. Poly Lens App is available for download at <https://www.poly.com/us/en/products/services/cloud/poly-lens/app>.
- <sup>4</sup> HP Wolf Security for Business requires Windows 10 or 11 Pro and higher, includes various HP security features and is available on HP Pro, Elite, RPOS and Workstation products. See product details for included security features.
- <sup>5</sup> Based on HP's internal analysis of docking stations that have auto validating & self healing firmware, Meet NIST 800-173 requirements, the ability to disable the RJ-45 and a BIOS MAPT authorized list. HP Sure Start on HP Thunderbolt and USB-C G6 dock supports firmware integrity verification and recovery during dock start-up and disconnect. It does not include real-time and runtime protections or Microsoft SCCM integration typically found on HP Sure Start in HP notebooks.
- <sup>6</sup> HP Total Test Process testing is not a guarantee of future performance under these test conditions. Damage under the HP Total Test Process test conditions or any accidental damage requires an optional HP Accidental Damage Protection Care Pack.
- <sup>7</sup> HP packaging for this product is reported by suppliers as plastic free. Packaging refers to the primary product box and all materials inside, excluding any additional boxes provided by third parties, bulk packaging, and packaging for accessories and spare parts.
- <sup>8</sup> Comes with power cord.
- <sup>9</sup> Windows Management Instrumentation installation required. Requires Windows 10 or higher.
- <sup>10</sup> Requires Windows 10 or higher.

### Technical Specifications Footnotes

- <sup>1</sup> Requires DisplayPort™ 1.4 support with Display Stream Compression.
- <sup>2</sup> HP Wolf Security for Business requires Windows 10 or 11 Pro and higher, includes various HP security features and is available on HP Pro, Elite, RPOS and Workstation products. See product details for included security features.
- <sup>3</sup> Based on HP's internal analysis of docking stations that have auto validating & self healing firmware, Meet NIST 800-173 requirements, the ability to disable the RJ-45 and a BIOS MAPT authorized list. HP Sure Start on HP Thunderbolt and USB-C G6 dock supports firmware integrity verification and recovery during dock start-up and disconnect. It does not include real-time and runtime protections or Microsoft SCCM integration typically found on HP Sure Start in HP notebooks.
- <sup>4</sup> Operating systems supported: Windows 10 22H2 and up, Win 10 IoT Enterprise LTSC 2021, Windows 11 23H2 and up, ChromeOS M133 and up, Ubuntu Linux 22.04 LTS with 5.15 kernel, ThinPro OS 8.0 and MacOS Sonoma 14. Not all features work with all operating systems, ask your sales representative about compatibility with your PC. Linux, ChromeOS, MacOS, and ThinPro OS testing currently underway and expected to be completed after launch.
- <sup>5</sup> The dock power button may support non-HP notebooks that have implemented USB Power Delivery specification to support Extended Alert messages.
- <sup>6</sup> Please refer to the User Guide for LED light behaviors. The User Guide can be found on <https://support.hp.com/>.
- <sup>7</sup> Your computer might support Wake on LAN from the Off, Sleep or Hibernate States, or only when the computer is On or in Sleep.
- <sup>8</sup> Your computer might support MAC address pass-through on the On, Off, Sleep or Hibernate States, or only when the computer is On or in Sleep. Thunderbolt™ host systems require Thunderbolt™ software (minimum SW17.x). Ethernet drivers need to be installed separately on non-HP Windows systems for headset auto switching functionality. Drivers available on HP website. For Apple PCs, HP does not provide ethernet and audio drivers. Firmware updates on Window-based host systems only. Certain features are not functional on non-HP supported nor non-HP notebooks: • Power button to turn on or wake the system. • Wake on LAN from warm and cold dock. • Wake on LAN from S4/S5. • MAC Address pass-through S0, S3, S4, S5 when connecting an on or off notebook to the dock.
- <sup>9</sup> Feature(s) not available on TAA docks.
- <sup>10</sup> Poly Lens is a cloud-based device management solution that provides actionable insights and analytics around unified communications endpoints like Poly voice, video, headset devices, and select HP docking stations and can be sold as a stand-alone service. Internet access is required. Not available on TAA versions. Visit [lens.poly.com](https://lens.poly.com) to set-up an account.
- <sup>11</sup> HP Quick Connect must be enabled on the PC's BIOS and on the dock. HP Quick Connect is available on select HP G11 Intel and G12 Intel and AMD PCs. Bluetooth® required. Not available on TAA versions. Contact your local sales representative to learn more.
- <sup>12</sup> Video resolution and support is dependent on the maximum capability of the notebook.
- <sup>13</sup> Compatible with the following HP locks: 63B28AA - HP Nano Combination Cable Lock, 63B31AA - HP Essential Nano Combination Cable Lock.
- <sup>14</sup> Recycled plastic content percentage is based on the definition set in the IEEE 1680.1-2018 standard.
- <sup>15</sup> HP packaging for this product is reported by suppliers as plastic free. Packaging refers to the primary product box and all materials inside, excluding any additional boxes provided by third parties, bulk packaging, and packaging for accessories and spare parts.

