





APC Smart-UPS X-Series External Battery Pack Rack/Tower 48V, 864VAh, rackmount, 2U

SMX48RMBP2U

Overview

Lead time Usually Ships within 2 Weeks

Main

Mani	
Main Input Voltage	48 V DC
Product or component type	Battery
number of rack unit	2U
Battery type	Lead-acid battery
Provided equipment	Installation guide Rack mounting brackets
Range of product	Smart-UPS Battery Systems

Batteries & Runtime

Device mounting	Enclosed battery cartridge
Number of battery filled slots	0
Number of battery free slots	0
Number of battery replacement quantity	2
Battery voltage	48 V
Replacement battery	APCRBC115 □

Physical

Colour	Black	
Height	8.9 cm	
Width	43.2 cm	
Depth	49 cm	
Net weight	28.64 kg	
Mounting mode	Rack-mounted	

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	24.6 cm
Package 1 Width	58.9 cm

Package 1 Length	62 cm
Package 1 Weight	35.5 kg
Unit Type of Package 2	PAL
Number of Units in Package 2	8
Package 2 Height	115 cm
Package 2 Width	100 cm
Package 2 Length	120 cm
Package 2 Weight	283.408 kg
SCC14	731304268611

Logistical informations

Country of origin PH

Contractual warranty

Warranty 2 years repair or replace



Green PremiumTM **label** is Schneider Electric's commitment to delivering products with best-inclass environmental performance. Green Premium promises compliance with the latest regulations, transparency on environmental impacts, as well as circular and low-CO₂ products.

Guide to assessing product sustainability is a white paper that clarifies global eco-label standards and how to interpret environmental declarations.

Learn more about Green Premium >

Guide to assess a product's sustainability >







Take-back Transparency RoHS/REACh

Resource performance



Take-Back Program Available

Well-being performance



Mercury Free



Rohs Exemption Information

Yes

Certifications & Standards

Reach Regulation	REACh Declaration
Eu Rohs Directive	Pro-active compliance (Product out of EU RoHS legal scope)
Environmental Disclosure	Product Environmental Profile
Circularity Profile	End of Life Information