

Tripp Lite Estimated Battery Runtime at Various Loads

Model: SMART2200NET

	SMART2200NET Alone	+ 1 BP24V33	+ 2 BP24V33	+ 3 BP24V33	+ 4 BP24V33	+ 5 BP24V33	+ 6 BP24V33	+ 7 BP24V33	+ 8 BP24V33	+ 9 BP24V33	+ 10 BP24V33
MaxWatts	Minutes	Minutes	Minutes	Minutes	Minutes	Minutes	Minutes	Minutes	Minutes	Minutes	Minutes
35	1000+	1000+	1000+	1000+	1000+	1000+	1000+	1000+	1000+	1000+	1000+
70	630	1000+	1000+	1000+	1000+	1000+	1000+	1000+	1000+	1000+	1000+
105	378	840	1000+	1000+	1000+	1000+	1000+	1000+	1000+	1000+	1000+
140	270	630	960	1000+	1000+	1000+	1000+	1000+	1000+	1000+	1000+
175	216	435	780	1000+	1000+	1000+	1000+	1000+	1000+	1000+	1000+
210	163	378	630	840	1000+	1000+	1000+	1000+	1000+	1000+	1000+
245	132	330	465	750	900	1000+	1000+	1000+	1000+	1000+	1000+
280	123	270	408	630	810	960	1000+	1000+	1000+	1000+	1000+
315	101	237	378	810	720	840	1000+	1000+	1000+	1000+	1000+
350	92	216	350	435	630	780	900	1000+	1000+	1000+	1000+
420	73	163	270	378	450	630	750	840	960	1000+	1000+
490	58	132	231	330	396	465	630	750	840	900	1000+
560	50	125	193	270	360	408	480	630	720	810	870
640	43	100	160	234	313	372	414	480	600	690	780
700	39	92	144	216	270	350	390	435	510	630	690
800	32	79	127	168	234	288	355	390	420	480	570
840	30	73	123								
910	27	64	109								
1000	25	58	97								
1050	23	55									
1120	20	50									
1200	19	46									
1260	18	44									
1330	17										
1400	16										
1470	14										
1540	13										
1600	12										

The policy of Tripp Lite is one of continuous improvement.
 Specifications are subject to change without notice.



1111 West 35th Street, Chicago, IL 60609 U.S.A. (773) 869-1234 www.triplite.com