HP LaserJet M209d Printer

Fast, reliable performance. Exceptional value.



Reliable, high-performance black-and-white two-sided printing in an award-winning compact design.²

Increase productivity with this highperformance black-and-white printer in an award-winning compact design.² Experience the fastest two-sided printing in class⁸ plus simplified setup and time-saving features with the HP app.³



This printer is intended to work only with cartridges that have a new or reused HP chip, and it uses dynamic security measures to block cartridges using a non-HP chip. Periodic firmware updates will maintain the effectiveness of these measures and block cartridges that previously worked. A reused HP chip enables the use of reused, remanufactured, and refilled cartridges. More at: http://www.hp.com/learn/ds

Print Speed: Letter: Up to 30 ppm black; First Page Out: As fast as 6.9 sec black

Print Resolution: Black (best): Up to 600 x 600 dpi Standard Connectivity: 1 Hi-Speed USB 2.0 (device) Duty cycle: Monthly (letter): Up to 20,000

Paper Handling: 150-sheet input tray; 100-sheet output tray



Built for fast and reliable printing

- Deliver multipage documents in a flash with the fastest two-sided printing in class.⁸
- Rely on consistent, high-quality prints page after page. Get the quality you expect from an industry leader.
- Easily handle high-volume print jobs and reload paper less often with a 150-sheet capacity paper tray.

Award-winning design for your workspace²

- Save space and reduce clutter with an award-winning compact design.²
- You can fit this Laser Jet almost anywhere. Get projects done quickly with a printer that fits your workspace.

Easy to set up, easy to use

- Get started fast with easy setup guidance from the HP app.¹ Quickly setup and get back to business.
- Help protect the information that matters most. Get security essentials to help maintain privacy and control.
- Easily connect your printer to your computer with the provided USB cable and built-in USB port.
- Easily manage tasks with smart-guided buttons buttons appear only when needed.

Compact and energy efficient design

- Optimize printer energy usage with HP Auto-On/Auto-Off technology.⁴
- Easily recycle your used Original HP Toner Cartridges for free through the HP Planet Partners program.⁵
- This HP Laser Jet meets ecolabel requirements, including ENERGY STAR[®] and Blue Angel.^{6,7}

HP LaserJet M209d Printer Technical specifications

Functions	Print
Print speed black ¹¹ , ⁹ , ¹⁰	First page out: As fast as 6.9 sec; Letter: Up to 30 ppm; 2-sided Letter: Up to 19 ipm; Print speed (Landscape, A5): Up to 29 ppm
Print resolution	Black (best): Up to 600 x 600 dpi
Print technology	Laser
Print cartridges number	1 (black)
Standard print languages	PCLmS; URF; PWG
Printer smart software features ^{2,3}	Automatic duplex printing, HP Auto-On/Auto-Off, HP App
Printer management	HP Printer Assistant (UDC); HP Device Toolbox
Standard connectivity	1 Hi-Speed USB 2.0 (device)
Memory	Standard: 64 MB; Maximum: 64 MB
Processor speed	500 MHz
Duty cycle ¹²	Monthly, letter: Up to 20,000; Monthly, A4: Up to 20,000
Recommended monthly page volume ¹³	200 to 2,000
Paper handling	Input Capacities: Up to 150 sheets Up to 10 envelopes Output Capacities: Up to 100 sheets; Up to 10 envelopes Duplex Options: Automatic (standard) Standard paper trays: 1

Media types supported	Paper (laser, plain, rough, vellum), envelopes, labels, cardstock, postcard
Media weight supported	16 to 43 lb
Media sizes supported	Letter, legal, executive, envelopes
Media Sizes Custom	4 x 6 to 8.5 x 14 in
Product dimensions	W x d x h: 13.98 x 11 x 8.07 in / 355 x 279.5 x 205 mm; Maximum: 13.98 x 16.80 x 10.43 in / 355 x 426.5 x 265 mm
Product weight	12.35 lb / 5.6 kg
What's in the box ¹	8J9LOF HP LaserJet M209d; Preinstalled HP Black Original LaserJet Toner Cartridge; Dust cover; Power Cord; Reference Guide; Setup Poster; Regulatory Flyer; USB cable.
Page yield (set-up/inbox cartridges) ⁷	In box cartridge yields ~700 black pages based on ISO/IEC 19752 and continuous printing. Actual yields vary considerably based on images printed and other factors. For details see: https://www.hp.com/go/toneryield . Pages may vary based on customer printing conditions and usage.
Replacement supplies ⁶	HP 134A Original Black LaserJet Toner Cartridge, W1340A (~1100); HP 134X Original Black LaserJet Toner Cartridge, W1340X (~2400)
Supplies	W1340A HP 134A Black Original LaserJet Toner Cartridge ; W1340X HP 134X High Yield Black Original LaserJet Toner Cartridge
Warranty features	One-year limited warranty
Ecolabels	Blue Angel; ENERGY STAR [®] certified
Energy star certified	Yes
Blue Angel Compliance	Yes, Blue Angel DE-UZ 219—only ensured when using Original HP supplies
Sustainable impact specifications	Mercury free
Control panel	Button LED
Software included	No CD inbox (except Indonesia and China Gov) Downloadable Software from hp.com or 123.hp.com #CD include HP Software Installer, Uninstaller, printer driver and other essential tools.
Compatible operating systems ¹⁴	Windows 11; Windows 10; macOS 12 Monterey; macOS 13 Ventura; macOS 14 Sonoma; macOS 15 Sequoia; Linux
Compatible network operating systems	Windows 11; Windows Server; macOS 15 Sequoia; Linux
Minimum system requirements	PC: Microsoft® Windows® 11, 10: 32-bit or 64-bit, 2 GB available hard disk space, Internet connection, Microsoft® Internet Explorer; USB Port; Mac: macOS v14 Sonoma; macOS v13 Ventura; macOS v12 Monterey; 2 GB HD; Internet required; USB
Power ^{4, 5}	Power supply type: Internal; Power requirements: 110-volt input voltage: 110 to 127 VAC (+/-109k), 60 Hz/50 Hz, 4.6 A; 220-volt input voltage: 220 to 240 VAC (+/-109k), 60 Hz/50 Hz, 2.7 A; Power consumption: 420 watts (active printing), 2.0 watts (ready), 0.5 watts (sleep), 0.5 watts (Auto Off/Wake on USB, enabled at shipment), 0.04 watts (Auto-off/Manual-on), 0.04 (Manual Off); Typical electricity consumption (TEC) number ⁶ : 0.273 kWh/Week (Energy Star)
Acoustics ⁸	Acoustic power emissions: 6.7 B(A)
Operating environment	Operating temperature range: 59 to 90.5° F / 15 to 32.5° C; Recommended
	operating temperature: 63.5 to 77^{e} F / 17.5 to 25^{e} C; Storage temperature range: .4 to 140^{e} F / .20 to 60° C; Non-operating humidity range: 10 to 90% RH, Operating humidity range: 10 to 80% RH; Recommended humidity operating range: 30 to 70% RH
HP Service and Support options	range: -4 to 140°F /-20 to 60°C; Non-operating humidity range: 10 to 90% RH Operating humidity range: 10 to 80% RH; Recommended humidity operating range: 30 to 70% RH U6M41E HP 2 year Onsite Exchange HW support for Consumer LaserJet Mid
HP Service and Support options	range: -4 to 140°F / -20 to 60°C; Non-operating humidity range: 10 to 90% RH; Operating humidity range: 10 to 80% RH; Recommended humidity operating range: 30 to 70% RH U6M41E HP 2 year Onsite Exchange HW support for Consumer LaserJet Mid printer; U6M42E HP 3 year Cnsite Exchange HW support for Consumer LaserJet Mid printer; U617E HP 2 year Care Pack w/Next Day Exchange for LaserJet Printers; U6087E HP 3 year Care Pack w/Next Day Exchange for LaserJet Printers; U6087E HP 3 year Care Pack w/Next Day Exchange for LaserJet Printers; U620E HP 3 year Care Pack UNext Day Exchange for LaserJet Printers; U620E HP 3 year Care Pack UNext Day Exchange for LaserJet Printers; U620E HP 3 year Next Business Day Advance Exchange HW support for Consumer LaserJet Mid printer; U622E HP 3 year Next Business Day

Learn more at hp.com

¹ For yield information on the cartridge included with your printer, see https://www.hp.com/go/toneryield. Yield values measured in accordance with ISO/IEC 19752 and continuous printing. Actual yields vary considerably based on images printed and other factors. ² HP Auto-On/Auto-Off Technology capabilities subject to printer and settings; may require a firmware upgrade. ³ Requires HP app download available at https://www.hp.com/go/mobileprinting . Certain features are available in English language only, and may vary by printer model/country, and between desktop/mobile applications. HP reserves the right to introduce charges for use of functionality facilitated by the HP app. Internet access required and may not be available in all countries. HP accountries are values on the country/region where the printer is sold. Do not corvert operating voltages. This will damage the printer and void the product warranty. Power consumption values typically based on measurement of 115V device. ⁹ Power requirements are based on the country/region where the printer is sold. Do not corvert operating voltages. This will damage the printer and void the product warranty. Fundy Star Voltage to measurement of 115V device. ⁹ Power requirements are based on the country/region where the printer is sold. Do not corvert operating voltages. This well beside voltage to printed and other factors. For details see https://www.hp.com/go/interclaims. Exact speed varies depending on the system configuration, software application, driver, and document complexity. ¹⁰ Measured using ISO/IEC 24734 Feature Performance Test, excludes first set of test documents. For more informations see https://www.hp.com/go/interclaims. Exact speed varies depending on the system configuration, software application, driver, and document complexity. ¹⁰ Measured in Measured using ISO/IEC 14732 For more informations are https://www.hp.com/go/interclaims. Exact speed varies depending on the system configuration, software application, driver, and document com

