

2-Port PCI Express FireWire Card - PCIe FireWire 1394a Adapter

Product ID: PEX1394A2V2



The PEX1394A2V 2-Port PCI Express FireWire Card lets you add two FireWire 400 ports to your desktop PC. This TAA compliant product adheres to the requirements of the US Federal Trade Agreements Act (TAA), allowing government GSA Schedule purchases.

Future Proof

Add FireWire to the latest computers with PCI Express slots. Keep using your legacy devices that would not otherwise be compatible with new computers. This allows you to connect IEEE 1394A FireWire devices such as digital cameras, external hard drives, DV camcorders, printers and more

www.startech.com 1 800 265 1844



Data Sheet

Wide Compatibility

For broad compatibility, the PCIE firewire adapter is natively supported in Windows® with no additional drivers required. The 2 port PCI Express 1394a Firewire Card comes equipped with a standard profile bracket and includes a low-profile/half-height bracket for installation in small form-factor computers. PCI Express to Firewire adapter is also compatible with macOS 10.10 through 10.13.

The Choice of IT Pros Since 1985

StarTech.com conducts thorough compatibility and performance testing on all our products to ensure we are meeting or exceeding industry standards and providing high-quality products to IT Professionals. Our local StarTech.com Technical Advisors have broad product expertise and work directly with our StarTech.com Engineers to provide support for our customers both pre and post-sales.

PEX1394A2V2 is backed by a StarTech.com 2-year warranty and free, lifetime technical support.

www.startech.com 1 800 265 1844



Data Sheet

Certifications, Reports and Compatibility





⊂€ F©



Applications

- Connect a digital camera to a desktop with a PCI Express slot to download photos and video
- Add a high-speed FireWire port to a desktop/server without any FireWire ports
- Connect a high-speed external hard drive to a PCI Express-enabled system

Features

- Built with a TI 1394 OHCI Compliant Host Controller
- Includes low profile/half-height installation bracket
- Two 6-pin FireWire 400 ports, each with transfer rates up to 400Mbps
- Plug-and-Play compatible
- PCI Express 1.1 and IEEE provisions 1394a-2000 Std, 1394-1995 Std compliant



Hard-to-find made easy*

Data Sheet

	Warranty	Lifetime
Hardware	Bus Type	PCI Express
	Card Type	Standard Profile (LP bracket incl.)
	Interface	FireWire 400 (1394a)
	Port Style	Integrated on Card
	Ports	2
Performance	Maximum Data Transfer Rate	400 Mbps
	Type and Rate	FireWire 400 IEEE-1394a - 400 Mbit/s
Connector(s)	Connector Type(s)	1 - PCI Express x1
	External Ports	2 - FireWire 400 (6 pin, IEEE 1394a)
Software	OS Compatibility	Windows® 2000, XP, Vista, 7, 8, 8.1, 10 Windows Server® 2003
Special Notes / Requirements	System and Cable Requirements	Available PCI Express Slot
Environmental	Operating Temperature	0°C to 70°C (32°F to 158°F)
	Storage Temperature	-20°C to 80°C (-4°F to 176°F)
Physical Characteristics	Color	Green
	Product Height	17.800
	Product Length	89.000
	Product Width	68.000
	Weight of Product	49.000
Packaging Information	Package Height	30.000
	Package Length	142.000
	Package Width	170.000
	Shipping (Package) Weight	117.000
What's in the Box	Included in Package	1 - PCI Express FireWire Card
		1 - Full Profile Bracket (pre-installed)
		1 - Low Profile Bracket
		1 - Quick-Start Guide

Product appearance and specifications are subject to change without notice.

www.startech.com 1 800 265 1844