

GUS432CA1KIT

2x4 USB 3.0 Peripheral Sharing Switch with USB-C Adapter



- Share 4 separate USB 3.0 devices between 2 computers
- Connect a USB-C PC or Mac via the included USB-A to USB-C adapter cable.
- Easy push-button switching between computers
- Supports data transfer rates of up to 5 Gbps
- LED indicates which computer is active

Share USB 3.0 Peripherals With Two Computers

IOGEAR's 4x2 USB 3.0 Peripheral Sharing Switch is a convenient way to share four (4) USB devices between two (2) USB-A or USB-C computers. Share a keyboard, mouse, printer, portable hard drive and more with simple push-button switching.

Connect USB-C Computers to Existing Devices

Share your existing USB-A peripheral devices with the newest USB-C-enabled laptop or tablet with the included USB-A to USB-C adapter cable.

Save Space and Expense

The Peripheral Sharing Switch is perfect for small office, and home office users since it not only saves users from purchasing duplicate peripherals, it also creates a space saving, productive work environment.

- Share 4 separate USB 3.0 devices between 2 computers
- Connect a USB-C PC or Mac via the included USB-A to USB-C adapter cable.
- Easy push-button switching between computers
- Supports data transfer rates of up to 5 Gbps
- LED indicates which computer is active
- Features over-current protection
- Connect or remove computers via hot-plugging without powering down
- Connect optional Micro USB cable to support additional power (up to 2.5W via USB 2.0 Port, up to 4.5W via USB 3.0 Port)





Requirements

Package Contents

- For PC Users
 - Windows XP, Windows Vista, Windows 7, Windows 8/8.1, 10
 - Available USB 3.0 port
 - Available USB-C port
 - Chrome Book
 - Linux®, Unix and other USB supported systems¹
 - For MAC Users
 - Mac 8.6 or greater. Requires OS X for USB 3.0 support
 - Available USB 3.0 port
 - Available USB-C port
- 1 x 2x4 USB 3.0 Peripheral Sharing Switch
 - 1 x Quick Start Guide
 - 1 x Warranty Card
 - 1x USB-C to A Adapter (G2LU3CAF10-SIL)

¹Additional drivers and support may be needed

Specifications

Function	GUS432CA1KIT	Dimensions	GUS432CA1KIT
Computer Connections		Unit Dimensions	
Direct	2	Height	3.75" (9.53cm)
Port Selection	Remote control selector button	Depth	1.06" (2.69cm)
LEDs		Length	3.75" (9.53cm)
Port Status	White	Unit Package Dimensions	
Switches		Width	6.5" (16.51cm)
Port Selection	Remote Console Selector Button x 1	Height	9.25" (23.50cm)
Connectors		Depth	2.875" (7.30cm)
Computer Side	USB 3.0 Type B x 2	Master Carton	
USB	USB 3.0 Type A x 4	Width	10" (254mm)
Power	USB Type Micro B (optional)	Height	7" (177.8mm)
Operating Temperature	32 ~ 104F (0 ~ 40C)	Depth	4" (101.6mm)
Storage Temperature	-4 ~ 140F (-20 ~ 60C)	Master Carton Qty.	1
Humidity	0~80%	Weight	
Cable Length	54" (137.16cm)	Master Carton Wt.	1.2lb (.54kg)
Cable Type	USB 3.0 Type B to A x 4	Unit Pack Wt.	0.95 lb (0.42 kg)
Power Consumption	DC 5V, 1.43W	Unit Wt.	0.27lb (0.124kg)