## **Lenovo V510z Platform Specifications**

Processor	Intel® Pentium® or 6th Generation Intel Core™ i3 / i5 / i7 Processor						Manageability	None	
	Processor	Cores /	Frequency	Cache	Memory Support	Integrated	Security chip	None	
			Base/Max(GHz)		(Up to)	Graphics	Security features	<ul> <li>Security slot (in rear for attachment of optional Kensington® MicroSaver® cable;</li> <li>Boot sequence control</li> </ul>	
	Celeron G3900T	2/2	2.6 G	2 MB	DDR4-2133	HD 510		Kensington lock also locks back cover)   Boot without keyboard and mouse	
	Pentium G4400T	2/2	2.9 G	3 MB	DDR4-2133	HD 510		<ul> <li>Smart USB protection, allows keyboard/</li> <li>Individual USB port disablement</li> </ul>	
	Core i3-6100T	2/4	3.2 G	3 MB 6 MB	DDR4-2133	HD 530		mouse only, blocks all storage devices	
	Core i5-6400T Core i7-6700T	4/4	2.2 G / 2.8 G 2.8 G / 3.6 G	8 MB	DDR4-2133 DDR4-2133	HD 530 HD 530	Keyboard	Some: Lenovo Slim USB Keyboard (USB connector), black	
	Core i3-7100T	2/4	3.4G	3 MB	DDR4-2133 DDR4-2400	HD 630	Mouse	Some: Ultraslim Plus Wireless Keyboard (2.4GHz via USB receiver), black Some: Optical USB Mouse, black, Lenovo logo	
	Core i5-7400T	4/4	2.4G / 3.0G	6 MB	DDR4-2400	HD 630		Some: Ultraslim Plus Wireless Mouse (2.4GHz via USB receiver), black	
N. 4			1				Mechanical	Black and business grey color	
Memory	32GB max, DDR4-2400*, two 260-pin SO-DIMM sockets, dual-channel capable  * System clocks down for the processors with lower memory controller							Support VESA mount (100mm)     Toolless back cover, memory, M.2 SSD, optical removal	
Disk	Some: SATA 6.0Gb/s, 2.5" Wide, 5400 rpm or 7200 rpm Some: M.2 Solid State Drive (SSD) / PCle interface, NVMe Some: DVD burner, SATA 1.5Gb/s, 9.5mm high 6-in-1 media card reader							Dimensions (WxDxH)   Max weight   Adjustments   (lb / kg)	
Optical Media reader								Without stand: 20.7 X 1.9 X 13.3 (inch); 525.5 X 49.1 X 338.8 (mm) 11.0 / 5.00 N/A	
Graphics	work as standalone monitor via HDMI in					, DirectX <sup>®</sup> 12,	,	With Monitor stand: 20.7 X 9.0 X 16.7 (inch); 525.5 X 227.9 X 423.3 (mm) 14.1 / 6.39 Tilt: 24° back, -5° forward Swivel: +/-45°	
Display						ect ratio,		With UltraFlex II stand:       20.7 X 9.4 X 16.2 (inch); 525.5 X 238.6 X 410.4 (mm)       16.7 / 7.58       Tilt: 61° back, -5° forward; Lift: 160mm; Swivel: +/-45°	
AA ISS .						·	Power supply	Some: 90 watts external adapter, autosensing, 88% PSU (for integrated models) Some: 120 watts external adapter, autosensing, 89% PSU (for discrete models)	
Multi-touch Camera	with privacy camera cover						Limited warranty <sup>3</sup>	Some: 1-year or 3-year, depot repair service Some: 1-year or 3-year, limited onsite service For Lenovo service upgrade options, please go to S-TC sheet	
Controls	Some: 1080p IR camera, with dual digital microphone, LED indicator Power on/off button on right side						Preload	Preloaded operating system	
Chipset	Intel H110 Chipset						Tieload	Some: Windows 10 Pro 64-bit	
Rear ports Side ports M.2 card slot	Three USB 2.0, ethernet (RJ-45), HDMI in port, HDMI out port Two USB 3.0, optional card reader, headphone / microphone combo jack (3.5mm) Two M.2 Card slots (one for WLAN, one for M.2 SSD)					ack (3.5mm)		Some: Windows 10 Home 64-bit Some: Windows 7 Professional 64 preinstalled through downgrade rights in Windows 10 Pro 64-bit (not available with 7th Gen Intel processor)  Preloaded applications (only some listed)	
Audio support	High Definition (HD) Audio, Realtek ALC233 / two internal speakers (3W x 2)					3W x 2)		<ul> <li>Lenovo Rescue System</li> <li>Driver and Application Installation</li> <li>Lenovo Solution Center</li> <li>McAfee® LiveSafe™ (30-day trial)</li> <li>Microsoft® Office preloaded; purchase a product key to activate</li> <li>Lenovo Companion</li> </ul>	
WLAN <sup>13</sup>	Some: 11ac wireless, M.2 Card, Realtek RTL8821AE (dual band), Wi-Fi + Bluetooth 4.0 combo adapter, 1x1 Some: 11ac wireless, M.2 Card, Qualcomm Atheros QCA6174 (dual band), Wi-Fi + Bluetooth 4.1 combo adapter, 2x2 Some: 11ac wireless, M.2 Card, Intel Dual Band Wireless-AC 3165,					band),			
	Wi-Fi + Bluetooth 4.0 combo adapter, 1x1  Some: 11ac wireless, M.2 Card, Intel Dual Band Wireless-AC 8260, Wi-Fi + Bluetooth 4.1 combo adapter, 2x2						Environment	ENERGY STAR® 6.1 (Need 85% PSU and Windows OS); ErP Lot 3; GREENGUARD®; RoHS-compliant	
Bluetooth™ Ethernet	Some: Bluetooth 4.0 or 4.1 wireless, integrated in Wi-Fi + Bluetooth combo adapter One gigabit ethernet port, Realtek RTL8111G, Wake on LAN®						Accessories	For compatible accessories, please go to http://www.lenovoquickpick.com/	
See footnotes for	more detailed informa	ation						© Lenovo	

(V510z-Spec) March 2017