

THE DOCUMENT COMPANY
FUJI XEROX



WorkCentre® 3119
Multifunction Laser Printer

print | copy | scan

Smart office for your home

Printer. Copier. Scanner.

Fuji Xerox WorkCentre 3119 is a laser multifunction device that's perfectly scaled for the single user. Enjoy the benefits of high-quality printing, copying, and scanning delivered by one compact, hard-working machine. It fits comfortably on your desktop – and in your budget.



Fuji Xerox Printers



Consolidate assets into one affordable solution with powerful features.

Your personal multifunction

- Fast warm-up and first-copy-out time
- High-quality, black-and-white laser printing and copying at up to 19ppm
- Scan and organise documents with the latest scanning / file management software, Nuance® PaperPort 10.0
- Convert scanned images into text documents you can edit
- Special copy features such as Clone, 2-Up, AutoFit, and ID Card Copy

Big features in a small space

- Access is easy with a device that's small enough to fit on your desktop
- 250-sheet paper tray can handle big jobs
- Gain space with a multi-function that can replace three single-function devices

Best for your budget

- Three robust functions (print, copy, scan) at one price you can afford
- Powers down when not in use, conserving energy
- Durable design that is built to last with a monthly duty cycle of up to 10,000 pages

CONFIGURATIONS

		WorkCentre® 3119
Speed		Up to 19ppm (Letter) / 18ppm (A4)
First-Page-Out Time		As fast as 11 seconds
Duty Cycle		Up to 10,000 pages / month
Paper Handling		
Paper Input	Standard	Platen Bypass Tray: 1 sheet, Size: Custom sizes from 76 x 127mm to A4 Main Tray: 250 sheets, Size: Custom sizes from 76 x 127mm to A4
Paper Output		50 sheets
Print		
Print Resolution		600 x 600dpi
Print Features		Reduce / Enlarge, Up to 16 Pages Per Side, Poster, Fit to Page, Watermark
Copy		
Copy Resolution		Up to 600 x 600dpi
Copy Features		Auto Fit, Clone, ID Card Copy, 2-Up, Poster, Reduce / Enlarge
Scan		Scan to Desktop, Nuance PaperPort® SE 10.0

SPECIFICATIONS

Print

Device Memory: 8MB
Print Drivers: Windows® 98 / Me / Server™ 2000 / XP; Mac; Linux®
Connectivity: USB 2.0
Language Support: GDI

Copy

Reduce / Enlarge
Platen: 50% – 200% in 1% increments
Multiple Copies: Up to 99 copies of multiple page originals

Scan

Compatibility: TWAIN standard
Technology: Direct Connect to PC (USB)

Scan Resolution

Optical Resolution: Up to 600 x 2,400dpi
Interpolated Resolution: Up to 4,800dpi
Pre-scan: 75dpi

Depth: Monochrome Line, Halftone: 1 bit;
Grayscale: 8 bit;
Colour: 24 bit

Scan Drivers: TWAIN and WIA

Media Handling

Bypass Tray: 60gsm – 120gsm
Main Tray: 60gsm – 90gsm
Media Types: Paper, Envelopes, Labels, Transparencies

Operating Environment

Temperature:
Maximum Range: 10°C – 32°C
Recommended Range: 16°C – 30°C
Humidity:
20% – 80%
Recommended Range: 30% – 70%

Electrical

Power: 110V, 2A; 220V, 1A
Power Consumption:
Normal Operation: 225W;
Ready Mode: 70W;
Power Saver Mode: 6W,
ENERGY STAR® Compliant
Sound Power Levels (LWA):
Run: 6.9 (B);
Standby: 4.8 (B)

Physical Dimensions (W x D x H)

409 x 362 x 232mm
Weight: 9.5kg

Supplies

Print Cartridge (CWAA0713): 3,000 pages†
Printer is shipped with 1,000 pages† yield print cartridge

†Approximate yield. Declared yield values in accordance with ISO/IEC 19752 ISO Compliant Toner Yields.

Agency Approvals

UL 60950-1 2003
CE, Nemco EN60950-1:2001



For more information, please contact:



©2006 Fuji Xerox Printers. All rights reserved. Contents of this publication may not be reproduced without permission of Fuji Xerox Printers. Xerox, The Document Company, the stylised X, Phaser®, CentreWare® and PhaseSmart® are registered trademark/ trademarks of Xerox Corporation. All other names mentioned are trademarks of their respective companies. The information in this brochure is subject to change without notice. Errors and omissions excepted. Fuji Xerox Printers practice a policy of continued product development, this means that product specifications may incorporate innovations and/ or enhancements resulting from ongoing research & development (and may vary from those specified in brochures at time of printing). In keeping with normally accepted commercial practices, the purchaser is advised to both confirm product specifications, and satisfy themselves as to product performance and exact configuration (to suit each particular requirement) before purchase. Fuji Xerox Printers will not accept any liability (product related and/ or resulting from product usage) where such diligence has not been performed and the incorrect product has been purchased. 09/06